

Lorawan Ear Tag Communication Protocol_V6.0

1. Upload data example

The hex data uploaded to the eartag is as follows:

AA 06 30 02 36 26 00 60 04 55

2. Protocol Analysis

0xAA: Header

0x06: Protocol version

0x3002: Power supply voltage 3002mV (BCD format)

0x3626: 36.26°C (BCD format)

0x0060: 96 steps (hexadecimal)

0x04: Reporting interval is 4 hours (hexadecimal)

0x55: Package end

3. Example of issuing instructions

The gateway issues the following hex command:

AA 01 55

4. Instruction parsing

0xAA: Header

0x01: Modify the upload time by 1 hour

0x55: Package end



HUNAN HKT TECHNOLOGY CO., LTD.

(Tel) : +86 137-8619-7540

(Email) : sales@hktlora.com

(Web) : www.hktlora.com www.hkttech.com

(Add) : No. 10, Qingshan Road, High-Tech Development Zone,
Changsha, Hunan, China



This manual is for reference only and subject to change without notice. For more information,
please call or visit the website.