Supplemental Material for: The Arrow of Time as Petz Recovery Failure

Sheng-Kai Huang[1,*]
[1] *Independent Researcher*
(Dated: March 8, 2026)

S1. QUANTUM ERASER AS PETZ RECOVERY: EXPLICIT CALCULATION

We provide the complete calculation showing that the quantum eraser phenomenon is precisely the Petz recovery map applied to the partial trace channel.

Setup

Consider a two-path interferometer with which-path detector:

Initial state.—The signal photon enters in a superposition of paths A and B:

$$|\phi\rangle_S = \frac{1}{\sqrt{2}}(|A\rangle + |B\rangle). \tag{1}$$

Entangling interaction.—A which-path detector entangles with the signal:

$$|\psi\rangle_{SE} = \frac{1}{\sqrt{2}}(|A\rangle|d_A\rangle + |B\rangle|d_B\rangle), \tag{2}$$

where $\langle d_A|d_B\rangle = 0$ (perfect which-path detection).

Which-path channel.—The effective noise channel on the signal is:

$$\mathcal{N}(\rho_S) = \mathrm{Tr}_E\big[U(\rho_S \otimes |d_0\rangle\langle d_0|)U^\dagger\big] = \sum_i |i\rangle\langle i|\,\rho_S\,|i\rangle\langle i|, \tag{3}$$

where $i \in \{A, B\}$. This is complete dephasing in the path basis.

Computing the Petz Recovery

We set the reference state on the full system SE:

$$\sigma_{SE} = |\psi\rangle\langle\psi|_{SE}. \tag{4}$$

The channel is $\mathcal{N} = \mathrm{Tr}_E : \mathcal{B}(\mathcal{H}_S \otimes \mathcal{H}_E) \to \mathcal{B}(\mathcal{H}_S)$. We compute:

Step 1: $\mathcal{N}(\sigma_{SE})$.

$$\begin{aligned}\mathcal{N}(\sigma_{SE}) &= \mathrm{Tr}_E\big[|\psi\rangle\langle\psi|_{SE}\big] \\ &= \tfrac{1}{2}\big(|A\rangle\langle A| + |B\rangle\langle B|\big) = \tfrac{1}{2}I_S.\end{aligned} \tag{5}$$

Step 2: $\mathcal{N}(\sigma_{SE})^{-1/2}$.

$$\big(\tfrac{1}{2}I_S\big)^{-1/2} = \sqrt{2}\,I_S. \tag{6}$$

Step 3: The adjoint $\mathcal{N}^\dagger$. For $\mathcal{N} = \mathrm{Tr}_E$, the Hilbert–Schmidt adjoint is defined by $\mathrm{Tr}[\mathcal{N}^\dagger(A)\cdot B] = \mathrm{Tr}[A \cdot \mathcal{N}(B)]$ for all A, B. One verifies $\mathrm{Tr}[(A \otimes I_E)\cdot B] = \mathrm{Tr}[A \cdot \mathrm{Tr}_E(B)]$, so:

$$\mathrm{Tr}_E^\dagger(\rho_S) = \rho_S \otimes I_E. \tag{7}$$

Step 4: Assembling the Petz map.
For input ρ_S:

$$\begin{aligned}\mathcal{R}_{\sigma,\mathrm{Tr}_E}(\rho_S) &= \sigma_{SE}^{1/2}\,\mathrm{Tr}_E^\dagger\big(\sqrt{2}I_S\;\rho_S\;\sqrt{2}I_S\big)\;\sigma_{SE}^{1/2} \\ &= |\psi\rangle\langle\psi|\;\big(2\rho_S \otimes I_E\big)\;|\psi\rangle\langle\psi|.\end{aligned} \tag{8}$$

Note: $\sigma_{SE}^{1/2} = |\psi\rangle\langle\psi|$ since σ_{SE} is a rank-1 projector.
Step 5: Evaluating for $\rho_S = \frac{1}{2}I_S$.
Using orthogonality $\langle d_A|d_B\rangle = 0$:

$$\langle\psi|\big(2\cdot\tfrac{1}{2}I_S \otimes I_E\big)|\psi\rangle = \langle\psi|(I_S \otimes I_E)|\psi\rangle = 1. \tag{9}$$

Therefore, the Petz map is trace-preserving and gives exact recovery:

$$\mathcal{R}_{\sigma,\mathrm{Tr}_E}(\rho_S) = |\psi\rangle\langle\psi|_{SE}. \tag{10}$$

This is exact recovery of the full entangled state, as expected for a pure-state reference with the partial trace channel. The quantum eraser measurement on E (projecting onto $|\pm\rangle = (|d_A\rangle \pm |d_B\rangle)/\sqrt{2}$) then yields:

$$\rho_S^{(+)} = \tfrac{1}{2}(|A\rangle + |B\rangle)(\langle A| + \langle B|) = |\phi^+\rangle\langle\phi^+|, \tag{11}$$

$$\rho_S^{(-)} = \tfrac{1}{2}(|A\rangle - |B\rangle)(\langle A| - \langle B|) = |\phi^-\rangle\langle\phi^-|, \tag{12}$$

each with probability 1/2. Interference is restored. □

S2. SELF-CONTAINED PROOF OF THEOREM 1 (UNIQUENESS)

We provide a self-contained proof following Parzygnat–Buscemi [1], emphasizing the key steps.

The Classical Case

For commutative C^*-algebras (i.e., classical probability), let $p = (p_1, \ldots, p_n)$ be a prior and $N = (N_{j|i})$ a stochastic matrix. Classical Bayes' rule gives:

$$R(N,p)_{i|j} = \frac{p_i\,N_{j|i}}{\sum_k p_k\,N_{j|k}}. \tag{13}$$

This can be written in the "Petz form":

$$R(N,p)(q)_i = p_i^{1/2} \sum_j \frac{N_{j|i}}{(Np)_j^{1/2}} \cdot q_j \cdot \frac{1}{(Np)_j^{1/2}} \cdot p_i^{1/2}. \quad (14)$$

In matrix notation, defining $D_p = \mathrm{diag}(p_1, \ldots, p_n)$:

$$R(N,p) = D_p^{1/2}\, N^T\, D_{Np}^{-1/2}\, (\cdot)\, D_{Np}^{-1/2}\, N\, D_p^{1/2}. \quad (15)$$

This is precisely the Petz map (2) of the main text restricted to diagonal matrices. The uniqueness of Bayes' rule in the classical case is well-known.

Extension to the Quantum Case

The key insight is that axioms (ii) (functoriality) and (iv) (classical limit) *together* uniquely determine the non-commutative extension.

Step 1: Stinespring dilation.—Any CPTP map $\mathcal{N}$ can be written as $\mathcal{N}(\rho) = \mathrm{Tr}_E[V\rho V^\dagger]$ for some isometry $V : \mathcal{H}_A \to \mathcal{H}_B \otimes \mathcal{H}_E$. The isometry V is unique up to unitary on $\mathcal{H}_E$.

Step 2: Factoring through the isometry.—By functoriality axiom (ii), $R(\mathcal{N}, \sigma) = R(\mathrm{Tr}_E, V\sigma V^\dagger) \circ R(\mathcal{V}, \sigma)$, where $\mathcal{V}(\rho) = V\rho V^\dagger$. For the isometric channel $\mathcal{V}$, axioms (i) and (iii) imply $R(\mathcal{V}, \sigma) = \mathcal{V}^{-1}$ (the adjoint $V^\dagger(\cdot)V$). This is because an isometry has a unique left inverse that is CPTP on the range.

Step 3: Reducing to the partial trace.—It remains to determine $R(\mathrm{Tr}_E, \omega)$ for $\omega = V\sigma V^\dagger$. The partial trace is a product of marginalizations over each factor of $\mathcal{H}_E$. By functoriality, $R(\mathrm{Tr}_E, \omega)$ factorizes accordingly.

Step 4: Classical limit forces the structure.—For each factor in the decomposition, axiom (iv) determines the map on the diagonal (classical) part. The off-diagonal (quantum coherence) part is then fixed by the requirement that R be CP (complete positivity). The unique CP extension of the classical Bayesian inverse is the Petz map—this follows from the structure theory of CP maps on matrix algebras.

The detailed argument uses the Choi–Jamiołkowski isomorphism: the Choi matrix of $R(\mathrm{Tr}_E, \omega)$ is uniquely determined by its diagonal blocks (from axiom (iv)) and the requirement of positive semidefiniteness of the Choi matrix (from axiom (i)). The unique positive semidefinite completion is the Choi matrix of $\mathcal{R}_{\omega, \mathrm{Tr}_E}$. □

What Happens When Each Axiom Is Dropped

- *Without (i) [CPTP]:* The map may not be physically realizable (not completely positive).
- *Without (ii) [functoriality]:* Multiple candidates exist, e.g., the "rotated Petz map" [3] $\tilde{R}(\rho) = \sigma^{1/2} U\, \mathcal{N}^\dagger(\cdots)\, U^\dagger \sigma^{1/2}$ for arbitrary unitary U.
- *Without (iii) [normalization]:* One could rescale by an arbitrary positive function of $(\sigma, \mathcal{N})$.
- *Without (iv) [classical limit]:* The "transpose channel" and other candidates remain viable.

S3. DETAILED PROOF OF THEOREM 2 (QEC OPTIMALITY)

Exact Recovery (Theorem 2a)

Let $\mathcal{C}$ be a $[\![n, k, d]\!]$ stabilizer code with projector P, and let $\mathcal{N}(\rho) = \sum_a E_a \rho E_a^\dagger$ with Kraus operators $\{E_a\}$ satisfying the Knill–Laflamme conditions:

$$P E_a^\dagger E_b P = c_{ab}\, P \quad (16)$$

for a Hermitian matrix $C = (c_{ab})$.

Set $\sigma_{\mathcal{C}} = P/\dim \mathcal{C}$. Then for any ρ supported on $\mathcal{C}$:

Step 1: $\mathcal{N}(\sigma_{\mathcal{C}}) = \sum_a E_a (P/\dim \mathcal{C}) E_a^\dagger$.

Step 2: By the KL conditions, for ρ supported on $\mathcal{C}$:

$$D(\rho \| \sigma_{\mathcal{C}}) = D(\mathcal{N}(\rho) \| \mathcal{N}(\sigma_{\mathcal{C}})). \quad (17)$$

This is because the KL conditions ensure that the noise channel $\mathcal{N}$ acts as an isometry on the code space (up to a decoupled environment), preserving all relative entropies.

Step 3: By Petz's sufficiency theorem [2], equality in the DPI implies $\mathcal{R}_{\sigma_{\mathcal{C}}, \mathcal{N}} \circ \mathcal{N} = \mathrm{id}$ on the support of $\sigma_{\mathcal{C}}$, which is the code space $\mathcal{C}$. □

Near-Optimal Recovery (Theorem 2b)

By Junge et al. [4], for any σ and $\mathcal{N}$, there exists a *rotated* Petz map $\tilde{\mathcal{R}}$ such that:

$$F(\rho, \tilde{\mathcal{R}} \circ \mathcal{N}(\rho))^2 \geq \exp(-\Delta D), \quad (18)$$

where $\Delta D = D(\rho \| \sigma) - D(\mathcal{N}(\rho) \| \mathcal{N}(\sigma))$. This is the bound used in the main text (Eq. (5)); it applies to the *rotated* Petz map, not the standard one.

The *standard* Petz map $\mathcal{R}_{\sigma, \mathcal{N}}$ satisfies the weaker Barnum–Knill bound [5]:

$$F_e(\mathcal{C}, \mathcal{R}_{\sigma_{\mathcal{C}}, \mathcal{N}} \circ \mathcal{N}) \geq \frac{1}{2} F_e(\mathcal{C}, R_{\mathrm{opt}} \circ \mathcal{N})^2, \quad (19)$$

where F_e is the entanglement fidelity and R_{opt} is the globally optimal decoder. Since $F_{e,\mathrm{opt}}^2 \geq \exp(-\Delta D)$ by the Junge et al. bound, this gives:

$$F_e(\mathcal{C}, \mathcal{R}_{\sigma_{\mathcal{C}}, \mathcal{N}} \circ \mathcal{N}) \geq \tfrac{1}{2} \exp(-\Delta D). \quad (20)$$

Note the factor of 1/2: the standard Petz map is within a constant factor of optimal, but does not saturate the exponential bound in general. For the saturation theorem (Theorem 3 of the main text, $\sigma = I/d$), the bound $F^2 \geq \exp(-\Delta D)$ for the standard Petz map is proved directly via the AM–GM inequality (Sec. S17), without invoking the Junge et al. machinery.

Worked Example: $[\![5,1,3]\!]$ Code

For the five-qubit code under depolarizing noise $\mathcal{N}_p(\rho) = (1-p)\rho + (p/3)(X\rho X + Y\rho Y + Z\rho Z)$ per qubit, the Knill–Laflamme conditions are satisfied exactly for weight-≤ 1 errors. At physical error rate $p = 0.01$:

$$F^2_{\text{Petz}} \geq \exp(-\Delta D) \approx 1 - 5p^2 + O(p^3) \approx 0.9995, \quad (21)$$

$$F^2_{\text{opt}} \approx 0.9997. \quad (22)$$

The Petz decoder achieves 99.95% fidelity vs. the optimal 99.97% —a gap of only 0.02%.

S4. DETAILED PROOF OF PROPOSITION 3 (MASTER INEQUALITY CHAIN)

We prove each link in the chain $-\log F^2 \leq I(A;E|B) \leq \Sigma \leq \Delta D$ separately.

Link 1: $-\log F^2 \leq \Delta D$ (Fidelity Bound)

This is the Junge–Renner–Sutter–Wilde–Winter theorem [4]. For the Petz recovery map:

$$F(\rho, \mathcal{R}_{\sigma,\mathcal{N}}(\mathcal{N}(\rho)))^2 \geq \exp\big(-(D(\rho\|\sigma) - D(\mathcal{N}(\rho)\|\mathcal{N}(\sigma)))\big). \quad (23)$$

Taking logarithms: $-\log F^2 \leq \Delta D$.

Link 2: $I(A;E|B) \geq -\log F^2$ (CMI Bound)

Consider the Stinespring dilation of $\mathcal{N}$: $\mathcal{N}(\rho_A) = \text{Tr}_E[V\rho_A V^\dagger]$, producing the state ω_{BE} from ρ_A. The conditional mutual information is:

$$I(A;E|B)_\omega = S(\omega_{AB}) + S(\omega_{BE}) - S(\omega_B) - S(\omega_{ABE}). \quad (24)$$

Fawzi–Renner [6] proved that for any tripartite state ω_{ABE}:

$$I(A;E|B)_\omega \geq -\log F(\omega_{AB}, \mathcal{R}_{B\to AB}(\omega_B))^2, \quad (25)$$

where $\mathcal{R}_{B\to AB}$ is the Petz recovery map for the partial trace Tr_A. Combined with Link 1, this gives:

$$I(A;E|B) \geq -\log F^2. \quad (26)$$

Link 3: $\Sigma \geq I(A;E|B)$ (Entropy Production Bound)

By the Kolchinsky–Wolpert decomposition [7], the entropy production of a process π with initial distribution p_0 and steady state q_0 decomposes as:

$$\Sigma(p_0) = \Sigma_{\text{Landauer}} + \Sigma_{\text{mismatch}} + \Sigma_{\text{res}} \quad (27)$$

$$\geq \Sigma_{\text{Landauer}} = D(p_0\|q_0) - D(\pi p_0\|\pi q_0). \quad (28)$$

The Landauer component Σ_{Landauer} captures the information-theoretic cost. For ideal (infinite, memoryless) thermal baths, the total entropy production Σ equals the relative entropy decrease ΔD; for finite-size baths, $\Sigma_{\text{Landauer}} \leq \Delta D$ and the mismatch and residual terms provide finite-size corrections. Since $\Delta D \geq I(A;E|B)$ (from Links 1–2) and $\Sigma \geq \Sigma_{\text{Landauer}} \geq 0$:

$$\Sigma \geq I(A;E|B). \quad (29)$$

For ideal baths this follows from $\Sigma = \Delta D \geq I(A;E|B)$. For finite baths, the chain $I(A;E|B) \leq \Sigma \leq \Delta D$ requires that the accessible entropy production exceeds the conditional mutual information, which holds whenever the environment thermalizes independently of the system's initial state (Markovian bath assumption).

Link 4: $\Delta D \geq \Sigma$ (Second Law)

The relative entropy decrease $\Delta D = D(\rho\|\sigma) - D(\mathcal{N}(\rho)\|\mathcal{N}(\sigma))$ is the total information lost under the channel. By the Reeb–Wolf improved Landauer principle [8], the accessible entropy production Σ satisfies:

$$\Delta D \geq \Sigma \geq 0. \quad (30)$$

The gap $\Delta D - \Sigma$ accounts for system-bath correlations established during the process. For ideal (Markovian) baths, $\Sigma = \Delta D$ and the chain collapses to $-\log F^2 \leq I(A;E|B) \leq \Delta D$.

Tightness Conditions

Condition	Physical meaning	Domain
$F^2 = 1$	Exact recovery	QEC
$I(A;E\|B) = 0$	Markov condition	No leakage
$\Sigma = 0$	Reversible process	Thermo.
$\Delta D = 0$	DPI saturated	Sufficiency

Gibbs State Specialization

When $\sigma = \sigma_\beta = e^{-\beta H}/Z$:

$$\begin{aligned} D(\rho\|\sigma_\beta) &= \text{Tr}[\rho\log\rho] - \text{Tr}[\rho\log\sigma_\beta] \\ &= -S(\rho) + \beta\langle H\rangle_\rho + \log Z \\ &= \beta\big(\langle H\rangle_\rho - TS(\rho) - \mathcal{F}_{\text{eq}}\big) \\ &= \beta\big(\mathcal{F}(\rho) - \mathcal{F}_{\text{eq}}\big), \end{aligned} \quad (31)$$

where $\mathcal{F}(\rho) = \langle H\rangle_\rho - TS(\rho)$ is the non-equilibrium free energy and $\mathcal{F}_{\text{eq}} = -k_{\text{B}}T\log Z$. (We use $\mathcal{F}$ for free energy to avoid confusion with the fidelity F.)

Therefore:

$$\begin{aligned}\Delta D &= D(\rho\|\sigma_\beta) - D(\mathcal{N}(\rho)\|\mathcal{N}(\sigma_\beta)) \\ &= \beta\big[\mathcal{F}(\rho) - \mathcal{F}(\mathcal{N}(\rho))\big] - \beta\big[\mathcal{F}_{\rm eq} - \mathcal{F}'_{\rm eq}\big] \\ &= \beta\, W_{\rm diss}. \end{aligned} \tag{32}$$

The master inequality becomes:

$$\boxed{F^2 \geq \exp(-\beta\, W_{\rm diss}) = \exp(-\Delta S_{\rm irr}/k_{\rm B}).} \tag{33}$$

This is a *recovery-theoretic second law*: the ability to recover a quantum state from a thermodynamic process is exponentially bounded by the dissipated work.

S5. PROOF OF SUPERPOSITION NECESSITY

Theorem 1 (Superposition from Recoverability)**.** *If a system is in a definite-path state $\rho_S = |i\rangle\langle i|$, then for any recovery procedure (Petz map + measurement on the detector E), the recovered signal state has no off-diagonal coherence in the path basis. Consequently, recovery of interference implies prior superposition.*

Proof.—

Step 1: No entanglement from definite paths. If $\rho_S = |i_0\rangle\langle i_0|$ (definite path), the entangling interaction produces:

$$\rho_{SE} = |i_0\rangle\langle i_0| \otimes |d_{i_0}\rangle\langle d_{i_0}|. \tag{34}$$

This is a product state—no entanglement is created.

Step 2: Petz recovery on product states. The Petz recovery $\mathcal{R}_{\sigma_{SE},{\rm Tr}_E}$ with $\sigma_{SE} = \rho_{SE}$ (the product state) gives:

$$\mathcal{R}(\rho_S) = |i_0\rangle\langle i_0| \otimes |d_{i_0}\rangle\langle d_{i_0}|, \tag{35}$$

which is again a product state.

Step 3: Measurement on E cannot create coherence. Any measurement $\{M_k\}$ on E followed by post-selection gives:

$$\begin{aligned}\rho_S^{(k)} &= \frac{{\rm Tr}_E[(I_S \otimes M_k)\,\rho_{SE}\,(I_S \otimes M_k^\dagger)]}{p_k} \\ &= \frac{|\langle d_{i_0}|M_k^\dagger|d_{i_0}\rangle|^2}{p_k}\,|i_0\rangle\langle i_0| = |i_0\rangle\langle i_0|. \end{aligned} \tag{36}$$

No coherence. No interference. □

Contrapositive: If the eraser procedure produces $\rho_S^{(k)}$ with $\langle j|\rho_S^{(k)}|l\rangle \neq 0$ for $j \neq l$ (off-diagonal coherence = interference), then the initial state was *not* $|i_0\rangle\langle i_0|$ for any i_0. It must have been a superposition.

S6. QUANTUM CROOKS FLUCTUATION THEOREM VIA PETZ MAP

Following Kwon–Kim [9], consider a thermodynamic protocol:

Initial state: $\sigma_\beta^{(i)} = e^{-\beta H_i}/Z_i$.

Forward process: unitary U (changing H_i to H_f), followed by thermalization $\mathcal{T}$. Total: $\mathcal{N}_F = \mathcal{T} \circ \mathcal{U}$.

Reverse process: Defined via the Petz map: $\mathcal{N}_R = \mathcal{R}_{\sigma_\beta^{(i)},\mathcal{N}_F}$.

By functoriality (Theorem 1, axiom (ii)):

$$\mathcal{N}_R = \mathcal{R}_{\sigma_\beta^{(i)},\mathcal{U}} \circ \mathcal{R}_{U\sigma_\beta^{(i)}U^\dagger,\mathcal{T}}. \tag{37}$$

Since $\mathcal{R}_{\sigma,\mathcal{U}} = U^\dagger(\cdot)U$ (the Petz reverse of a unitary is its inverse):

$$\mathcal{N}_R = \mathcal{U}^{-1} \circ \mathcal{R}_{U\sigma_\beta^{(i)}U^\dagger,\mathcal{T}}. \tag{38}$$

In the two-point measurement (TPM) scheme, the work distribution is:

$$p_F(w) = \sum_{n,m} \delta(w - E_m^f + E_n^i)\,\frac{e^{-\beta E_n^i}}{Z_i}\,|\langle m_f|U|n_i\rangle|^2. \tag{39}$$

For the reverse process defined by $\mathcal{N}_R$:

$$p_R(-w) = \sum_{n,m} \delta(w - E_m^f + E_n^i)\,\frac{e^{-\beta E_m^f}}{Z_f}\,\left|\langle n_i|U^\dagger|m_f\rangle\right|^2. \tag{40}$$

Taking the ratio:

$$\frac{p_F(w)}{p_R(-w)} = \frac{Z_f}{Z_i}\,e^{\beta w} = e^{\beta(w-\Delta F)}, \tag{41}$$

where $\Delta F = -k_{\rm B}T\log(Z_f/Z_i)$. This is the Crooks fluctuation theorem. □

The Petz map naturally produces the correct time-reversed thermodynamic process. The $e^{-\beta H/2}$ factors in the Petz map implement the Boltzmann weighting that distinguishes thermodynamic time reversal from mere unitary reversal.

S7. SPECIALIZATION DIAGRAM

The four domains are connected by specialization of the pair $(\sigma, \mathcal{N})$:

$$\begin{array}{ccc} \text{(ii) Time Reversal} & \xrightarrow{\sigma = P/|\mathcal{C}|} & \text{(iii) QEC} \\ \downarrow_{\mathcal{N} = {\rm Tr}_E} & & \downarrow_{|\mathcal{C}|=1} \\ \text{(i) Quantum Eraser} & \xleftarrow{\mathcal{C} = \{|\phi\rangle\}} & \text{(iii) single codeword} \\ \downarrow_{\sigma = \sigma_\beta} & & \\ \text{(iv) Thermodynamics} & & \end{array}$$

QEC with single codeword = Quantum eraser.—For a one-dimensional code $\mathcal{C} = \mathrm{span}\{|\phi\rangle\}$, the Knill–Laflamme conditions $PE_a^\dagger E_b P = c_{ab}P$ are *automatically satisfied* (every operator has a matrix element in a one-dimensional space). Therefore, exact Petz recovery is always possible for a single codeword. This is the quantum eraser: the "code" is the coherent superposition state, and the "noise" is decoherence.

Universal bound connects all.—The bound $F^2 \geq \exp(-\Delta D)$ specializes to:

- *Quantum eraser:* $\Delta D = S(\rho_S^{\mathrm{decoh}}) - S(\rho_S^{\mathrm{init}})$ (entropy of decoherence). $\Delta D = 0$ for pure bipartite state $\Rightarrow$ exact recovery.
- *QEC:* $\Delta D = D(\rho\|\sigma_{\mathcal{C}}) - D(\mathcal{N}(\rho)\|\mathcal{N}(\sigma_{\mathcal{C}}))$ (information lost to noise). $\Delta D = 0$ when KL conditions hold.
- *Thermodynamics:* $\Delta D = \beta W_{\mathrm{diss}}$ (dissipated work). $F^2 \geq e^{-\beta W_{\mathrm{diss}}}$.

S8. NOTATION AND CONVENTIONS

Symbol	Meaning
$\mathcal{H}$	Hilbert space
$\mathcal{B}(\mathcal{H})$	Bounded operators on $\mathcal{H}$
$\mathcal{S}(\mathcal{H})$	Density matrices on $\mathcal{H}$
$\mathcal{N}$	Quantum channel (CPTP map)
$\mathcal{N}^\dagger$	Hilbert–Schmidt adjoint
$\mathcal{R}_{\sigma,\mathcal{N}}$	Petz recovery map
$D(\rho\|\sigma)$	Quantum relative entropy
$F(\rho,\sigma)$	Uhlmann fidelity
$I(A;B\|C)$	Conditional mutual information
Σ	Entropy production
σ_β	Gibbs state $e^{-\beta H}/Z$
k_{B}	Boltzmann constant
P	Code projector
$\mathcal{C}$	Code space

Relative entropy: $D(\rho\|\sigma) = \mathrm{Tr}[\rho(\log\rho - \log\sigma)]$, with the convention $D(\rho\|\sigma) = +\infty$ if $\mathrm{supp}(\rho) \not\subseteq \mathrm{supp}(\sigma)$.

Fidelity: $F(\rho,\sigma) = \left\|\sqrt{\rho}\sqrt{\sigma}\right\|_1 = \mathrm{Tr}\sqrt{\sqrt{\rho}\sigma\sqrt{\rho}}$.

S9. POST-SELECTION ANALYSIS

We derive the post-selection improvement factor stated in the main text and connect it to the Ising–QEC mapping.

Derivation of the Improvement Factor

Consider a stabilizer code $\mathcal{C}$ of distance d under noise $\mathcal{N}$. Syndrome measurement yields outcome s with probability $p(s)$. For each syndrome, define the instance-level data-processing gap:

$$\Delta D(s) = D(\rho^{(s)}\|\sigma_{\mathcal{C}}) - D(\mathcal{N}(\rho^{(s)})\|\mathcal{N}(\sigma_{\mathcal{C}})), \tag{42}$$

where $\rho^{(s)}$ is the post-syndrome logical state. By the universal recovery bound, $F(s)^2 \geq \exp(-\Delta D(s))$.

The overall logical failure probability is:

$$p_{\mathrm{fail}} = \sum_s p(s)\left(1 - F(s)^2\right) \leq \sum_s p(s)\left(1 - e^{-\Delta D(s)}\right). \tag{43}$$

Post-selecting: accept only syndromes in $\mathcal{A}_\varepsilon = \{s : \Delta D(s) \leq \Delta D_{\mathrm{th}}(\varepsilon)\}$, where $\sum_{s\notin\mathcal{A}_\varepsilon} p(s) = \varepsilon$. The post-selected failure probability is:

$$p_{\mathrm{fail}}^{(\varepsilon)} = \frac{1}{1-\varepsilon}\sum_{s\in\mathcal{A}_\varepsilon} p(s)\left(1 - F(s)^2\right) \leq \Delta D_{\mathrm{th}}(\varepsilon), \tag{44}$$

where the last step uses $1 - e^{-x} \leq x$ for $x \geq 0$.

The improvement factor is:

$$R(\varepsilon) = \frac{p_{\mathrm{fail}}}{p_{\mathrm{fail}}^{(\varepsilon)}} \approx \exp\big(\Delta D_{\mathrm{th}}(\varepsilon)\big), \tag{45}$$

where the exponential form holds when the dominant contribution to failures comes from the tail of the ΔD distribution.

Distribution of $\Delta D(s)$

For a distance-d surface code under depolarizing noise at rate p, errors of weight w have probability $\sim p^w$ and produce $\Delta D(s) \approx w\ln(1/p)$. The tail probability is:

$$\Pr[\Delta D > x] \sim \exp(-x/\lambda), \quad \lambda \sim \ln(1/p). \tag{46}$$

This exponential tail makes post-selection effective: a small fraction of high-ΔD instances carries a disproportionate share of failures.

Connection to the Ising–QEC Mapping

English et al. [12] established an exact mapping from surface-code failure rates to Ising-model partition functions:

$$p_{\mathrm{fail}}(s) = \frac{Z_-(s)}{Z_+(s) + Z_-(s)} = \frac{1}{1 + e^{\Delta F(s)/T_{\mathrm{eff}}}}, \tag{47}$$

where $\Delta F(s)$ is the Ising domain-wall free energy. Identifying $\Delta F(s)/T_{\mathrm{eff}} \approx \Delta D(s)$, the Petz bound $F(s)^2 \geq e^{-\Delta D(s)}$ becomes a statement about Ising free-energy gaps: post-selection on low-ΔD syndromes is equivalent to conditioning on Ising configurations with large free-energy gaps, where the correct logical value is thermodynamically favored.

The Scaling Prediction

For a distance-d code at error rate p with rejection fraction ε:

$$\ln R(\varepsilon, d) = \alpha(p)\, d + \beta(\varepsilon), \tag{48}$$

where $\alpha(p) \approx \frac{1}{2}\ln(p_{\rm th}/p)$ (the per-unit-distance improvement, decoder-independent) and $\beta(\varepsilon) \approx \ln(1/(1-\varepsilon))$ (the rejection overhead, code-distance-independent). The decoder-independence of α follows from $\Delta D(s)$ depending only on $(\mathcal{N}, \sigma_{\mathcal{C}})$, not on the recovery map.

This prediction is supported by: quadratic post-selection gains [10], Ising-based thresholds [11], scalable gains $p_f \to p_f^b$ with $b \geq 2$ [13], and below-threshold surface code operation [16].

S10. DECODER RETRODICTION HIERARCHY

We develop the interpretation of the QEC decoder hierarchy as a sequence of approximations to optimal Petz retrodiction.

ML Decoding as Exact Retrodiction

For a stabilizer code with syndrome s, maximum-likelihood decoding selects:

$$\ell^* = \arg\max_{\ell}\ p(\ell \,|\, s) = \arg\max_{\ell}\ p(s \,|\, \ell)\, p(\ell). \tag{49}$$

This is classical Bayes' rule—the classical limit (axiom (iv) of Theorem 1) of the Petz retrodiction functor. For the full quantum problem, the Petz map $\mathcal{R}_{\sigma_{\mathcal{C}},\mathcal{N}}$ generalizes ML by retrodicting the full quantum state including coherences.

The Retrodiction Gap Hierarchy

For decoder $\mathcal{D}$, define:

$$\delta_{\mathcal{D}} = D\Big(\tilde{\mathcal{R}}_{\sigma_{\mathcal{C}},\mathcal{N}} \,\big\|\, \mathcal{D}\Big), \tag{50}$$

measuring the distinguishability from optimal retrodiction. The established hierarchy [14] becomes:

$$0 = \delta_{\rm ML} < \delta_{\rm NN} < \delta_{\rm CM} < \delta_{\rm MWPM} < \delta_{\rm UF}. \tag{51}$$

The bound from the main text gives:

$$F(\rho,\, \mathcal{D} \circ \mathcal{N}(\rho))^2 \geq F(\rho,\, \tilde{\mathcal{R}} \circ \mathcal{N}(\rho))^2 \cdot e^{-\delta_{\mathcal{D}}}. \tag{52}$$

The Computational Entropy Conjecture

We conjecture $\delta_{\mathcal{D}} \leq c\,\sigma_{\mathcal{D}}$, where $\sigma_{\mathcal{D}}$ is the thermodynamic entropy produced during the decoder's computation. The motivation is Landauer's principle: erasing correlations during decoding costs $k_{\rm B}T\ln 2$ per bit and simultaneously degrades retrodictive information.

Heuristic support:

- Union-Find: greedy local rules discard long-range correlations (high σ, large δ).
- MWPM: global matching but ignores error correlations (moderate σ and δ).
- Neural networks (AlphaQubit [15]): learn correlations from data, potentially lower δ.
- ML/tensor-network: full probabilistic inference, minimal information erasure ($\delta \approx 0$).

Regime of Applicability

Preliminary numerical experiments on $d = 3$ surface codes show that decoder *expressiveness* (the ability to represent complex correlations) dominates over thermodynamic efficiency in the small-code regime. A highly dissipative but expressive neural network outperforms a thermodynamically efficient but inexpressive decoder. We expect the conjecture to become relevant at $d \gtrsim 15$–20, where the syndrome space grows exponentially and efficient information compression becomes the bottleneck.

Even without the thermodynamic conjecture, the retrodiction-gap framework provides independent value: $\delta_{\mathcal{D}}$ is a decoder-independent metric computable from output statistics, offering a unified lens for comparing decoders of entirely different architectures.

Caveat on current evidence.—The rank-order consistency between the retrodiction hierarchy and known decoder performance reported in the main text is a *prediction*, not a verified result. Computing $\delta_{\mathcal{D}}$ from published data requires access to the full CPTP decoder map, which is not available for most decoders. Direct numerical verification of $\delta_{\rm NN} < \delta_{\rm MWPM} < \delta_{\rm UF}$ from decoder output statistics is an important open task.

S11. TEMPORAL ASYMMETRY AND THE EQUIVALENCE CHAIN

We prove the equivalence chain stated in the main text and develop the temporal asymmetry parameter τ.

Definition and Basic Properties

For a quantum channel $\mathcal{N}$, faithful reference state σ, and input ρ, define:

$$\tau(\rho, \sigma, \mathcal{N}) = 1 - F\big(\rho,\, \tilde{\mathcal{R}}_{\sigma,\mathcal{N}}(\mathcal{N}(\rho))\big), \tag{53}$$

where $\tilde{\mathcal{R}}$ is the rotated Petz map of Junge et al. [4].

Basic properties:

1. $0 \le \tau \le 1$ (from $0 \le F \le 1$).
2. $\tau = 0$ if and only if exact Petz recovery: $\tilde{\mathcal{R}}_{\sigma,\mathcal{N}} \circ \mathcal{N}(\rho) = \rho$.
3. τ is continuous in all arguments (by continuity of fidelity).
4. τ is monotone under composition: for composable $\mathcal{N}_1, \mathcal{N}_2$, $\tau(\rho, \sigma, \mathcal{N}_2 \circ \mathcal{N}_1) \ge \tau(\rho, \sigma, \mathcal{N}_1)$, since additional processing cannot improve recovery.

The Equivalence Chain: Proof

We prove that for a faithful σ and channel $\mathcal{N}$ with Stinespring dilation $V : \mathcal{H}_A \to \mathcal{H}_B \otimes \mathcal{H}_E$, the following are equivalent:
(a) $\tau = 0$ (exact Petz recovery).
(b) $\Delta D = 0$ (DPI saturated).
(c) $I(A; E|B)_\omega = 0$ (quantum Markov chain).
(d) $\Sigma = 0$ (zero entropy production, for thermal σ).
(e) Detailed balance: $\mathcal{R}_{\sigma,\mathcal{N}} = \mathcal{N}$ (the channel is its own Petz reversal).

(a) ⇔ (b): This is the Petz sufficiency theorem [2]. Exact recovery $F = 1$ holds if and only if $D(\rho\|\sigma) = D(\mathcal{N}(\rho)\|\mathcal{N}(\sigma))$ for all ρ in the support of σ, i.e., $\Delta D = 0$.

(b) ⇔ (c): By Fawzi–Renner [6], $I(A; E|B)_\omega = 0$ if and only if ω_{ABE} is a quantum Markov chain $A - B - E$. By the Stinespring structure, this is equivalent to perfect recoverability of A from B, i.e., $\Delta D = 0$.

(b) ⇔ (d) (for Gibbs σ): When $\sigma = e^{-\beta H}/Z$, the entropy production $\Sigma = \beta W_{\text{diss}} + D_{\text{mismatch}}$ by Kolchinsky–Wolpert [7]. $\Sigma = 0$ requires both $W_{\text{diss}} = 0$ and zero mismatch, which for the Gibbs reference means $\Delta D = \beta W_{\text{diss}} = 0$. The converse follows from $\Sigma \le \Delta D$ (second law, Reeb–Wolf [8]).

(d) ⇔ (e): By Kwon–Kim [9]: the Crooks ratio $P_F/P_R = \exp(\Sigma/k_{\text{B}})$. Detailed balance ($\mathcal{R}_{\sigma,\mathcal{N}} = \mathcal{N}$, i.e., the channel equals its own reversal) holds if and only if $P_F = P_R$ for all trajectories, i.e., $\Sigma = 0$.

This completes the chain. □

Bound: $\tau \le 1 - \exp(-\Sigma/2)$

From Proposition 3 of the main text (master inequality chain):

$$F^2 \ge \exp(-\Sigma). \tag{54}$$

Since $F \ge 0$ and $\exp(-x/2) \ge 0$, taking the square root:

$$F \ge \exp(-\Sigma/2). \tag{55}$$

Therefore:

$$\tau = 1 - F \le 1 - \exp(-\Sigma/2). \tag{56}$$

For small Σ: Taylor-expanding gives $\tau \lesssim \Sigma/2$. For large Σ: $\tau \to 1$. The bound is tight when $F^2 = \exp(-\Sigma)$ (saturation of the Junge bound).

Connection to the Crooks Fluctuation Theorem

The Crooks theorem [17] states:

$$\frac{P_F(w)}{P_R(-w)} = \exp\big(\beta(w - \Delta F)\big). \tag{57}$$

For a cyclic process ($\Delta F = 0$), averaging over trajectories: $\langle P_F/P_R \rangle = \exp(\langle \beta W \rangle) = \exp(\Sigma/k_{\text{B}})$. When $\Sigma = 0$: $P_F = P_R$ pointwise. Forward and reverse processes are equally probable for every trajectory.

The temporal asymmetry parameter τ provides a *state-level* (rather than trajectory-level) measure of this asymmetry. While the Crooks ratio is defined over stochastic trajectories, τ is defined for a single input state ρ and measures whether that state can be recovered after the channel. The connection is: $\tau = 0$ implies $\Sigma = 0$ implies $P_F = P_R$ (the process is its own time reversal).

In a zero-entropy-production system, forward and reverse processes are statistically indistinguishable.

The Retrodiction Landauer Principle

The energy cost of retrodiction—inferring the pre-channel state from the post-channel state—is bounded by the entropy produced during the forward process.

Observation (Retrodiction Landauer principle).—For a channel $\mathcal{N}$ with thermal reference state $\sigma_\beta = e^{-\beta H}/Z$, we argue heuristically that the minimum energy cost of any physical implementation of approximate retrodiction satisfies:

$$E_{\text{retro}} \ge k_{\text{B}} T \cdot \Sigma. \tag{58}$$

The argument applies Landauer's principle [8] (energy dissipation $\ge k_{\text{B}} T \ln 2$ per bit erased) to the task of recovering ΔD nats of distinguishability from $\mathcal{N}(\rho)$ to ρ,

giving $E_{\text{retro}} \geq k_{\text{B}}T \cdot \Delta D$. By the master chain, $\Delta D \geq \Sigma$, giving Eq. (58). This extends Landauer's principle from bit erasure to state retrodiction; the extension is physically motivated but not rigorously derived from first principles.

Physical consequences:

- $\Sigma = 0$ (closed system): retrodiction is thermodynamically free. The past is as accessible as the future.
- $\Sigma > 0$ (open system): retrodiction has a minimum energy cost proportional to the entropy produced. The past becomes energetically expensive to access.
- The bound is tight when $\Delta D = \Sigma$ (all information loss is dissipative). □

The Quantum Eraser as the $\tau = 0$ Special Case

For a pure bipartite state $|\psi\rangle_{SE}$ with $\mathcal{N} = \text{Tr}_E$:

- $\sigma = |\psi\rangle\langle\psi|_{SE}$ (pure).
- $D(\sigma\|\sigma) = 0$ and $D(\mathcal{N}(\sigma)\|\mathcal{N}(\sigma)) = 0$, so $\Delta D = 0$ trivially.
- By the equivalence chain: $\Delta D = 0 \Rightarrow I(A; E|B) = 0 \Rightarrow \Sigma = 0 \Rightarrow \tau = 0$.
- $F = 1$: exact recovery, as computed in Sec. S1.

The quantum eraser operates in the $\tau = 0$ regime. The idler measurement "works" not because of backward causation but because the signal-idler pair forms a closed system with zero entropy production. In such a system, the Crooks ratio is exactly 1, and there is no statistical distinction between measuring the signal first or the idler first.

The "need to wait" for the idler measurement arises only in the *open-system description*: when we trace out the idler and describe only the signal, we have $\tau > 0$ for the signal alone. The full bipartite system has $\tau = 0$, but the subsystem has $\tau > 0$. Recovering $\tau = 0$ requires accessing the idler—this is the operational meaning of "waiting for the future measurement."

S12. NUMERICAL VERIFICATION: DESIGN RATIONALE AND RESULTS

In this section we describe numerical experiments designed to test the *new predictions* of our framework (Predictions 1 and 2 of the main text), and explain why these experiments go beyond verifying known mathematics.

Scope of Numerical Tests

The individual inequalities in the master chain (6) of the main text are rigorously proven [4, 6, 8]; computing them for specific channels confirms implementation correctness but does not test any physical prediction. The numerical experiments below instead test consequences that follow from the *uniqueness* of the Petz map as a retrodiction functor (Theorem 1) and from the *structure* of the master inequality chain when applied to error correction.

Experiment 1: Decoder Retrodiction Hierarchy

Known: Different QEC decoders (ML, MWPM, Union-Find, etc.) have different logical error rates [14]. This performance ordering is well-established empirically.

New prediction: The retrodiction gap $\delta_{\mathcal{D}} = D(\tilde{\mathcal{R}}_{\sigma,\mathcal{N}}\|\mathcal{D})$ should *quantitatively rank-order* decoder performance. Specifically, decoders with smaller $\delta_{\mathcal{D}}$ must have higher recovery fidelity.

The prediction is non-trivial because if the Petz map were merely *one of many* good recovery maps, then $\delta_{\mathcal{D}}$ (the divergence from the Petz map) would have no reason to predict decoder quality — a decoder could differ greatly from the Petz map yet still perform well by approximating some other good recovery map. The prediction that $\delta_{\mathcal{D}}$ rank-orders performance follows specifically from the *uniqueness* of the Petz map (Theorem 1): since it is the *only* Bayesian-consistent retrodiction functor, any sufficiently good decoder must converge toward it.

Numerical protocol:

1. Fix a surface code of distance d under depolarizing noise at rate p.
2. Implement four decoders: maximum-likelihood (ML, via exhaustive enumeration for small d), minimum-weight perfect matching (MWPM), Union-Find (UF), and a simple lookup-table decoder.
3. For each decoder $\mathcal{D}$, compute the effective channel $\mathcal{D} \circ \mathcal{N}$ by Monte Carlo sampling over error configurations.
4. Compute $\delta_{\mathcal{D}} = D(\tilde{\mathcal{R}}_{\sigma,\mathcal{N}}\|\mathcal{D})$ via the channel divergence between the Petz decoder and $\mathcal{D}$.
5. Compare the ordering $\delta_{\text{ML}} < \delta_{\text{MWPM}} < \delta_{\text{UF}} < \delta_{\text{lookup}}$ against the known performance ordering.

The prediction fails if a decoder with *larger* $\delta_{\mathcal{D}}$ consistently outperforms one with *smaller* $\delta_{\mathcal{D}}$, which would indicate that the Petz map's uniqueness as a retrodiction functor does not constrain the structure of practical decoders.

Experiment 2: Post-Selection Thermodynamic Filtering

Known: Post-selection on syndrome outcomes can improve logical error rates in QEC [10, 13]. The improvement depends on the rejection fraction ε and the code distance d.

New prediction: The improvement factor obeys $\ln R(\varepsilon, d) = \alpha(p)\, d + \beta(\varepsilon)$, where:

- $\alpha(p)$ depends on the noise rate p but is *independent of the decoder* $\mathcal{D}$;
- $\beta(\varepsilon)$ depends on the rejection fraction but is *independent of the code distance* d.

Why α is decoder-independent: The data-processing gap $\Delta D(s)$ for syndrome s is determined by the noise channel $\mathcal{N}$ and the code state $\sigma_{\mathcal{C}}$ alone — it measures how much distinguishability is lost under the noise, which is a property of the noise and the code, not of the decoder. The per-distance scaling $\alpha(p)$ inherits this decoder-independence because it is set by the distribution of $\Delta D(s)$ values, which is a property of the channel.

Numerical protocol:

1. Fix surface codes of distances $d = 3, 5, 7$ under depolarizing noise at rates $p \in \{0.01, 0.03, 0.05\}$.
2. For each (d, p), sample 10^5–10^6 syndrome outcomes and compute $\Delta D(s)$ for each.
3. Apply multiple decoders (MWPM, UF, lookup) to each syndrome.
4. For each decoder and rejection fraction $\varepsilon \in [0, 0.3]$, compute the post-selected logical error rate $p_{\text{fail}}^{(\varepsilon)}$ and the improvement factor $R(\varepsilon, d)$.
5. Fit $\ln R(\varepsilon, d) = \alpha(p)\, d + \beta(\varepsilon)$ and verify:
   (a) The factorization holds (linear in d with d-independent intercept);
   (b) $\alpha(p)$ is the same across different decoders.

A decoder-dependent α — e.g., MWPM and Union-Find giving different slopes at the same noise rate — would indicate that the thermodynamic filtering picture is incomplete.

Relationship to the Quantum Eraser Calculation

The explicit quantum eraser calculation (Sec. S1) serves a different purpose from the numerical experiments above. The eraser calculation demonstrates that the Petz map formalism correctly reproduces the known physics of quantum erasure ($\tau = 0$ for a closed bipartite system). This is a *consistency check* of the formalism, not a test of a new prediction. The numerical experiments in this section, by contrast, test consequences of the framework that are *not known a priori* and could in principle be falsified.

S13. EXPERIMENTAL PROPOSALS AND EXISTING EVIDENCE

The master inequality chain (6) of the main text and the predictions derived from it can be tested against both existing published data and purpose-built experiments. In this section we describe reanalysis strategies for published results (Sec. S13.1), propose two new experimental protocols (Secs. S13.2–S13.3), and specify the simulation methodology used in this work (Sec. S13.4).

S13.1: Reanalysis of Published Data

Several recent experimental results can be reinterpreted through the lens of the Petz retrodiction framework, providing immediate consistency checks without new hardware.

Decoder hierarchy.—Bausch et al. [15] (AlphaQubit) demonstrated that a recurrent neural-network decoder outperforms correlated minimum-weight perfect matching (MWPM), which in turn outperforms standard MWPM, which outperforms Union-Find (UF). Our framework (Sec. S10) predicts that this performance ordering is equivalent to the retrodiction divergence ordering: $\delta_{\text{NN}} < \delta_{\text{cMWPM}} < \delta_{\text{MWPM}} < \delta_{\text{UF}}$. A concrete test is to compute $\delta_{\mathcal{D}}$ for each decoder from the published logical error rates and noise model parameters reported in Ref. [15]. If the CPTP map of the decoder is not fully specified, one can use an operational proxy: $\delta_{\mathcal{D}}^{\text{op}} = p_L(\mathcal{D}) - p_L(\text{ML})$, normalized by the code distance, where $p_L(\text{ML})$ is the maximum-likelihood logical error rate.

Post-selection.—English et al. [11] and Chen et al. [13] demonstrated that post-selecting on syndrome outcomes improves the effective QEC threshold. Our framework predicts that the improvement factor satisfies $\ln R = \alpha(p) \cdot d + \beta(\varepsilon)$ with the per-distance coefficient α being decoder-independent (Sec. S9). Reanalyzing their published data to extract α for different decoders at the same noise rate would directly test this prediction. Preliminary inspection of the data in Ref. [13] shows scaling consistent with decoder-independent α, but a systematic extraction has not been performed.

Petz recovery experiments.—Singh et al. [23] implemented the Petz recovery map on a nuclear magnetic resonance (NMR) platform, and Png and Scarani [24] realized it on a trapped-ion quantum processor. Both experiments measured aspects of recovery fidelity under controlled noise channels. Our framework predicts

$F \geq \exp(-\Sigma/2)$, where Σ is the entropy production of the noise process. Two important caveats apply: (i) neither experiment directly measured the Petz recovery fidelity F in the precise sense of Eq. (9) of the main text (i.e., fidelity between the input state and the output of the rotated Petz map); rather, they measured circuit-level recovery fidelities that serve as proxies; and (ii) neither experiment simultaneously measured Σ. One can compute Σ from the reported channel parameters (e.g., amplitude damping with measured decay rate γ, giving $\Sigma(\gamma) = \gamma \ln[(1+\gamma)/\gamma]$ for a thermal bath) and check consistency, but this constitutes an indirect test based on the theoretical channel model, not a direct simultaneous measurement of F and Σ on the same experimental run. A simultaneous measurement of both quantities on the same quantum channel is an important open experimental direction (see Sec. S13.2).

S13.2: Proposed Experiment—Simultaneous F and Σ Measurement

To our knowledge, no existing experiment has simultaneously measured the Petz recovery fidelity F and the entropy production Σ for the same quantum channel in the same experimental run. This represents a significant gap in the experimental evidence base: all existing tests of the bound $F \geq \exp(-\Sigma/2)$ rely either on theoretical calculations from channel parameters (Sec. S15.1) or on separate measurements of F and Σ in different experimental contexts. A simultaneous measurement would provide the most direct test of both the bound and the equivalence $\tau = 0 \Leftrightarrow \Sigma = 0$.

System.—A superconducting transmon qubit coupled to a tunable electromagnetic environment (e.g., a lossy resonator with adjustable coupling κ). The effective noise channel is amplitude damping $\mathcal{N}_\gamma$ with damping parameter $\gamma = 1 - e^{-\kappa t}$ controlled by the coupling time t.

Protocol:

1. *Preparation*: Initialize the qubit in a known state ρ (e.g., $|+\rangle = (|0\rangle + |1\rangle)/\sqrt{2}$) via standard gate operations.

2. *Noise application*: Apply the amplitude damping channel $\mathcal{N}_\gamma$ by coupling to the lossy resonator for time t. Vary γ from 0 to 1 by sweeping t.

3. *Measurement 1 (entropy production)*: Perform quantum state tomography on $\mathcal{N}_\gamma(\rho)$ to reconstruct the output state. Compute Σ from the channel parameters:

$$\Sigma(\gamma) = D\big(\mathcal{N}_\gamma(\rho)\big\|\mathcal{N}_\gamma(\sigma_\beta)\big) - D(\rho\|\sigma_\beta) + \beta\, Q, \qquad (59)$$

   where $Q = \mathrm{Tr}[H(\rho - \mathcal{N}_\gamma(\rho))]$ is the heat dissipated and σ_β is the thermal state of the qubit. For a zero-temperature bath, $\Sigma(\gamma) = (1-\gamma)\ln(1-\gamma) + \gamma$ (in nats) when $\rho = |1\rangle\langle 1|$.

4. *Measurement 2 (recovery fidelity)*: Implement the Petz recovery map $\mathcal{R}_{\sigma,\mathcal{N}_\gamma}$ as a quantum circuit. For amplitude damping, the Petz map has a known circuit decomposition [5] involving an ancilla qubit and controlled rotations. Apply $\mathcal{R}_{\sigma,\mathcal{N}_\gamma}$ to $\mathcal{N}_\gamma(\rho)$ and perform state tomography on the output. Compute $F = F(\rho, \mathcal{R}_{\sigma,\mathcal{N}_\gamma}(\mathcal{N}_\gamma(\rho)))$.

5. *Sweep*: Repeat steps 1–4 for $\gamma \in \{0, 0.1, 0.2, \ldots, 1.0\}$.

Predictions:

- $F(\gamma) \geq \exp(-\Sigma(\gamma)/2)$ for all γ.
- At $\gamma = 0$: $F = 1$ and $\Sigma = 0$ (unitary limit, quantum eraser regime, $\tau = 0$).
- At $\gamma = 1$: F is minimized and Σ is maximized (complete decoherence, maximal arrow of time).
- The curve $F(\gamma)$ vs. $\Sigma(\gamma)$ should lie on or above the line $F = \exp(-\Sigma/2)$ in a log-linear plot.

Resources.—This experiment requires a single superconducting qubit with tunable coupling to a dissipative environment, plus one ancilla qubit for implementing the Petz recovery circuit. No large-scale quantum processor is needed. The main technical challenge is accurate characterization of γ and implementation of the Petz recovery circuit with sufficiently high gate fidelity.

S13.3: Proposed Experiment—Decoder-Independent α

The prediction that the post-selection improvement coefficient $\alpha(p)$ is decoder-independent (Sec. S9, Prediction 1 of the main text) can be tested on any surface code platform.

System.—Any platform supporting surface codes of distance $d = 3, 5, 7$ (or higher) under circuit-level noise. Suitable platforms include Google Sycamore/Willow [16], IBM Eagle/Heron, or Quantinuum ion-trap processors.

Protocol:

1. Run a distance-d surface code under the native noise of the device, collecting syndrome measurement data over $N \geq 10^6$ rounds per code distance.

2. Decode the data using at least two decoders of different architecture: MWPM (e.g., via PyMatching [26]) and Union-Find.

3. For each decoder, compute the logical error rate with and without post-selection at rejection fractions $\varepsilon \in \{0, 0.05, 0.10, 0.15, 0.20, 0.25, 0.30\}$.

4. Compute the improvement factor $R(\varepsilon, d) = p_{\text{fail}}/p_{\text{fail}}^{(\varepsilon)}$ for each $(d, \varepsilon, \text{decoder})$ triple.

5. Fit $\ln R(\varepsilon, d) = \alpha \cdot d + \beta(\varepsilon)$ separately for each decoder.

6. Compare α_{MWPM} vs. α_{UF}.

Prediction: $\alpha_{\text{MWPM}} \approx \alpha_{\text{UF}}$ within statistical uncertainty, because α is determined by the noise channel and code structure (via $\Delta D(s)$), not by the decoder.

Significant decoder-dependence of α would point to decoder-specific correlations contributing to the per-distance scaling beyond what $\Delta D(s)$ alone captures.

Resources.—This experiment can potentially be performed using *already published data*. Google's Willow experiment [16] reported surface code data at $d = 3, 5, 7$. If the raw syndrome data is available, one can apply different decoders and compute α for each. Similarly, IBM's published surface code experiments may provide suitable datasets.

S13.4: Simulation Methodology

To validate the predictions numerically (Secs. S12–S13.3), we employ the following simulation tools:

stim [25].—Developed by Google Quantum AI, `stim` is a stabilizer circuit simulator that models circuit-level noise including: (i) depolarizing errors on single- and two-qubit gates, (ii) measurement errors, (iii) idle errors during multi-round syndrome extraction, and (iv) hook errors from the circuit geometry. This noise model matches the error structure of real quantum processors and is the same tool used by Google to benchmark the Willow chip [16]. Crucially, `stim` operates at the circuit level rather than using simplified phenomenological or independent identically distributed (i.i.d.) noise models, ensuring that our simulation results are directly comparable to experimental data.

PyMatching [26].—We use `PyMatching v2` as the MWPM decoder, which is the industry-standard decoder for benchmarking surface codes. It constructs a detector error model from the `stim` circuit and performs minimum-weight perfect matching on the syndrome graph.

The combination of circuit-level noise simulation (`stim`) and a standard decoder (`PyMatching`) ensures comparability with real quantum hardware data.

S14. CAVEATS AND LIMITATIONS

Interpretation

The equivalence $\Sigma = 0 \Leftrightarrow \tau = 0$ is a statement about quantum channels and recovery maps. It is agnostic about ontology (block-universe vs. other interpretations) and does not imply retrocausation; the Petz map is a Bayesian inference tool, not a physical process sending information backward. The operational content is that in a closed system ($\Sigma = 0$), statistical predictions are identical whether one conditions on past or future data—the content of the ABL rule [22], here derived from Petz recovery rather than postulated.

"Zero Entropy" is Entropy Production, Not State Entropy

The quantity Σ in our framework is the *entropy production* of the system-environment interaction, not the von Neumann entropy of the system state. Key distinctions:

- A system can have high state entropy ($S(\rho)$ large) but zero entropy production ($\Sigma = 0$) if it evolves unitarily.
- Conversely, a pure state ($S(\rho) = 0$) interacting with an environment can have $\Sigma > 0$.
- The relevant quantity for temporal asymmetry is Σ (process irreversibility), not $S(\rho)$ (state uncertainty).

Measurement Back-Action

Any projective measurement on a quantum system produces entropy: the measurement process couples the system to a macroscopic apparatus (environment), creating $\Sigma > 0$. Therefore:

- Verifying $\tau = 0$ directly requires non-demolition or weak measurements.
- Projective measurement itself breaks the closed-system condition.
- The quantum eraser "resolves" this by deferring the measurement to the idler subsystem, preserving the closed-system condition on the signal-idler pair until the erasure measurement is performed.

Non-Markovian Subtleties

For non-Markovian processes (system-environment memory effects) [21]:

- Σ can be temporarily negative (information backflow from environment to system).
- This corresponds to transient τ decrease: the system partially "reverses" its temporal asymmetry.

- The equivalence chain holds for CP-divisible (Markovian) processes. For non-Markovian dynamics, the chain holds at the level of the total process map but not necessarily at intermediate times.

The individual mathematical ingredients—Petz recovery [2], the Crooks theorem [17], the Fawzi–Renner characterization [6], and entropy production bounds [7, 8]—are established. The new mathematical results are Theorem 3 (saturation characterization) and Theorem 4 (composition sub-additivity). The remaining contributions—the τ definition, the equivalence chain, the eraser calculation, and the τ bound (which restates the Junge et al. bound [4])—are synthesis and interpretation.

S15. EXTENDED NUMERICAL EVIDENCE

We present additional numerical results that strengthen the evidence base beyond the published-data reanalysis of Sec. S13.1.

S15.1: Direct Test of the Retrodiction Landauer Principle

We compute the Petz recovery fidelity F and relative entropy drop ΔD for the amplitude damping channel $\mathcal{N}_\gamma$ with $\gamma \in [0, 1]$, using the maximally mixed reference $\sigma = I/2$. For three input states ($|1\rangle$, $|+\rangle$, and a mixed state with $p = 0.3$), we verify:

$$F(\rho,\, \mathcal{R}_{\sigma,\mathcal{N}_\gamma}(\mathcal{N}_\gamma(\rho))) \geq \exp(-\Delta D/2) \tag{60}$$

at 600 parameter values. All data points satisfy the bound, with near-saturation for the $|1\rangle$ input (which maximizes entropy production).

We also compute predicted $(F, \Delta D)$ values using the *reported experimental parameters* from Singh et al. [23] (NMR, $\gamma = 0.1$–0.9) and Png and Scarani [24] (ion trap, $\gamma = 0.05$–0.5). *Important caveat:* these $(F, \Delta D)$ values are computed from the published damping parameters γ using the theoretical amplitude damping model—they are *not* direct experimental measurements of the Petz recovery fidelity F or the entropy production Σ. Neither experiment simultaneously measured both quantities; Singh et al. measured recovery fidelity for specific circuits, and neither group reported Σ. The comparison here therefore tests consistency of the theoretical framework with reported channel parameters, not a direct experimental verification of the bound. All 41 computed data points satisfy the bound, with NMR points showing $\sim$2% deviations below the theoretical curve (consistent with reported experimental imperfections) and ion-trap points showing $\sim$0.5% deviations. Direct experimental measurement of Petz recovery fidelity and entropy production on the same quantum channel remains an important open direction (see Sec. S13.2 for a concrete proposal).

IBM/Google calibration data.—To ground the bound in realistic hardware parameters, we repeat the calculation using published T_1/T_2 calibration data from five quantum processors: IBM Brisbane ($T_1 = 200\,\mu$s, $T_2 = 150\,\mu$s), IBM Sherbrooke ($T_1 = 260\,\mu$s, $T_2 = 190\,\mu$s), IBM Torino ($T_1 = 180\,\mu$s, $T_2 = 120\,\mu$s), Google Sycamore ($T_1 = 15\,\mu$s, $T_2 = 12\,\mu$s), and Google Willow ($T_1 = 25\,\mu$s, $T_2 = 20\,\mu$s). For each device, 17 input states and 12 wait times yield 204 $(F, \Delta D)$ pairs; across all five devices (1020 total points), 100% satisfy $F \geq \exp(-\Delta D/2)$. We additionally validate against Qiskit's FakeBrisbane noise model (which extracts real calibration data, $T_1 = 237\,\mu$s, $T_2 = 49\,\mu$s from device snapshots), confirming consistency between the analytical amplitude-damping model and the full circuit-level noise simulation.

S15.2: Optimality of the Petz Recovery Map

We explicitly construct the Petz recovery map and compare it against four alternative recovery strategies: (i) identity (do nothing), (ii) reset to σ, (iii) transpose channel, and (iv) state-specific Petz ($\sigma = \rho$). We test on three channels: amplitude damping, depolarizing, and phase damping.

Key findings across 20,250 state-channel pairs:

1. The state-specific Petz map ($\sigma = \rho$) achieves $F = 1$ for all inputs, confirming the Petz sufficiency theorem.

2. Among maps satisfying the retrodiction condition $\mathcal{R}(\mathcal{N}(\sigma)) = \sigma$, the Petz map achieves the highest fidelity at all parameter values.

3. The identity map has higher raw fidelity for small noise parameters, but violates the retrodiction condition for non-unital channels—it is not a valid Bayesian inverse.

4. The bound $F \geq \exp(-\Delta D)$ is satisfied at 100% of tested points.

This demonstrates that the definition $\tau = 1 - F(\text{Petz})$ has operational meaning: the Petz map is provably optimal among retrodiction-consistent recovery maps.

S15.3: Decoder α-Independence (Extended Test)

We test the α-independence prediction at two levels of code distance.

Initial test ($d = 3, 5, 7$, six decoders).—Six decoders (MWPM, Unweighted MWPM, Union-Find, BP+OSD, Greedy nearest-neighbor, Lookup table) are tested on

surface codes $d = 3, 5, 7$ with circuit-level depolarizing noise at $p \in \{0.003, 0.005, 0.007, 0.01, 0.015\}$. The overall coefficient of variation (CV) across all six decoders is 0.46, driven by the Greedy decoder ($\alpha \approx 0$), which is too suboptimal for the factorization ansatz to apply. Among the four functionally distinct decoders (MWPM, Unwt-MWPM, Union-Find, BP+OSD), all pairwise α differences are $\leq 1.4\sigma$.

Extended test ($d = 3$–11, three decoders).—To resolve the asymptotic scaling, we extend to $d \in \{3, 5, 7, 9, 11\}$ with three decoders (MWPM, Unwt-MWPM, Union-Find) at $p \in \{0.003, 0.005, 0.007, 0.01\}$, using `stim` with 30k–100k shots. The mean CV across all noise rates is 0.091, well below the 0.15 threshold for decoder-independence. All pairwise α differences are $\leq 0.62\sigma$. The CV improved 2.4× from the initial test (mean $0.215 \to 0.091$), confirming that the initial scatter was a finite-size effect at small d, not a failure of the prediction.

We characterize this as *supported*: the α-independence prediction holds among all functional decoders tested, with improved statistical significance at larger code distances. Further confirmation with (i) real hardware data and (ii) neural network decoders would strengthen the result.

S15.4: Fixed-Petz-Recovery Non-Markovianity Witness

We introduce and numerically validate a new non-Markovianity witness based on the Petz recovery framework (Prediction 3 of the main text).

Definition.—Fix the Petz recovery map at time t_0: $\mathcal{R}_{t_0} \equiv \mathcal{R}_{\sigma,\mathcal{N}_{t_0}}$. For a time-dependent channel $\mathcal{N}_t$, define:

$$\mathcal{N}_{\text{Petz}} = \int_{dF/dt>0} \frac{dF}{dt}\, dt, \tag{61}$$

where $F(t) = F(\rho_0, \mathcal{R}_{t_0}(\mathcal{N}_t(\rho_0)))$. If $\mathcal{N}_{\text{Petz}} > 0$, the dynamics is non-Markovian.

Physical intuition.—Under Markovian (CP-divisible) dynamics, a fixed recovery map can only degrade over time, so $dF/dt \leq 0$ always. A positive dF/dt signals that information has flowed back from the environment, enabling the old recovery map to perform *better* than expected.

Numerical test.—We simulate the Jaynes–Cummings model with Lorentzian spectral density, parameterized by γ_0/λ (coupling strength / spectral width):

- *Markovian* ($\gamma_0/\lambda = 0.1$): $F(t)$ decreases monotonically. $\mathcal{N}_{\text{Petz}} = 0$. No false positives.
- *Non-Markovian* ($\gamma_0/\lambda = 10$): $F(t)$ oscillates with 26 detected revival intervals. $\mathcal{N}_{\text{Petz}} = 0.304$.
- *Comparison with BLP measure* [21]: Both witnesses detect non-Markovianity in the same parameter regime ($\gamma_0/\lambda \gtrsim 0.9$), with comparable magnitudes.

Advantages over existing witnesses:

1. *Single-state witness*: requires only one input state ρ_0, not optimization over state pairs (as in BLP).
2. *Operational QEC connection*: directly quantifies how much a fixed decoder degrades under non-Markovian noise.
3. *Thermodynamic interpretation*: $dF/dt > 0$ corresponds to transient $\Sigma < 0$ (local entropy production reversal).

S16. AMPLITUDE DAMPING SATURATION: COMPLETE DERIVATION

We provide the complete proof that the amplitude damping channel exactly saturates the Junge et al. recovery bound for fixed-point input states.

S16.1: Setup

The amplitude damping channel $\mathcal{N}_\gamma$ with damping parameter $\gamma \in [0, 1]$ has Kraus operators:

$$E_0 = |0\rangle\langle 0| + \sqrt{1-\gamma}\,|1\rangle\langle 1|, \qquad E_1 = \sqrt{\gamma}\,|0\rangle\langle 1|. \tag{62}$$

The reference state is the maximally mixed state $\sigma = I/2$.

S16.2: Petz map for amplitude damping

Step 1: Channel output on σ.

$$\mathcal{N}_\gamma(I/2) = \frac{1}{2}\big(E_0E_0^\dagger + E_1E_1^\dagger\big) = \frac{1}{2}\begin{pmatrix} 1+\gamma & 0 \\ 0 & 1-\gamma \end{pmatrix} \equiv \frac{1}{2}\big(I + \gamma Z\big). \tag{63}$$

Step 2: Inverse square root. With $a = (1+\gamma)/2$ and $b = (1-\gamma)/2$:

$$\mathcal{N}_\gamma(I/2)^{-1/2} = \operatorname{diag}\big(1/\sqrt{a},\ 1/\sqrt{b}\big). \tag{64}$$

Step 3: Hilbert–Schmidt adjoint. The adjoint $\mathcal{N}_\gamma^\dagger$ satisfies $\operatorname{Tr}[X\,\mathcal{N}_\gamma(Y)] = \operatorname{Tr}[\mathcal{N}_\gamma^\dagger(X)\,Y]$ for all X, Y. From the Kraus operators:

$$\mathcal{N}_\gamma^\dagger(X) = E_0^\dagger X E_0 + E_1^\dagger X E_1. \tag{65}$$

Explicitly, for $X = \begin{pmatrix} x_{00} & x_{01} \\ x_{10} & x_{11} \end{pmatrix}$:

$$\mathcal{N}_\gamma^\dagger(X) = \begin{pmatrix} x_{00} + \gamma\, x'_{00} & \sqrt{1-\gamma}\, x_{01} \\ \sqrt{1-\gamma}\, x_{10} & (1-\gamma)\, x_{11} \end{pmatrix}, \tag{66}$$

where $x'_{00} = 0$ for the off-diagonal contribution from E_1. More precisely:

$$\begin{aligned}
[\mathcal{N}_\gamma^\dagger(X)]_{00} &= x_{00}, \\
[\mathcal{N}_\gamma^\dagger(X)]_{01} &= \sqrt{1-\gamma}\, x_{01}, \\
[\mathcal{N}_\gamma^\dagger(X)]_{10} &= \sqrt{1-\gamma}\, x_{10}, \\
[\mathcal{N}_\gamma^\dagger(X)]_{11} &= (1-\gamma)\, x_{11} + \gamma\, x_{00}.
\end{aligned} \tag{67}$$

Step 4: Petz map. The Petz map $\mathcal{R}_{\sigma,\mathcal{N}_\gamma}$ for $\sigma = I/2$ is:

$$\mathcal{R}(X) = \tfrac{1}{2}\, \mathcal{N}_\gamma^\dagger\big(\mathcal{N}_\gamma(I/2)^{-1/2}\, X\, \mathcal{N}_\gamma(I/2)^{-1/2}\big). \tag{68}$$

S16.3: Ground state input—exact saturation

For $\rho = |0\rangle\langle 0|$:

Channel output: $\mathcal{N}_\gamma(|0\rangle\langle 0|) = |0\rangle\langle 0|$ (the ground state is a fixed point).

Petz recovery: Applying Eq. (68) to $X = |0\rangle\langle 0| = \mathrm{diag}(1, 0)$:

$$\begin{aligned}
Y &= \mathcal{N}_\gamma(I/2)^{-1/2}\, |0\rangle\langle 0|\, \mathcal{N}_\gamma(I/2)^{-1/2} = \mathrm{diag}(1/a,\ 0), \\
\mathcal{N}_\gamma^\dagger(Y) &= \mathrm{diag}(1/a,\ \gamma/a), \\
\mathcal{R}(|0\rangle\langle 0|) &= \frac{1}{2}\, \mathrm{diag}(1/a,\ \gamma/a) = \mathrm{diag}\Big(\frac{1}{1+\gamma},\ \frac{\gamma}{1+\gamma}\Big).
\end{aligned} \tag{69}$$

Fidelity:

$$F^2 = \langle 0|\mathcal{R}(|0\rangle\langle 0|)|0\rangle = \frac{1}{1+\gamma}. \tag{70}$$

Relative entropy drop:

$$\begin{aligned}
D(|0\rangle\langle 0|\|I/2) &= \log 2, \\
D(\mathcal{N}_\gamma(|0\rangle\langle 0|)\|\mathcal{N}_\gamma(I/2)) &= D(|0\rangle\langle 0|\|\mathrm{diag}(a,b)) = -\log a = \log\frac{2}{1+\gamma}, \\
\Delta D &= \log 2 - \log\frac{2}{1+\gamma} = \log(1+\gamma) = \ln(1+\gamma).
\end{aligned} \tag{71}$$

Saturation:

$$\boxed{F^2 = \frac{1}{1+\gamma} = e^{-\ln(1+\gamma)} = e^{-\Delta D}.} \tag{72}$$

The Junge et al. bound $F^2 \geq \exp(-\Delta D)$ is *exactly saturated* for all $\gamma \in [0, 1]$.

S16.4: Unital channels—strict non-saturation

For the dephasing channel $\mathcal{N}_p^{\mathrm{deph}}$ with Bloch contraction $\lambda = 1-2p$, the Petz map reduces to $\mathcal{R} = \mathcal{N}_p^{\mathrm{deph}}$ (self-adjoint, unital). For the equatorial input $\rho = |+\rangle\langle +|$:

$$\begin{aligned}
F^2 &= \langle +|\mathcal{N}_p(\mathcal{N}_p(|+\rangle\langle +|))|+\rangle = (1+\lambda^2)/2, \\
\Delta D &= H_{\mathrm{bin}}\big((1+\lambda)/2\big),
\end{aligned} \tag{73}$$

where $H_{\mathrm{bin}}(x) = -x\ln x - (1-x)\ln(1-x)$ is the binary entropy in nats.

The tightness ratio is:

$$\eta(\lambda) = \frac{F^2}{\exp(-\Delta D)} = \frac{(1+\lambda^2)/2}{\exp(-H_{\mathrm{bin}}((1+\lambda)/2))}. \tag{74}$$

At the boundaries: $\eta(0) = \eta(1) = 1$ (saturated). In the interior $\lambda \in (0, 1)$: $\eta > 1$ strictly (verified analytically by checking $d^2\eta/d\lambda^2 < 0$ at boundary and $\eta > 1$ at $\lambda = 1/2$ where $\eta \approx 1.097$).

The depolarizing channel gives the identical functional form by Bloch-sphere symmetry, with λ replaced by $\mu = 1 - 4p/3$.

S16.5: Physical interpretation

The saturation $F^2 = \exp(-\Delta D)$ for amplitude damping means that the temporal asymmetry parameter $\tau = 1 - F = 1 - 1/\sqrt{1+\gamma}$ exactly equals the information-theoretic lower bound $1 - \exp(-\Delta D/2)$. The arrow of time for this channel-state pair is *tight*: no recovery strategy can do better than the Petz map, and the Petz map achieves exactly the bound.

For unital channels, $\tau < 1 - \exp(-\Delta D/2)$: there is "slack" in the bound, meaning the actual temporal asymmetry is less than what information loss alone would permit. This suggests that unital noise is in some sense "less irreversible" than non-unital noise at the same information loss ΔD.

S17: BOUND SATURATION—IF-AND-ONLY-IF PROOF

We prove Theorem 3 of the main text: a complete characterization of when the Junge et al. bound $F^2(\rho, \mathcal{R}_{\sigma,\mathcal{N}}(\mathcal{N}(\rho))) \geq \exp(-\Delta D)$ is exactly saturated, for $\sigma = I/d$.

S17.1: Statement

Let $\mathcal{N}$ be a CPTP map, $\sigma = I/d$ the maximally mixed state, and $\rho = |\psi\rangle\langle\psi|$ a pure state. Write $\omega = \mathcal{N}(\rho)$ and $\tau = \mathcal{N}(\sigma)$. Then

$$F^2\big(\rho,\, \mathcal{R}_{\sigma,\mathcal{N}}(\mathcal{N}(\rho))\big) = \exp(-\Delta D) \tag{75}$$

if and only if:

(i) $[\omega, \tau] = 0$ (channel outputs commute);

(ii) $\omega_i/\tau_i = c$ for all i with $\omega_i > 0$ (constant likelihood ratio on support).

When these hold, $F^2 = c/d$ and $\Delta D = \ln(d/c)$.

S17.2: Proof

Step 1: Petz map for $\sigma = I/d$. With $\sigma = I/d$, the Petz map (**??**) simplifies to

$$\mathcal{R}_{\sigma,\mathcal{N}}(\cdot) = \frac{1}{d}\mathcal{N}^\dagger\big(\tau^{-1/2}\,(\cdot)\,\tau^{-1/2}\big). \tag{76}$$

Step 2: Fidelity as arithmetic mean. For pure $\rho = |\psi\rangle\langle\psi|$, the recovery fidelity is

$$F^2 = \langle\psi|\mathcal{R}_{\sigma,\mathcal{N}}(\omega)|\psi\rangle = \frac{1}{d}\,\mathrm{Tr}\big[\omega\,\tau^{-1/2}\omega\,\tau^{-1/2}\big]. \tag{77}$$

When (i) holds, ω and τ are simultaneously diagonalizable with eigenvalues $\{\omega_i\}$ and $\{\tau_i\}$, giving

$$F^2 = \frac{1}{d}\sum_{i:\,\tau_i>0}\frac{\omega_i^2}{\tau_i}. \tag{78}$$

Writing $x_i = \omega_i/\tau_i$ (the likelihood ratios), this is a weighted arithmetic mean: $F^2 = \frac{1}{d}\sum_i \omega_i\, x_i$.

Step 3: Relative entropy drop as geometric mean.

$$\begin{aligned} D(\omega\|\tau) &= \sum_i \omega_i \ln(\omega_i/\tau_i) = \sum_i \omega_i \ln x_i, \\ D(\rho\|\sigma) &= \ln d, \\ \Delta D &= \ln d - D(\omega\|\tau). \end{aligned} \tag{79}$$

Therefore

$$\exp(-\Delta D) = \frac{1}{d}\exp\bigg(\sum_i \omega_i \ln x_i\bigg) = \frac{1}{d}\prod_i x_i^{\omega_i}, \tag{80}$$

which is a weighted geometric mean of $\{x_i\}$ (divided by d).

Step 4: AM–GM gives the bound and its saturation. By the weighted arithmetic-mean/geometric-mean inequality,

$$\sum_i \omega_i\, x_i \;\geq\; \prod_i x_i^{\omega_i}, \tag{81}$$

with $\sum_i \omega_i = 1$. Hence $F^2 \geq \exp(-\Delta D)$. The AM–GM inequality is saturated if and only if all x_i with $\omega_i > 0$ are equal, i.e., $\omega_i/\tau_i = c$ for some constant c. This is condition (ii).

Step 5: Non-commutativity gives strict inequality. When (i) fails ($[\omega,\tau] \neq 0$), the scalar AM–GM argument of Step 4 does not directly apply because ω and τ have no joint eigenbasis. In this case, $F^2 = \frac{1}{d}\,\mathrm{Tr}[\omega\,\tau^{-1/2}\omega\,\tau^{-1/2}]$ involves the non-commutative product $\tau^{-1/2}\omega\,\tau^{-1/2}$, while $\exp(-\Delta D) = \frac{1}{d}\exp\big(\mathrm{Tr}[\omega\ln\omega - \omega\ln\tau]\big)$ involves the matrix logarithm. We verify strict inequality $F^2 > \exp(-\Delta D)$ numerically: among 5×10^5 random non-commuting (ω,τ) pairs in dimensions $d \in \{2,3,4,5\}$, zero achieve saturation (minimum gap: $> 10^{-6}$). A fully analytical proof that $[\omega,\tau] \neq 0$ precludes saturation is left as an open problem.

Combining: Saturation $F^2 = \exp(-\Delta D)$ holds iff (i) $[\omega,\tau] = 0$ *and* (ii) ω_i/τ_i is constant on $\mathrm{supp}(\omega)$. □

S17.3: Sufficient-statistic interpretation

In classical statistics, a statistic T is *sufficient* for discriminating P from Q if and only if the likelihood ratio dP/dQ is constant on each level set of T (Fisher–Neyman factorization theorem). Conditions (i)–(ii) are the quantum analogue: the channel $\mathcal{N}$ acts as a *quantum sufficient statistic* for the pair $(\rho, I/d)$, meaning it preserves the distinguishability ratio uniformly on the support.

This connects to the Petz sufficiency theorem [2]: exact DPI saturation ($\Delta D = 0$) implies exact Petz recovery ($F = 1$). Our result characterizes a weaker condition—saturation of the *bound* $F^2 = \exp(-\Delta D)$ rather than exact recovery $F = 1$—and shows it corresponds to a weaker form of sufficiency where the likelihood ratio is constant but not necessarily equal to 1.

S17.4: Examples

(a) Amplitude damping, ground-state input. $\mathcal{N}_\gamma^{\mathrm{AD}}$ with $\rho = |0\rangle\langle0|$: $\omega = |0\rangle\langle0|$ (rank 1), $\tau = \mathrm{diag}((1+\gamma)/2,\,(1-\gamma)/2)$. Ratio: $\omega_0/\tau_0 = 2/(1+\gamma) = c$. Only one term in the support, so (ii) is trivially satisfied. $F^2 = c/2 = 1/(1+\gamma)$. Saturated.

(b) Completely depolarizing channel. $\mathcal{N}(\rho) = I/d$ for all ρ: $\omega = \tau = I/d$, ratio $c = 1$, $F^2 = 1/d$. Saturated for all pure inputs.

(c) Amplitude damping, excited-state input. $\rho = |1\rangle\langle1|$: $\omega = \mathrm{diag}(\gamma, 1-\gamma)$, $\tau = \mathrm{diag}((1+\gamma)/2,\,(1-\gamma)/2)$. Ratios: $2\gamma/(1+\gamma) \neq 2(1-\gamma)/(1-\gamma) = 2$ for $\gamma \neq 0$. Not saturated.

(d) Depolarizing channel, $0 < p < 1$. $\mathcal{N}_p(\rho) = (1-p)\rho + p\,I/d$: ratios generically unequal. Not saturated.

S17.5: Numerical verification

The if-and-only-if characterization is verified numerically in `numerical/iff_saturation_rigorous.py`: 5×10^4 random channel-state pairs in dimensions $d \in \{2,3,4,5\}$, testing both directions of the equivalence. Results: zero false positives (no pair satisfies (i)–(ii) but violates saturation) and zero false negatives (no pair saturates without satisfying (i)–(ii)). Accuracy: 100% over all 5×10^4 trials.

Additionally, the specific channel families (amplitude damping, completely depolarizing, complement of amplitude damping, pure loss bosonic, three-level decay) are verified in `numerical/saturation_verification.py`: 46/46 tests pass.

S18: COMPOSITION SUB-ADDITIVITY—PROOF AND NUMERICS

S18.1: Statement

For sequential channels $\mathcal{N}_1, \mathcal{N}_2$, reference σ, and any state ρ:

$$\sqrt{\tau_{12}} \;\leq\; \sqrt{\tau_1} + \sqrt{\tau_2^{\text{eff}}}, \tag{82}$$

where τ_{12}, τ_1, and τ_2^{eff} are defined in the main text (Theorem 4), with τ_2^{eff} evaluated at evolved state $\mathcal{N}_1(\rho)$ and updated reference $\mathcal{N}_1(\sigma)$.

S18.2: Proof

Define:

$$\begin{aligned} \rho_1 &= \mathcal{R}_{\sigma,\mathcal{N}_1}(\mathcal{N}_1(\rho)), \\ \rho_{12} &= \mathcal{R}_{\sigma,\mathcal{N}_2\circ\mathcal{N}_1}((\mathcal{N}_2\circ\mathcal{N}_1)(\rho)). \end{aligned} \tag{83}$$

Step 1: Functoriality. By the Parzygnat–Buscemi theorem [1]:

$$\mathcal{R}_{\sigma,\mathcal{N}_2\circ\mathcal{N}_1} = \mathcal{R}_{\sigma,\mathcal{N}_1} \circ \mathcal{R}_{\mathcal{N}_1(\sigma),\mathcal{N}_2}. \tag{84}$$

Step 2: Bures triangle inequality. The Bures distance $d_B(\rho,\sigma) = \sqrt{1 - F(\rho,\sigma)}$ is a metric, so:

$$d_B(\rho,\rho_{12}) \leq d_B(\rho,\rho_1) + d_B(\rho_1,\rho_{12}). \tag{85}$$

The left side is $\sqrt{\tau_{12}}$ and the first term on the right is $\sqrt{\tau_1}$.

Step 3: Data-processing bound on the second term. By functoriality, $\rho_{12} = \mathcal{R}_{\sigma,\mathcal{N}_1}(\mathcal{R}_{\mathcal{N}_1(\sigma),\mathcal{N}_2}(\mathcal{N}_2(\mathcal{N}_1(\rho))))$. Since $\rho_1 = \mathcal{R}_{\sigma,\mathcal{N}_1}(\mathcal{N}_1(\rho))$, both ρ_1 and ρ_{12} are images of $\mathcal{R}_{\sigma,\mathcal{N}_1}$. By contractivity of fidelity under CPTP maps:

$$\begin{aligned} F(\rho_1,\rho_{12}) &\geq F\big(\mathcal{N}_1(\rho),\, \mathcal{R}_{\mathcal{N}_1(\sigma),\mathcal{N}_2}(\mathcal{N}_2(\mathcal{N}_1(\rho)))\big) \\ &= 1 - \tau_2^{\text{eff}}. \end{aligned} \tag{86}$$

Therefore $d_B(\rho_1,\rho_{12}) \leq \sqrt{\tau_2^{\text{eff}}}$, completing the proof. □

S18.3: Failure of the naive version

If one defines $\tau_2^{\text{naive}} = 1 - F(\rho, \mathcal{R}_{\sigma,\mathcal{N}_2}(\mathcal{N}_2(\rho)))$ using the original state ρ and reference σ (instead of the evolved ones), the inequality $\sqrt{\tau_{12}} \leq \sqrt{\tau_1} + \sqrt{\tau_2^{\text{naive}}}$ *fails*: numerical tests find violations in 2/1000 random channel pairs (worst margin: -0.030).

S18.4: The rotated Petz map violates composition

The rotated Petz map $\tilde{\mathcal{R}}(\cdot) = \int dt\, p(t)\, \sigma^{it}\mathcal{R}(\mathcal{N}(\sigma)^{-it}(\cdot)\mathcal{N}(\sigma)^{it})\sigma^{-it}$ of Ref. [4] does *not* satisfy the functoriality axiom (**??**) and consequently violates the composition inequality (82). Numerical tests (`numerical/composition_verification.py`) find violations for non-unital channel pairs: $\sim 10\%$ failure rate for amplitude damping pairs, with worst violation margin -0.0046. No violations are found for unital channel pairs (dephasing, depolarizing).

This provides a new structural distinction: the standard Petz map uniquely "decomposes time correctly," while the rotated Petz map achieves tighter recovery bounds at the cost of breaking compositional consistency.

S18.5: Numerical verification

The composition inequality is verified in `numerical/composition_verification.py`: 0 violations in 1338 structured tests (qubit and qutrit channels) and 0 violations in 1000 random qubit channel pairs. Petz functoriality is confirmed to machine precision (max trace distance error: 8.44×10^{-16}).

* akai@fawstudio.com

[1] A. J. Parzygnat and F. Buscemi, Quantum **7**, 1013 (2023).
[2] D. Petz, Q. J. Math. **39**, 97 (1988).
[3] M. M. Wilde, Proc. R. Soc. A **471**, 20150338 (2015).
[4] M. Junge, R. Renner, D. Sutter, M. M. Wilde, and A. Winter, Ann. Henri Poincaré **19**, 2955 (2018).
[5] H. Barnum and E. Knill, J. Math. Phys. **43**, 2097 (2002).
[6] O. Fawzi and R. Renner, Commun. Math. Phys. **340**, 575 (2015).
[7] A. Kolchinsky and D. H. Wolpert, J. Stat. Mech. **2017**, 083202 (2017).
[8] D. Reeb and M. M. Wolf, New J. Phys. **16**, 103011 (2014).
[9] H. Kwon and M. S. Kim, Phys. Rev. X **9**, 031029 (2019).
[10] S. C. Smith, B. J. Brown, and S. D. Bartlett, Commun. Phys. **7**, 386 (2024).
[11] L. H. English, D. J. Williamson, and S. D. Bartlett, Phys. Rev. Lett. **135**, 120603 (2025).
[12] L. H. English, S. Roberts, S. D. Bartlett, A. C. Doherty, and D. J. Williamson, arXiv:2512.10399 (2025).
[13] H. Chen, D. Xu, G. M. Sommers, D. A. Huse, J. D. Thompson, and S. Gopalakrishnan, arXiv:2510.05222 (2025).
[14] A. deMarti iOlius *et al.*, Quantum **8**, 1498 (2024).
[15] J. Bausch, A. W. Senior *et al.*, Nature **635**, 834 (2024).
[16] R. Acharya *et al.* (Google Quantum AI), Nature **638**, 920 (2025).
[17] G. E. Crooks, Phys. Rev. E **60**, 2721 (1999).
[18] W. H. Zurek, Rev. Mod. Phys. **75**, 715 (2003).
[19] H. D. Zeh, Found. Phys. **1**, 69 (1970).

[20] G. T. Landi and M. Paternostro, Rev. Mod. Phys. **93**, 035008 (2021).
[21] H.-P. Breuer, E. M. Laine, J. Piilo, and B. Vacchini, Rev. Mod. Phys. **88**, 021002 (2016).
[22] Y. Aharonov, P. G. Bergmann, and J. L. Lebowitz, Phys. Rev. **134**, B1410 (1964).
[23] G. Singh, R. S. Sahani, V. Jagadish, L. Lautenbacher, N. K. Bernardes, and K. Dorai, "Realizing the Petz recovery map on an NMR quantum processor," arXiv:2508.08998 (2025).
[24] W.-H. Png and V. Scarani, "Petz recovery maps of single-qubit decoherence channels in an ion trap quantum processor," Phys. Rev. A **112**, 022613 (2025).
[25] C. Gidney, "Stim: A fast stabilizer circuit simulator," Quantum **5**, 497 (2021).
[26] O. Higgott and C. Gidney, "Sparse Blossom: Correcting a million errors per core second with minimum-weight matching," Quantum **9**, 1600 (2025).
[27] G. Bai, F. Buscemi, and V. Scarani, "Fully quantum stochastic entropy production," arXiv:2412.12489 (2024).