

OBJECTIVES:

Upon completion of these exercises the student will be able to:

- Modify Trouble Tickets
- Attach a Work Order to a Trouble Ticket
- View how Resolution is associated to NIM-R
- Collecting more information on alarms using the Historical Alarm Handling window
- Launch the Ericsson Sub Network Managers from NS-T
- Understand the processes that lead to the clearing of alarms in NS-T
- Apply his/her knowledge to real life scenarios

Table of Contents

Topic	Page
-------	------

FAULT RESOLUTION	ERROR! B
TROUBLE TICKET HANDLING	3
ATTACHING A WORK ORDER	3
ASSOCIATING RESOLUION TO NIM-R	4
COLLECTING MORE INFORMATION ON ALARMS	4
LAUNCHING THE SUB NETWORK MANAGERS	4-5
CLEARING ALARMS IN NS-T	5
SCENARIOS	5-

FAULT RESOLUTION

TROUBLE TICKET HANDLING

1. Create a TTR on an Alarm. Follow the instructions on page 21 of the Alarm Surveillance Student Text if you need some help.
2. Modify this TTR from the Iconic Map of NS-T. *This integration is currently not available and therefore these instructions need to be added here when a customer purchases this integration.* Write an action in the Work Log. To do this click on the Add button to the right of the Work Log. A Work Log entry box appears and here you can add operator notes. Automatically the Work Log is updated with information. View this information.
3. What information has been added automatically?

-
4. View the Full Alarm Information. This information is retrieved from the Alarms tab in the Modify window. It links the TTR to the actual FM alarm.

ATTACHING A WORK ORDER (WO)

The work needed to solve a problem can involve several people. To support this, work orders can be attached to a TTR. Each WO is assigned to a certain group or person.

1. In the TTR Modify window, click Attach WO.
2. Describe some work that can be carried out.
3. Click Select Field Technician.
4. In the dialogue box that appears, specify the required skill in the Skill field and specify the region where the work shall be carried out in the Region field. Select one of the Field Technicians on the list, Choose FT, then click Save.
5. Click Save in the WO

6. View the Work Order Relations by selecting the Work Order Relations Tab. Here you can see that the WO is seen as the child of a TTR.

ASSOCIATING RESOLUTION TO NIM-R

These exercises need to be written when a customer purchases this integration. Currently, this is a theoretical integration.

COLLECTING MORE INFORMATION ON ALARMS

1. In Not Closed Alarm handling window Select an alarm to add note ->Operation -> Set Operator Note... If there is not a Trouble Ticketing tool then here you can add information to an alarm in NS-T. Does NS-T add automatically extra information to the operator note?

2. How does this compare with Resolution Work Log Entries?

3. Open the Historical Alarm Handling window. List the 3 possible ways to do this. Observe the 3 ways.

4. Set a filter on your chosen OC and apply to view the historical alarm list. Become familiar with this process.

LAUNCHING THE SUB NETWORK MANAGERS (SNM)

1. Launch RANOS. Select RANOS icon in the Iconic Map. From the Operations main menu select Launch RANOS Sub Network Manager from the drop down menu.

2. Login to RANOS using the Login ID given to you by the instructor.
3. Take time to browse through the applications and become familiar with the system e.g. View the real time alarm list (if the system is live).
4. Launch CN-OSS. Select CN-OSS in the Iconic Map. From the Operations main menu select Launch CN-OSS Sub Network Manager from the drop down menu.
5. Login to CN-OSS using Login ID given to you by the instructor.
6. Take time to browse through the applications and become familiar with the system e.g. View the real time alarm list (if the system is live).

CLEARING ALARMS IN NS-T

- 1) Locate a cleared alarm in the Not-Closed Alarm Window or in the Alarm View Window.
- 2) View Alarm Details.
- 3) When was this alarm cleared? What is the name of the parameter that gives the cleared time?

- 4) When was the alarm raised? What is the name of that parameter?

- 5) If you are on a live system find a cleared alarm with an associated trouble ticket. See if you can find out how the fault was repaired and thus the alarm cleared.

SCENARIOS

Scenario 1.

In this scenario there are two participants. One of you are the surveillance technician, Sven, the other one is the field technician, Filip.

There are two versions of the scenario; with or without Resolution.

Scenario with Resolution:

- 1) Ask the instructor to send scenario 1 alarms to your OC.
- 2) Sven: Look at the equipment alarm. Using your expertise you determine that the faulty board has to be replaced.
- 3) Sven: Create a new trouble ticket associated to the alarm as you have learned in earlier exercises.
- 4) Sven: If NIM-R is integrated select “Import site data” in the TT. If NIM-R not used add site data manually. In a real system it can probably be fetched by launching the Sub-Network Manager and navigating to the correct site using information from the alarm. In this case enter “Site = Instructors desk”.
- 5) Sven: Create a work order in the Trouble Ticket stating that the alarming board has to be replaced, assign the Work Order to Filip of our group.
- 6) Sven: Leave the Work Order and Trouble Ticket. (Should TT also be assigned to Filip or to self?)
- 7) Filip: Check your Resolution work list in Resolution. Open your new Work Order.
- 8) Filip: Go to the site given (Instructors Desk) in the Work Order and replace the board (Tell the instructor about it)
- 9) Filip: Back at the terminal mark the Work Order as completed.
- 10) Sven: Check your Resolution work list. Open your Trouble Ticket.
- 11) Sven: Note that the associated Work Order is completed.
- 12) Sven: Check the original alarm. It should now be cleared. (Clear icon appears). Check full information for clearance flag and clearance time stamp, if you like.
- 13) Sven: Mark Trouble Ticket as closed.
- 14) Check the original alarm it should now show the closed icon and then disappear from the Not-Closed alarm list. If things go too fast for you, you can study the alarm in the alarm view window.

Scenario without Resolution:

- 1) Ask the instructor to send scenario 1 alarms to your OC.
- 2) Sven: Look at the equipment alarm. Using your expertise you determine that the faulty board has to be replaced.

- 3) Acknowledge the alarm.
- 4) Sven: Start an email and enter enough information about the alarm to make it identifiable.
- 5) Sven: Enter site data into the email. In a real system site data can probably be fetched by launching the Sub-Network Manager and navigating to the correct site using information from the alarm. In this case enter “Site = Instructors desk”.
- 6) Sven: Write an instruction that you want the specific board replaced in the e-mail
- 7) Sven: Find out from a list or similar who is on duty. Sent the e-mail to that person. In this case Filip of your group.
- 8) Filip: Check your e-mail. Open your new e-mail.
- 9) Filip: Go to the site given (Instructors Desk) in the e-mail and replace the board (Tell the instructor about it)
- 10) Filip: Back at the terminal replay to the e-mail indicating that the task is completed.
- 11) Sven: Check your e-mail. Open your new e-mail.
- 12) Sven: Locate the original alarm using the information in the e-mail.
- 13) Sven: Check the original alarm. It should now be cleared. (Clear icon appears) and then disappear from the Not-Closed alarm list. If things go to fast for you, you can study the alarm in the alarm view window.