Firewall Configuration

🔥 Firewall Configuration Reference

Proper firewall configuration is essential for GCXONE to communicate with your devices. This reference provides the exact IPs, ports, and domains required for a secure and functional installation.

Without whitelisting the primary gateway IPs, the GCXONE platform will be unable to receive alarms or heartbeat signals from your hardware.

🌐 Mandatory IP Addresses

These addresses must be whitelisted for **Outbound** traffic from your device network.

Primary Gateways

Service IP Address Purpose **GCXONE Gateway (Primary)** `18.185.17.113` Main platform communication **GCXONE Gateway (Backup)** `3.124.50.242` Failover and redundancy **Messaging Services** `3.127.50.212` Secure event delivery

Video Streaming Servers

Service IP Address Usage **Streaming Node 1** `3.126.237.150` Primary WebRTC node **Streaming Node 2** `3.75.73.51` Fallback streaming **Streaming Node 3** `18.156.39.63` Regional overflow

🔌 Required Ports & Protocols

Ensure these ports are open for the specified protocols.

Port Range Protocol Service Usage **80** HTTP Web Redirects Initial connection handshake **443** HTTPS/WSS Core API Secure dashboard & WebSockets **554** RTSP Video Stream Fallback for legacy viewers **5671 / 5672** AMQPS Messaging Secure event delivery (TLS) **10001 - 10500** UDP/TCP WebRTC Dynamic ports for video streaming **123** UDP NTP Time synchronization **WebRTC Port Range:** The 10001-10500 range is required for peer-to-peer video negotiation, ensuring the lowest possible latency during live monitoring.

🏢 Manufacturer-Specific Receivers

If you are using these specific brands, whitelist their dedicated alarm receivers:

| Brand | IP Address | Role | | :--- | :--- | :--- | | **Hikvision** | `35.156.60.98` | Alarm Receiver | | **Dahua** | `52.59.60.20` | Alarm Receiver | | **Hanwha** | `18.184.110.24` | Alarm Receiver | | Brand | IP Address | Role | | :--- | :--- | :--- | | **Milestone** |

`3.66.98.181` | VMS Bridge | | **Camect** | `3.122.169.231` | Smart Hub Receiver | | **Uniview** | `18.158.140.99` | Alarm Receiver | | **Heitel** | `3.123.206.197` | Gateway (Live) |

🛠️ Connectivity Diagnostics

Use these commands from a workstation on the same network as your devices to verify access:

ping 18.185.17.113

Check API access

---

telnet 18.185.17.113 443

Check streaming node

---

telnet 3.126.237.150 10001

Related Articles

Next: