

OPERATIONAL PLAN | LTSA LCY-LTSA-GAL-2026

OPERATIONS AND MAINTENANCE PLAN (O&M)

BESS SYSTEM - GALASCOPE 1 AND GALASCOPE 2

Implementation document for Tier C services: 24/7 monitoring, preventive and corrective maintenance, incident response, availability guarantee and preservation of OEM warranty rights.

Field	Value	Field	Value
Project	Galascope 1 / Galascope 2	Status	REV.3 - DRAFT FOR REVIEW
BESS Capacity	20 MWh + 10 MWh = 30 MWh	BESS AC Power	5.0 MW + 2.5 MW = 7.5 MW
Technology	Linyang Power Atlantic 5 MWh, LFP	EMS/SCADA	DISPERON
Service Level	Tier C (default from PAC)	O&M Contractor	Lighthief Cyprus Ltd
Client	Galascope Ltd	Document Type	Plan O&M
Base Document	LTSA v4.7 / Annex LT-2	Governing LTSA Language	English

DOCUMENT STATUS: Working version following investor review. The Plan becomes a controlled document once the pre-PAC conditions have been closed, the duty roster has been approved and the Parties have signed it. The final controlled version for the Client shall be issued in English. In the event of conflict, the LTSA shall prevail and, within the LTSA, Annex LT-2 shall prevail.

Document Control Table

Revision	Change Description	Prepared by	Approved by
Rev.0	Initial project plan based on LTSA v4.7 and the Lighthief draft	Lighthief	[TO BE COMPLETED]
Rev.1	EOA data, BESS capacities, locations, permits, site obligations and named list of responsible persons	Lighthief	[TO BE COMPLETED]
Rev.2	Investor review: SLA, PAC conditions, availability, spares, SOH/RTE and stop-clock	Lighthief	[TO BE COMPLETED]
Rev.3	GPS coordinates (Galascope 1 & 2) and PCS/Transformer/MVS technical data completed from SA-13/SA-14; RMU brand confirmed Mingyang	Lighthief	[TO BE COMPLETED]

	(Linyang/Costas, Aug 2026) [13 Aug 2026: corrected LTSA version citation from v6.5 to v4.3] [14 Aug 2026: LTSA further revised to v4.6 (Annex LT-2 fully integrated inline) — citation updated accordingly.] [18 Aug 2026: LTSA further revised to v4.7 (fixed Schedule/Annex-V6 drafting artifacts) — citation updated accordingly.]		
--	--	--	--

Contents and Document Map

Section	Scope
1	Status, Purpose, Basis and Document Hierarchy
2	Project Data and System Boundaries
3	Tier C Service Scope and Exclusions
4	Responsible Persons, RACI and Communication
5	Pre-PAC Mobilisation and Operational Readiness
6	24/7 Monitoring, SCADA/EMS and Operational Control
7	Alarms, SLA, Escalation and Incident Management
8	Preventive Maintenance Programme
9	Corrective Maintenance and Work Control
10	HSE, Fire Safety, Environment and Emergency Response
11	Spare Parts, Warehouse and Obsolescence
12	Availability, SOH, RTE and Warranty Management
13	Reporting, Data and Cybersecurity
14	Regulatory Compliance, DSO and Competence
15	Quality, Audits and Improvement
16	Service Completion and Handover
A-D	Schedules, checklists, matrices and source registers

1. STATUS, PURPOSE, BASIS AND DOCUMENT HIERARCHY

1.1 Purpose of the Plan

This O&M Plan translates the LTSA provisions into a practical operating system for the two BESS Parks, covering monitoring, on-call organisation, maintenance planning, alarm response, work records, warranty management, spare parts and regulatory compliance. It applies to Lighthief personnel, subcontractors and all persons performing activities within the O&M system boundaries.

1.2 Document Basis and Order of Precedence

- LTSA LCY-LTSA-GAL-2026, version v4.7, together with Schedules 1-5.
- Annex LT-2 - Agreed Technical & Service Amendments; where it conflicts with the main body, Annex LT-2 shall prevail.
- EPC Agreement LCY-EPC-GAL-B1-2026, OEM Direct Warranty Undertaking, OEM Warranty Terms, Technical Agreements, EMS Subscription Agreement and the approved Linyang OEM instructions.
- EOA Submission Documents package dated 07.08.2026: designer declarations, BESS site plans dated April 2026, approval certificates, building permits and conditions, CERA/RAEK exemptions, lease agreements, title deeds, cadastral plans and powers of attorney for plots 71/73 and 471/520.
- Current site procedures: Emergency Response Plan, LOTO, permits to work, fire protection plan, cybersecurity procedures and DSO/EAC requirements.

CONTROL PRINCIPLE: Any change to OEM instructions, BMS/PCS/EMS/SCADA configuration, DSO requirements or warranty conditions triggers a review of this Plan and the relevant checklists. No activity outside the OEM instructions may be performed without prior OEM authorisation.

1.3 Controlled Status and Reviews

Event	Required Action
Before PAC	Complete all open fields, the asset register, contacts, spare-parts list and HSE documents.
At least annually	Review of the Plan by the O&M Manager, discipline leads and the Client representative.
After a major incident	Update following RCA, closure of corrective actions and approval of changes by the Parties.
After a technical/regulatory change	Assess the impact on warranty, safety, SCADA, DSO and the PM schedule.
After a permit/site-layout change	Update the Permit Register, site plan, roads, drainage, fencing, security measures and environmental obligations.
After a contractual change	Issue a new revision with a change log and formal approval.

1.4 Operational Definitions

Term	Operational Meaning
PAC	Provisional Acceptance Certificate; commencement of Tier C service for the relevant Park.
Park	Galascope 1: 5.0 MW / 20 MWh BESS adjacent to a 5.0 MWp PV plant, plots 71/73; Galascope 2: 2.5 MW / 10 MWh BESS adjacent to a 2.5 MWp PV plant, plots 471/520.
EOA	District Local Government Organisation of Famagusta - the competent building/local authority for the

	documentation covered by this Plan.
CERA / RAEK	Cyprus Energy Regulatory Authority / Ρυθμιστική Αρχή Ενέργειας Κύπρου.
Restoration Time	Time from detection to restoration of safe operating capability, including partial capability.
Resolution Time	Time from detection to permanent repair/replacement, recommissioning and incident closure.
Critical / Major / Minor Alert	Alarm class determined by the impact on safety, availability, performance and warranty.
SOH / SOC / RTE	Battery state of health / state of charge / round-trip efficiency.
Unavailable Hours	Time during which the BESS cannot operate at rated power for reasons included under the LTSA.
Warranty-Preservation File	A complete, auditable set of warranty-preservation evidence for each Park.

2. PROJECT DATA AND SYSTEM BOUNDARIES

2.1 Baseline Configuration

Item	Galascope 1	Galascope 2	Remarks
Capacity	20 MWh	10 MWh	Total 30 MWh
Reference PV Plant	5.0 MWp	2.5 MWp	Confirmed in CERA/RAEK exemptions E2674/2020 and E2673/2020
BESS AC Power	5.0 MW	2.5 MW	In accordance with the 5 MW and 2.5 MW project designations in the EOA package; confirm PCS ratings in the as-built documentation
Location	Foinitzi, Avgorou, Famagusta 35°03'53.8"N 33°51'30.0"E	Kerimis, Avgorou, Famagusta 35°03'52.0"N 33°51'47.9"E	GPS per site coordinates provided Aug 2026. Distance to nearest coastline (Famagusta Bay, NE, straight-line — not surveyed): Galascope 1 ≈ 10.0 km, Galascope 2 ≈ 9.7 km.
Plots / plan / section	71 and 73 / 2-278-381 and 2-278-382 / 12	471 and 520 / 2-278-381 / 03	In accordance with title deeds, powers of attorney and EOA

			certificates
Plot Area	60,093 m ² + 59,159 m ²	13,500 m ² + 26,775 m ²	Registered plot areas; these do not represent the entire area occupied by the BESS
Battery Containers	4 × Linyang Power Atlantic 5 MWh	2 × Linyang Power Atlantic 5 MWh	Configuration derived from 20/10 MWh; tags and serial numbers from the asset register
Chemistry / Parameters	LFP, 5,015 kWh/container	LFP, 5,015 kWh/container	12P416S; 45 kW liquid cooling
PCS / Transformer / MVS	4× Kehua PCS BCS1250K-C-HUD (skid: BCS5000K-C-HUD/T4), 5,000 kW 1× step-up transformer 5,000 kVA 22/0.69 kV, oil-immersed, Dy11 1× auxiliary transformer 250 kVA 0.69/0.38 kV, dry-type, Dyn11 1× RMU: Mingyang, 24 kV, SF6-free, 630 A	2× Kehua PCS BCS1250K-C-HUD (skid: BCS2500K-C-HUD/T2), 2,500 kW 1× step-up transformer 2,500 kVA 22/0.69 kV, oil-immersed, Dy11 1× auxiliary transformer 125 kVA 0.69/0.38 kV, dry-type, Dyn11 1× RMU: Mingyang, 24 kV, SF6-free, 630 A	Per SA-13/SA-14 Technical Agreements v6.5 and OEM.rmu in portfolio-data.ts. RMU brand confirmed Mingyang (Aug 2026, Linyang/Costas). Serial numbers from FAT reports/asset register.
EMS/SCADA	DISPERON	DISPERON	Local and global access, DSO interface
CERA/RAEK Exemption for PV	E2674/2020; 14.04.2020-13.04.2050	E2673/2020; 14.04.2020-13.04.2050	Modification/expansion of the plant requires the applicable regulatory procedure
PAC / Warranty Start	[TO BE COMPLETED]	[TO BE COMPLETED]	Separately for each Park

2.2 Locations and Site Infrastructure

Element	Galascope 1 - plots 71/73	Galascope 2 - plots 471/520
Access	Old Larnaca-Famagusta road; 4 m and 6 m entrance gates; internal roads and unpaved sections.	Public and internal road; 4 m gates; designated parking and access to the EAC room.
Fencing / Security	2.10 m fencing, CCTV, lighting and laser-barrier points.	2.10 m fencing, CCTV, lighting, laser barriers and lightning-protection points.
Water / Drainage	Registered stream No. 303 between the plots; 4 m × 0.30 m channels and cable trenches - no interference with the stream.	Maintain effective stormwater drainage and protect the road reserve and access to EAC infrastructure.
Surroundings	Agricultural Zone G2; approximately 2	Kerimis location in Avgorou; control

	km from Vrysoulles	public access at the site
	and approximately 200 m from the Monastery of Agios Kendeas.	boundary.
BESS Plans	Plots 71/73 plan, April 2026; C35 foundations, B420C reinforcing steel.	Plots 471/520 plan, April 2026; C35 foundations, B420C reinforcing steel.

BESS EOA STATUS: The package contains designer declarations and BESS plans dated April 2026 prepared for the Special Exemption Order 2026 procedure, but it does not contain final confirmation of EOA acceptance/approval for the BESS scope. Before work starts and before PAC, this item shall be closed in the Permit Register and an approved set of stamped drawings/as-built documentation shall be obtained.

2.3 Technical Boundaries and Interface Responsibility

The O&M scope covers the BESS, BMS, PCS, MV/MVS switchgear, transformers within the contractual scope, auxiliary systems, HVAC/liquid cooling, fire detection and suppression systems, SCADA gateway, EMS, DSO telemetry and all interconnections and control functions between these systems. Lighthief is responsible for end-to-end BMS-PCS-SCADA-EMS compatibility, communications, command execution and data integrity throughout the service period. Failure of an affiliate, DISPERON or a subcontractor does not release Lighthief from this responsibility towards the Client.

EXTERNAL BOUNDARY: Grid issues beyond the point of connection, unagreed civil works and third-party equipment may be excluded from the calculation only to the extent that they directly caused the relevant consequences. Monitoring, diagnosis, safe disconnection, impact mitigation, documentation and warranty-claim support remain required.

2.4 Asset and Configuration Register

- Asset register per Park: tag, manufacturer, model, serial number, firmware version, warranty date, location and spare part reference.
- Single-line electrical diagram, communication architecture, point list, Modbus / IEC 61850 / IEC 60870-5-104 maps and approved protection settings.
- List of user accounts, permissions and remote access rights, including the owner of each account and the review date.
- Post-PAC baseline: SOC/SOH, usable AC capacity, RTE, thermal condition, cell imbalance, alarms, software versions and C5 coating condition.

3. TIER C SERVICE SCOPE AND EXCLUSIONS

3.1 Services Covered by the Plan

Area	Execution Scope
Monitoring 24/7/365	Data collection, alarming, classification, initial diagnosis, notifications and technical on-call duty.
Preventive Maintenance	Monthly remote checks, quarterly on-site visits, quarterly

	health checks and semi-annual and annual tests.
Corrective Maintenance	Diagnosis, labour, travel within Cyprus, dismantling/reassembly, configuration restoration, testing and documentation.
PCS and MVS	Service and fault handling for the Tier B scope included in Tier C.
Emergency Response	Priority response times, isolation, dispatch, restoration and incident reporting.
Availability	97% annual group-level guarantee for G1+G2, with each Park tracked in parallel.
Spare Parts	Local stock of critical components in Cyprus, with replenishment and storage-condition control.
OEM Warranty	Preservation of warranty conditions, evidence files, claims management and annual performance tests.
Reports and Data	Monthly, quarterly and annual reports, raw-data export, incident registers and availability calculations.
Compliance	DSO/EAC testing, fire safety, environment, cybersecurity and audit documentation.
Site Infrastructure	Routine inspection of access roads, gates, fencing, fauna passages, drainage, the stream, security systems and housekeeping; non-routine civil repairs require a separate order.

3.2 Exclusions and Classification Rules

- Customisation and non-standard expansion of the EMS beyond the standard configuration.
 - Third-party equipment outside the EPC scope and grid issues beyond the point of connection.
 - Damage directly caused by Force Majeure, the Client, vandalism or an unauthorised modification.
 - Civil, structural and site infrastructure works beyond routine maintenance.
 - Replacement of major components outside warranty/SOH coverage - subject to separate quotation.
- Each exclusion must be supported by causal evidence identifying the event, extent of impact, period, technical evidence and classification rationale. The Client may reasonably challenge the classification. An exclusion does not limit the duty to take immediate protective action and minimise damage.

4. RESPONSIBLE PERSONS, RACI AND COMMUNICATION

4.1 Named List of Responsible Persons

Person	Role	Responsibility under the O&M Plan
Marcin Niedośpał	O&M Site Manager	Overall service delivery, Client interface, operational safety, escalations, PM schedule, permit/lease register and

		report approval.
Taras Rybak	Remote Monitoring Manager	Organisation of 24/7 monitoring, duty rosters, alarms, KPIs, platform continuity and shift escalations.
Mateusz Kasprzyk	SCADA System Operator	Continuous monitoring, alarm acknowledgement, authorised commands, shift log, telemetry quality and local dispatch.
Andrzej Lechowicz	EMS Engineer	EMS logic, BMS-PCS-SCADA-DSO integration, operating schedules, command diagnostics and configuration change control.
Wojciech Czyż	O&M Electrical Manager	Electrical supervision, MV/LV, LOTO/PTW, protection, measurements, thermography, DSO/EAC and acceptance of electrical work.
Kacper Góral	Electrician	Field work, PM/CM, measurements, connection inspections, fault rectification and work records.
Maciej Lachowski	HVAC Manager	Liquid cooling/HVAC, thermal performance, filters, fans, alarms and the auxiliary-equipment repair plan.
Zbigniew Janik	Mechanical Engineer	Containers, locks, seals, fixings, corrosion, mechanical components and support for heavy replacements.
Mateusz Kozieł	Civil Engineer	Foundations, roads, drainage, the stream, fencing, fauna passages and site-layout compliance with EOA plans.
Dimos	External Electrical Designer	Design support, settings and technical/DSO coordination within the formally commissioned scope.

The table above identifies responsible persons and does not constitute the full shift roster. Telephone numbers, e-mail addresses, deputies, emergency numbers and availability periods shall be finalised in the controlled contact and duty roster before PAC. Official reports and notices to the Client shall be issued in English unless the Parties agree otherwise in writing; English remains the governing language of the LTSA.

4.2 Key Responsibilities

Area	Responsible Persons	Scope
Management and HSE	Marcin Niedośpiał	Single point of contact, operational decisions, escalations, emergency plan, HSE coordination and action closure.
Monitoring / SCADA / EMS	Taras Rybak, Mateusz Kasprzyk, Andrzej Lechowicz	24/7 alarms, safe control, data integrity, EMS/SCADA and shift handover.
Electrical	Wojciech Czyż, Kacper Góral, Dimos	MV/LV, PTW/LOTO, protection, measurements, DSO, works and post-repair testing.
HVAC / Mechanical	Maciej Lachowski, Zbigniew Janik	Thermal performance, cooling, containers and mechanical components.
Site / Civil / EOA	Mateusz Kozieł	Foundations, drainage, roads, fencing, the stream and site compliance with permit conditions.
Client	Person appointed by Galascope Ltd	Safe access, site documents, internet connectivity, compliant operation, no unauthorised modifications and required insurance.

4.3 RACI Matrix

Process	A	R	C	I
Monitoring and Alarm Classification	Taras Rybak	Mateusz Kasprzyk	Andrzej Lechowicz / Marcin Niedośpiał	Client
PM Plan and Visits	Marcin Niedośpiał	Relevant Discipline Leads	OEM	Client
Critical Incident	Marcin Niedośpiał	Mateusz Kasprzyk + relevant lead	OEM / DSO / emergency services	Client / Lender's IE
Warranty Claim	Marcin Niedośpiał	Relevant Technical Lead	OEM / Client	Lender IE
Monthly Report	Marcin Niedośpiał	Taras Rybak / Mateusz Kasprzyk	Discipline Leads	Client
EMS/SCADA/Settings Change	Marcin Niedośpiał	Andrzej Lechowicz / Mateusz Kasprzyk	Wojciech Czyż / Dimos / DSO / OEM	Client
Site / EOA Compliance	Marcin Niedośpiał	Mateusz Kozieł	Wojciech Czyż / designer	Client

Spare-Parts Warehouse	Marcin Niedosiał	Relevant Technical Lead	OEM	Client
-----------------------	------------------	-------------------------	-----	--------

A - Accountable, R - Responsible, C - Consulted, I - Informed.

5. PRE-PAC MOBILISATION AND OPERATIONAL READINESS

O&M readiness is a condition for the safe takeover of each Park. Each Park shall pass a separate readiness gate. An open item blocks takeover unless the Client accepts in writing an interim plan identifying the owner, deadline and risk controls.

Gate	Acceptance Criterion	Owner	Status
EOA / Permits	Final acceptance of the BESS scope, stamped drawings, authority conditions and no unresolved deviations.	O&M Manager	[]
As-Built Documentation	GPS, SLD, communication diagrams, datasheets, instructions, settings, certificates and FAT/SAT/PAC protocols.	O&M Manager	[]
Asset register	Complete asset list, serial numbers, firmware, warranties, locations and photographs.	Back Office	[]
Monitoring	SCADA/EMS/BMS/PCS online, time synchronisation, point-to-point testing, alarms, redundant channels and notification test.	SCADA	[]
Cybersecurity	MFA, RBAC, named accounts, VPN, logs, configuration backups and emergency-access procedure.	SCADA / IT	[]
HSE / ERP	Site-specific ERP, LOTO, PTW, PPE, SDS, 6 m fire-access roads, isolation maps and an emergency-services drill.	HSE	[]
Local Team	Duty roster, deputies, Cypriot qualifications, Linyang training, EMS/SCADA and fire-safety training.	O&M Manager	[]

Spare-Parts Warehouse	Signed min/max list, part numbers, ownership, compatibility, storage, replenishment and evidence of availability.	Back Office	[]
PCS / Transformer	Approved major-component failure strategy: stock, OEM pool, replacement unit or binding lead time.	O&M Manager	[]
Baseline	98.5% SOH at COD (LTSA reference), AC capacity, RTE, thermal performance, cell imbalance and C5 condition.	OEM / O&M	[]
SOH/RTE Protocol	Signed protocol: AC measurement point, auxiliary energy, temperature, C-rate, rest period, data and validity criteria.	OEM / O&M	[]
External Contacts	Client, DSO/EAC, Fire Service, security, OEM, DISPERON, transport and crane provider.	O&M Manager	[]
Warranty File	Folder structure, report templates, required photographs/measurements and 15+5-year retention method.	Back Office	[]

PRE-PAC CLOSURE CONDITIONS: Closure evidence is the document identified in the controlled PAC Readiness Register and accepted by the relevant owner and the Client. Absence of evidence means the item remains open. The critical-spares list, SOH/RTE protocol, final EOA/as-built documents, ERP readiness and PCS/transformer strategy shall be closed before PAC or covered by a written, accepted interim plan.

6. 24/7 MONITORING, SCADA/EMS AND OPERATIONAL CONTROL

6.1 Monitored Parameters

Group	Minimum Scope
Battery	Cell voltage and temperature; string and container SOC/SOH; current; power limits; cell imbalance; BMS alarms.
PCS / MVS / Transformer	Status, trips, P/Q, efficiency, voltage, current, temperature, protection and availability.
Thermal Systems	HVAC/liquid cooling, temperatures, flow/status, filters, fans

	and alarms.
Safety	Fire and gas detection, suppression readiness, E-stop, door interlock and auxiliary power.
Communications	BMS-PCS-EMS-SCADA, gateway, internet, time synchronisation, data loss and telemetry quality.
EMS / Dispatch	Command execution, power limits, schedules, zero-export (if applicable) and integration errors.
DSO / EAC	P, Q, V, I, f, SOC, SOH, remote commands, IEC 60870-5-104, PQDIF and COMTRADE.
Environment / Cybersecurity	Ambient temperature, humidity, access events, configuration changes and firmware integrity.

6.2 Monitoring Centre Operating Routine

- Continuous monitoring of dashboards and the alarm queue; each alarm shall have a source timestamp.
- Acknowledge and classify in accordance with Section 7; failure to acknowledge triggers automatic escalation.
- Remote response shall be performed only by authorised persons and in accordance with the approved procedure.
- The shift log shall include active alarms, power limitations, open work orders, spare-part status and required follow-up actions.
- Shift handover requires acknowledgement by the incoming person; Critical and Major alarms shall also be handed over verbally.
- A monitoring platform failure is a Major Alert and becomes a Critical Alert if it affects safety.

6.3 Warranty Protection Thresholds

Parameter / Condition	Operating Threshold	Action
Cell Voltage - Pre-Alarm	< 2.9 V	Automatic alarm; immediate trend assessment and safe recharge plan.
Cell Voltage - Warranty Void	< 2.8 V for 120 h	Prevent occurrence; Critical escalation and SOC restoration plan.
Under-Voltage - Warranty Void	≤ 2.5 V, any occurrence	Immediate isolation/protection, OEM notification and incident report.
SOC During Standstill	> 5%	Maintain above the threshold; low-SOC alarm.
Long-Term Standstill	30-50% SOC	Set before a long shutdown in accordance with OEM instructions.
Charging Temperature	0 to +55°C	Pre-alarm 5°C from the limit; derate/stop in accordance with BMS/OEM.
Discharging Temperature	-20 to +55°C	Pre-alarm 5°C from the limit; derate/stop in accordance with BMS/OEM.
Humidity	> 90% RH alarm; max.	Check sealing, condensation and

	95% RH	HVAC; do not open in adverse weather.
--	--------	---------------------------------------

6.4 Command and Configuration Change Control

- Start/stop, P-set, Q-set and zero-export commands shall be positively confirmed and recorded in the log.
- Any change to protection settings requires designer/DSO approval and a four-eyes check.
- Firmware/software updates require OEM authorisation, a backup, rollback plan, service window and functional test.
- Every change shall be entered in the configuration register, identifying who, when, reason, version before/after, test result and approval.
- Remote control functionality and telemetry completeness shall be tested monthly.

7. ALARMS, SLA, ESCALATION AND INCIDENT MANAGEMENT

7.1 Alarm Classification

Class	Criterion	Examples
Critical	Immediate risk to people, the environment or warranty, or total/material loss of safe operation.	Fire/thermal event, gas, E-stop, ≤ 2.5 V, full Park outage, safety-related loss of monitoring.
Major	Material impact on performance or reliability without an immediate safety threat.	PCS trip, HVAC fault, communication loss, partial outage, monitoring platform unavailable.
Minor	Non-critical fault that can be handled on a planned basis.	Minor sensor anomaly or punch-list item with no impact on operation.
Informational	Event for trend analysis with no intervention required.	Status change, operating record or diagnostic alert.

7.2 Operational SLA Target Matrix

The matrix separates notification time, remote response, on-site attendance, safe restoration and permanent resolution. These are operational targets used to organise the O&M service. Liability thresholds, service credits and legal remedies remain exclusively governed by the LTSA and Annex LT-2 unless the Parties expressly agree otherwise in writing.

Stage	Critical	Major	Minor
Client Notification	Telephone + e-mail ≤ 30 min	E-mail ≤ 2 h	Next Report
Acknowledgement / Remote Response	Ack ≤ 30 min; immediate isolation if required	Remote response ≤ 4 h	Remote response ≤ 12 h during working hours
On-Site Attendance	≤ 4 h if required; safety-critical 24/7	≤ 6 h if required	Next visit or ≤ 5 business days
Restoration Plan	≤ 4 h	≤ 1 business day	In the work order

Safe Restoration	≤24 h where technically feasible	≤5 business days	Next visit
Permanent Resolution	≤5 business days unless OEM parts are required	≤15 business days	Next visit or ≤30 days
Status Updates	At least every 2 h until stabilisation	In accordance with the repair plan	In the report / work order

SLA AND STOP-CLOCK RULES: The Critical on-site attendance target of ≤4 h is an enhanced operational target under this Plan. For Major events, the ≤6 h attendance target does not amend the service-credit threshold in LTSA §8.5. Stop-clock or excluded hours may be applied only to the extent of direct causation, supported by timestamps, correspondence and other evidence, following prompt notification and Client acceptance. Unilateral reclassification of time is not permitted. If a restoration or resolution target cannot be met, a written recovery plan shall be issued stating the reason, revised deadline and risk-mitigation actions.

7.3 Incident Handling Workflow

1. Detect and retain the alarm source timestamp.
2. Acknowledge and classify the event and assess the risk to people, warranty and availability.
3. Apply safe isolation or shutdown where required and authorised.
4. Notify the Client and the relevant persons in the escalation matrix.
5. Perform remote diagnosis, secure the logs and open a work order.
6. Initiate local/OEM/DSO/emergency-services dispatch and confirm site access.
7. Restore safe partial or full operating capability and document any limitations.
8. Complete the permanent repair, recommissioning and functional test.
9. Determine the root cause and define corrective and preventive actions.
10. Close the incident after evidence acceptance, register updates and submission of the Client report.

7.4 Major Incident

The Major Incident Procedure applies to fire/thermal events, repeated trips, forced outages exceeding 24 hours, cyber incidents, grid-code breaches, warranty-threatening events or unavailable capacity exceeding 10% of a Park.

- Client notification - immediately.
- Initial incident report - within 24 hours.
- Secure logs, photographs, alarms, configurations and witness information.
- RCA after stabilisation; the deadline, owner and action plan shall be stated in the initial report.
- Provide updates until closure and assess the impact on Availability, SOH, warranty, DSO and insurance.

8. PREVENTIVE MAINTENANCE PROGRAMME

8.1 Planning Principles

- Four quarterly visits per year for each Park, at intervals of approximately three months.
- Plan at least 30 days in advance; the preferred low-dispatch window is 04:00-08:00 local time.

- Total Scheduled Downtime shall not exceed 48 h per Park per year; exceeding 48 consecutive hours requires the Client's prior written consent, except in a safety emergency.
- Container doors shall not be opened during rain, snow, fog, high humidity or excessive wind.
- The scope of each activity shall follow the current OEM instructions; stricter requirements shall prevail.
- A visit not completed because of weather shall be promptly rescheduled and recorded, without interruption to monitoring continuity.

8.2 Baseline Frequencies

Frequency	Scope	Owner
Continuous / Each Shift	Alarms, communications, dispatch, limitations, safety status and handover log.	SCADA / Duty Tech
Monthly - Remote	Container status, BMS backup, run-data/parameter/log capture, software review, telemetry and command test.	SCADA
Quarterly - Remote	SOH trend, degradation, thermal performance, cell imbalance, communications, data integrity and recommendations.	SCADA + Electrical
Quarterly - On Site	Inspection of BESS/PCS/MVS/transformer, thermography, balancing, HVAC, fire systems, connections, relays, sensors, alarms and C5 protection.	Local Team
Every 6 Months	Cable screens, SPDs, fuses, copper busbars and connections.	Electrical
Annually	Earthing $\leq 4 \Omega$, insulation $> 1 \text{ M}\Omega$, protection, SCADA, fire systems, E-stop, SOH/capacity/RTE and cyber-access review.	Discipline Leads + OEM
Event-Driven	Alarm, OEM recommendation, serial defect, recall, firmware/regulatory change or trend result.	O&M Manager

8.3 Scope of the Quarterly Visit

- Visual inspection of enclosures, structures, foundations, connections, seals, moisture and contamination.
- Thermal imaging of electrical connections and switchgear under an appropriate load condition.
- Verification of module balancing, BMS and cell voltages and temperatures.
- Inspection and cleaning of cooling systems: filters, fans, intake/outlet, sensors and abnormal noise.
- Check readiness of detection/suppression, E-stop, interlocks, signage and fire-service access.
- Check cable terminations and tightening torques against OEM values.
- Functional test of protection, relays, sensors, meters and communications.

- Review of alarms, firmware and OEM-approved updates.
- C5 protection: coatings, salt deposits, grilles, seals, drains, surfaces, hinges and fasteners, with photographs.
- Restore configuration, complete post-work testing, close doors and confirm monitoring.

8.4 PM Completion Evidence

A work order is considered complete only after attaching the checklist, before/after photographs, measurements, thermograms, tightening torques, test results, parts/consumables list, names and qualifications of personnel, downtime, deviations, recommendations and the verifier's signature.

9. CORRECTIVE MAINTENANCE AND WORK CONTROL

9.1 CM Scope

Under Tier C, Corrective Maintenance includes diagnosis, labour, travel within Cyprus, safe dismantling and reassembly, configuration restoration, testing, recommissioning and incident documentation for the BESS, PCS, BMS, MVS, SCADA gateway and associated control systems. Parts costs are governed by the warranty, spares and LTSA exclusion provisions.

9.2 Work-Order Control

Stage	Minimum Data / Gate
Opening	Number, Park/tag, alarm source, timestamp, class and impact on safety/availability/warranty.
Work Plan	Scope, method, risks, LOTO/PTW, PPE, parts, personnel, OEM/DSO approval and rollback plan.
Execution	Times, measurements, photographs, parts, serial numbers, configurations before/after and deviations.
Post-Repair Test	Protection/interlocks, communications, commands, thermal stability and no active alarms.
Restoration	Safe partial/full operation, limitations, post-work monitoring and Client notification.
Closure	Cause, CAPA, warranty status, availability coding and updates to the asset/spares/configuration registers.

9.3 Permit to Work and LOTO

- Before work: risk assessment, PTW, identification of energy sources and confirmation of competence and weather conditions.
- Before work on a rack, disconnect all MSDs; release locking mechanisms before disconnecting the pack plug.
- Each person shall apply their own lock; the de-energised state shall be verified using the appropriate instrument and procedure.
- Work near hazardous energy shall be performed only by authorised personnel wearing the required PPE and with a safety observer where required by the risk assessment.

- After work: check tools and foreign objects, reconnect MSDs, test interlocks, close doors and have lock owners remove their LOTO devices.

10. HSE, FIRE SAFETY, ENVIRONMENT AND EMERGENCY RESPONSE

10.1 Overriding Safety Rules

STOP WORK: Every person has the right and duty to stop work in the event of uncontrolled energy, a fire/gas alarm, signs of thermal runaway, inadequate PTW/LOTO/PPE, adverse weather or unclear configuration. Work may resume only after reassessment and authorisation.

- Access is restricted to authorised persons; maintain entry/exit records and key control.
- Maintain current SDS, OEM instructions, evacuation plan, assembly points and 112/Fire Service contact numbers.
- Keep fire-access roads clear, with a minimum width of 6 m.
- Keep extinguishers and detection/suppression systems ready and within their inspection dates.
- Do not attempt firefighting or open a container during a thermal event except within roles and procedures approved by the OEM and emergency services.

10.2 Response to Fire Alarm / Thermal Event

1. Do not approach the container or open the doors; warn persons nearby.
2. Initiate the alarm, evacuation and emergency-services call in accordance with the ERP.
3. Apply remote E-stop/isolation only where safe and provided for by the procedure.
4. Provide emergency services with the location, LFP chemistry, SDS, diagram, stored energy, suppression status and possible adjacent hazards.
5. Secure the zone and 6 m access; do not permit re-entry without approval from the incident commander/HSE.
6. Preserve logs, monitoring, images and communications; initiate the Major Incident Procedure.

10.3 Environment

- Prevent uncontrolled leaks and emissions; respond to spills in accordance with the site plan.
- Maintain cooling systems in accordance with F-gas requirements where applicable.
- Record and secure damaged batteries, electrical/electronic waste and other hazardous waste and transfer them only to licensed recipients.
- Maintain vegetation and remove dry biomass to reduce fire risk without affecting protected areas or environmental conditions.
- On plots 71/73, do not interfere with registered stream No. 303; monitor its flow, erosion and signs of contamination and promptly escalate deviations.
- Maintain fencing and fauna passages in accordance with approved plans; for plots 471/520, inspect 50 × 25 cm openings spaced every 70-100 m and ensure there are no sharp edges.
- Maintain drainage, roads and the site to minimise flooding, corrosion, dust and unauthorised access; do not store materials outside designated areas.

11. SPARE PARTS, WAREHOUSE AND OBSOLESCENCE

11.1 Local Tier C Warehouse

The Cyprus warehouse shall maintain the agreed minimum stock of critical components sufficient to remedy typical faults within 24 hours. For each item, record the part number, compatibility, application, min/max quantity, condition, location, storage conditions, expiry date, lead time and replenishment deadline.

Parts Group	Minimum Scope	Control
BMS / Communications	BMS controllers, communication modules, gateway and sensors.	ESD, firmware/compatibility, test after issue
Cooling	Fans, filters, sensors and agreed liquid-cooling components.	Storage conditions, sealing and dates
Electrical	Fuses, contactors, SPDs, protection components and minor connections.	Rating, certificates and shelf life
PCS	Control boards and agreed power modules.	Model/version and OEM approval
Battery	Balancing equipment and OEM-approved parts.	SOC/storage and traceability
PM Materials	Filters, cleaning agents, fasteners and protective C5 lubricants.	Min/max and consumption per visit

The minimum critical-spares list requires written acceptance before PAC and shall identify, for each item, the owner, location, min/max quantity, replenishment deadline and periodic verification method. Full PCS units and transformers need not be stocked unless separately agreed, but the failure strategy shall identify stock, an OEM pool, a replacement unit or a binding lead time. A declared four-week OEM delivery period shall qualify as mitigation only upon presentation of written, binding OEM confirmation. Failure to maintain the agreed stock or critical strategy constitutes Service Provider default, and the resulting downtime shall be classified as Unavailable.

11.2 Replenishment, Warranty Parts and Obsolescence

- Issue of a part automatically generates a replenishment reservation/purchase and updates the stock ledger.
- A removed part shall be labelled with the fault tag, retained pending the OEM decision and linked to the warranty claim.
- Warranty components shall be supplied at no additional cost in accordance with OEM terms; Lighthief shall manage the claim and evidence.
- Replacement of major components outside warranty/SOH coverage is subject to a separate quotation.
- For at least 15 years, support the availability of compatible parts and firmware; replacements shall be equivalent or better without loss of warranty, certification or grid-code compliance.

12. AVAILABILITY, SOH, RTE AND WARRANTY MANAGEMENT

12.1 Availability

The contractual Availability guarantee remains as stated in the LTSA: 97% per year at G1+G2 group level. For investor transparency, each Park is also reported separately together with an additional non-binding capacity- weighted group indicator. The additional indicators do not increase the Service Provider's guarantee or liability without a written LTSA amendment.

LTSA CONTRACTUAL FORMULA: Group Availability [%] = SUM(Available Hours per Park) / SUM(Total Hours per Park) × 100.
Total Hours are counted for each Park from its PAC: 8,760 h per year or 8,784 h in a leap year, pro rata in the first year.

Indicator	Calculation Method / Status
Availability G1	Reported separately for Galascope 1; diagnostic KPI and basis for remediation.
Availability G2	Reported separately for Galascope 2; diagnostic KPI and basis for remediation.
Group Availability LTSA	Contractual hourly indicator calculated in accordance with the LTSA; annual target ≥97%.
Capacity-weighted Availability	$100 \times [1 - \text{SUM}(\text{Unavailable MW} \times \text{h}) / \text{SUM}(\text{Rated MW} \times \text{Total h})]$; reporting indicator without separate service credits.

Time Category	Rule
Unavailable	Inability to operate at rated power due to equipment failure, Service Provider-caused downtime, waiting for parts/repair or a culpable SCADA/EMS interface fault.
Scheduled Downtime	Previously agreed shutdown; operational limit of 48 h per Park/year.
Grid / Curtailment	Excluded where directly caused by a grid/operator instruction and properly documented.
Client / Third Party / Force Majeure	Excluded only to the extent of direct causation; the clock is stopped for the documented period.
No Dispatch	Does not constitute unavailability if the BESS remains technically capable of operation.
EMS/SCADA	Included where the cause is attributable to Lighthief/DISPERON, configuration, integration, gateway, firmware or cyber controls and prevents dispatch/monitoring/DSO operation.

Each time exclusion from the calculation requires event identification, start and end timestamps, the direct cause, source evidence and Client acceptance. Disputed items remain included until agreed. The monthly report shall list all adjustments, and the annual report shall include joint agreement of the final calculation. If

the Availability of either Park falls below 95% in a year, below 97% for two consecutive years, or at least three Critical SLA breaches occur in a 12-month period, the O&M Manager shall initiate a remediation plan, independent technical audit and review of additional stock.

12.2 SOH and Performance Testing

Year	Minimum SOH - 1 Cycle/Day	Condition
COD	98,50%	Initial Reference
1	94,62%	OEM curve / operating conditions
2	91,77%	OEM curve / operating conditions
3	89,91%	OEM curve / operating conditions
4	88,00%	OEM curve / operating conditions
5	86,78%	Base warranty
10	79,58%	Only if the Years 6-10 extension is selected and paid for
15	73,61%	Only if the Years 11-15 extension is selected and paid for

SOH, usable AC capacity and RTE shall be measured at least annually in accordance with the OEM/EPC protocol signed before PAC. The protocol shall unambiguously define the AC measurement point, treatment of auxiliary energy, temperature and tolerance, C-rate, initial and final SOC, rest period, meter calibration, complete required data set, validity criteria and repeat-test rules. The Client and the Lender's Independent Engineer may witness the test. The result shall be delivered as an SOH Certificate and the performance report within 10 business days after the test.

- LTSA reference conditions: 20-25°C, full charge/discharge cycle at C/3 and 2 h rest between charge and discharge - to be confirmed against the current OEM protocol before testing.
- If the result deviates from the curve, preserve raw data, cycle history, temperatures, power limits, firmware and events that may affect warranty coverage.
- The remedy includes parts, labour, installation, recommissioning, testing, documentation and data updates; Lighthief shall actively manage and document the OEM claim.
- Annual confirmation of the validity of the OEM warranty reserve, extended warranty, parts availability and support shall form part of the Annual Review.
- Any OEM dispute, insolvency risk, supply restriction, recall, safety notice or firmware issue affecting the project shall be reported to the Client within 5 business days.

12.3 Warranty-Preservation File

- PM/CM checklists and work orders
- photographs and C5 coating condition
- torque records
- thermograms
- earthing and insulation measurements
- firmware and configuration register
- alarms, SOC and logs
- environmental data

- fire-system and E-stop tests
- parts and traceability
- OEM correspondence/claim
- SOH/RTE/capacity certificates
- personnel qualification evidence
- Client/DSO notification evidence

13. REPORTING, DATA AND CYBERSECURITY

13.1 Reporting Package

Document	Deadline / Frequency	Minimum Content
Shift Handover Log	Each Shift	Alarms, limitations, work orders, actions, parts and persons responsible for follow-up.
Critical/Major Notification	≤30 min / ≤2 h	Event, impact, protective actions, ETA and owner.
Initial Major Incident Report	≤24 h	Timeline, safety condition, downtime, data, preliminary cause and RCA plan.
Monthly Performance Report	≤10 business days after month-end	Throughput, G1/G2 Availability, group and capacity-weighted indicators, SOC/SOH, KPIs, alarms, PM/CM, parts and downtime.
Quarterly Health Report	≤15 business days after quarter-end	Degradation, thermal performance, cell imbalance, firmware, recommendations and warranty risks.
PM / CM Report	After Each Work Activity	Checklist, results, photographs, measurements, post-work test, punch list and parts.
SOH / Performance Report	Annually; ≤10 business days after the test	SOH, usable AC capacity, RTE, protocol, conditions and certificate.
Annual Availability Calculation	≤15 business days after year-end	Per Park, LTSA group and capacity-weighted indicators; included/excluded hours, evidence and LD basis.
Annual Review Report	≤30 days after the PAC anniversary	Benchmark, maintenance, warranties, cybersecurity, spares, regulations and next-year plan.

Monthly, quarterly and annual reports shall also include raw-data extracts, the incident log, justification of excluded hours, Availability per Park and in aggregate, SOH trend, cell imbalance, thermal deviation, firmware/software versions, open punch items, parts consumption, warranty notices, cyber/security events and recommendations.

13.2 Data Ownership, Access and Retention

- The Client owns all operational, technical, market, dispatch, SCADA/BMS/PCS, SOH and Availability data.
- The Client shall have continuous secure access to current and historical data and the right to export it at no additional charge.
- Retention: at least 15 years from the Commissioning Date and 5 years after termination of the LTSA, in formats accepted by Linyang and the competent authorities.
- Client-identifiable data shall not be used for benchmarking, training, product development or third parties without prior written consent.
- Documentation shall be delivered in editable format where reasonably available, including settings files, point lists, protocol maps, firmware and certificates.

13.3 ICS Cybersecurity

Control	Requirement
Identity	MFA, named accounts, RBAC, least privilege and no shared passwords except for the break-glass account.
Remote Access	Encrypted VPN/secure access, approved devices, time-bound access and session logging.
Data	Encryption in transit and at rest, configuration backup, restoration testing and integrity control.
Changes	Change request, approval, backup, firmware integrity, testing and rollback.
Monitoring	Audit logs, access alerts, telemetry loss, anomaly review and retention.
Vulnerability Management	Vulnerability register, impact assessment, OEM patches, implementation plan and risk exceptions.
Review	Access review at least annually and after each personnel change/incident.
Incident	Isolation, evidence preservation, Client notification, RCA and controlled recovery.

The control framework should align with IEC 62443 principles; the formal scope of IEC 62443 / NIS2 certification shall be confirmed with DISPERON and the ICS suppliers before controlled Rev.2 is issued.

14. REGULATORY COMPLIANCE, DSO AND COMPETENCE

14.1 Permit, Licence and Lease Register

Document / Condition	Galascope 1 - 5.0 MWp	Galascope 2 - 2.5 MWp	O&M Control
CERA/RAEK operating exemption	E2674/2020; 14.04.2020-13.04.2050	E2673/2020; 14.04.2020-13.04.2050	Annual review; apply for extension at least 3 months before expiry.
EOA approval certificate	P1 139876 dated 25.02.2026; certificate noting a container on plot	P1 139841 dated 25.02.2026; PV completion confirmed in	Protect the approved configuration; maintain a register of

	73.	accordance with the permits.	deviations and approvals.
BESS submission 2026	Designer declaration and plots 71/73 plans dated April 2026.	Designer declaration and plots 471/520 plans dated April 2026.	Obtain final EOA approval/acceptance and stamped drawings; update after any change.
Lease / land right	Lease from 01.11.2018 to 2039; right to two five-year extensions.	Leases from 01.11.2018 to 2039; renewal rights in accordance with the agreements.	Annual review; alerts 24/12/6 months before the required action date.
Decommissioning	Remove the installation at end of life; the fencing remains with the owner; permit conditions require site reinstatement.	Remove the installation and reinstate the site; the permit specifies a deadline of 6 months after PV operation ceases.	Maintain a current decommissioning plan, cost estimate and materials/waste register.

REGULATORY CHANGE CONTROL: Modification of the plant requires the applicable permit/licence amendment; expansion requires a new building/regulatory procedure. A change of ownership requires an application to CERA/RAEK at least 3 months in advance. Disposal of or creation of security over a material asset with replacement value above EUR 200,000 requires at least one month's prior notice and the applicable consent/no objection. A planned closure shall be notified at least 12 months in advance where circumstances permit.

14.2 Site Obligations from EOA Documentation

Area	Control Requirement	Frequency / Evidence
Access and EAC	Keep roads, gates, parking, access strips and routes to EAC rooms/substations clear throughout the year.	Each visit; photographs and work orders for defects.
Fencing / Fauna	Maintain the 2.10 m fence free of damage; keep fauna passages clear, without sharp edges or trapping hazards.	Quarterly and after storms/events.
Drainage / Stream	Keep drains and channels clear; no erosion, ponding or contamination; no interference with stream No. 303.	Quarterly and after heavy rain.
Fire Safety / Vegetation	Remove dry biomass, keep fire-access roads clear, maintain extinguishers and systems ready and cooperate with the Fire Service.	Monthly during the dry season; each visit.
Waste	Transfer WEEE, batteries, oils/coolants and other waste only to licensed	For each consignment; quarterly report.

	entities; maintain a complete transfer record.	
Site Security	Maintain CCTV, laser barriers, lighting, locks and lightning protection operational; no unauthorised structures.	Monthly remotely / quarterly on site.
Approved Configuration	Containers, foundations, roads and equipment located in accordance with stamped drawings/as-built documentation.	After changes and during the annual audit.

14.3 Testing and Operational Obligations

Area	Activity	Frequency / Deadline
Protection	Test all protection-relay functions.	Annually
Earthing	Measure resistance; result $\leq 4 \Omega$.	Annually
Insulation	Measure insulation resistance; result $> 1 M\Omega$.	Annually
SCADA	Verify P, Q, V, I, f, SOC and SOH signals and the IEC 60870-5-104 link.	Annually + continuous monitoring
Control	Test P-set, Q-set, start/stop and zero-export, if applicable.	Monthly
Power quality	Availability of PQDIF and COMTRADE data.	Continuous / after an event
Fire Safety	Detection, suppression, pressure, E-stop and extinguishers.	Each visit / as required by law
Permit / Lease Register	Status of EOA/CERA approvals, conditions, leases, designer insurance and renewal dates.	Quarterly + deadline alerts
Site	Access, gates, fencing, fauna passages, drainage, stream, CCTV/lighting and waste.	Each visit / after an event
DSO Planned Outage	Notification of the planned outage.	At least 7 days in advance
DSO Fault	Fault report within 24-48 h; emergency outage notified immediately by telephone + e-mail.	Event-Driven
Authority Inspection	Provide personnel and documents within 5 business days and close findings.	On request

The regulatory basis has been adopted in accordance with the LTSA: the laws of Cyprus, EAC Technical Guide for Storage 2025, EAC Universal Technical Guide for RES 2025 and fire-safety and environmental

requirements. Before controlled Rev.2 is issued, confirm that all legal and technical references are current and applicable.

14.4 Qualifications and Training

- Current Cypriot electrical authorisations/competence appropriate to the work scope.
- Linyang OEM training on the BESS, BMS, warranty limitations and maintenance manual.
- Training on PCS/MVS, EMS/SCADA, IEC 60870-5-104 and approved settings.
- HSE: HV/LV safety, LOTO/PTW, arc flash/PPE according to the risk assessment, work near batteries and first aid.
- Fire and emergency response, including drills with the local Fire Service and knowledge of SDS.
- Cybersecurity and secure remote access; refresher training after a system change/incident.

15. QUALITY, AUDITS AND IMPROVEMENT

15.1 Management KPIs

KPI	Control Method	Target / Trigger
Group Availability LTSA	Monthly and annually; G1+G2 weighted by hours.	≥97% annually - contractual guarantee
Park Availability	G1 and G2 separately; monthly and rolling 12 months.	<95%/year triggers remediation
Capacity-weighted Availability	1 - SUM(Unavailable MW × h) / SUM(Rated MW × total h).	Reporting only; no separate service credits
Critical acknowledgement	From alert timestamp to acknowledgement.	≤30 min
SLA restoration/resolution	Clock with documented stop-clock periods.	100% or an accepted deviation plan
PM completion	Completed on time / planned.	100% of OEM-required tasks
Overdue actions	Open CAPA/punch/warranty items.	0 overdue Critical/Major items
Warranty evidence	Completeness of the Warranty File.	100% of work orders with evidence
Spare stock compliance	Items at or above minimum stock and within storage conditions.	100%; replenishment by the deadline
Cyber access review	Accounts, permissions and sessions.	At least annually and after a change
Safety	Incidents, near misses and actions.	Zero recordable incidents; 100% closure

15.2 Audits and CAPA

- Quarterly review of data quality, downtime classification, work orders and evidence completeness.
- Annual audit of compliance with OEM requirements, warranty, spares, cybersecurity, qualifications, DSO requirements and documentation.
- Each Critical incident, repeated service failure or warranty non-compliance triggers RCA and CAPA.
- Each CAPA shall have an owner, deadline, effectiveness evidence and closure approval.

- The Client and the Lender's Independent Engineer shall have access to agreed evidence and may witness tests.

16. SERVICE COMPLETION AND HANDOVER

Upon LTSA expiry or termination, Lighthief shall provide up to 90 days of transition assistance at agreed rates to preserve safe operation, warranties and full knowledge transfer.

- Export all data and logs in the agreed format.
- Transfer passwords and access credentials through a secure channel; rotate them after receipt.
- Configuration files, point lists, register maps and firmware versions.
- PM/CM registers, measurements, thermograms, certificates, photographs and Warranty Files.
- Open incidents, CAPA, punch items, restrictions and schedules.
- Parts list, stock ledger, storage conditions and open purchase orders.
- Warranty claims, OEM correspondence and extended-warranty status.
- Joint handover review and Client-approved handover record.

Appendix A. APPENDIX A - ANNUAL MAINTENANCE MATRIX

The matrix is the minimum schedule. Current OEM instructions, monitoring results, regulations and warranty conditions may require more frequent or broader activities.

Activity	Cont.	Monthly	Quarterly	6 Months	Year	Event-Driven
Alarms / Telemetry / Connectivity	X	X	X		X	X
BMS backup / logs / parameters		X	X		X	X
Remote command verification		X			X	X
SOH / cell imbalance / thermal trend	X	X	X		X	X
Container / seals / moisture / C5			X		X	X
HVAC / liquid cooling / filters	X	X	X		X	X
Thermal imaging			X		X	X
Cable shielding / SPD / fuses / busbar				X	X	X

Torque verification			X		X	X
Grounding ≤ 4 Ω / bonding					X	X
Insulation resistance > 1 M Ω					X	X
Protection relays / switchgear			X		X	X
Fire detection / suppression / E-stop	X		X		X	X
SCADA signal / IEC 104 / PQ data	X	X	X		X	X
SOH / AC capacity / RTE test					X	X
Cyber access / backup restore review	X	X	X		X	X
Spares stock / shelf life		X	X		X	X
Vegetation / drainage / access roads			X		X	X
Fence / fauna passages / gates			X		X	X
CCTV / laser barriers / lighting	X	X	X		X	X
Registered stream no. 303 - G1			X		X	X
Permit / licence / lease register			X		X	X
Waste transfer records			X		X	X

Appendix B. APPENDIX B - QUARTERLY ON-SITE VISIT CHECKLIST

For each item, enter the result: OK / NOK / N/A, evidence and work-order number. Absence of evidence means completion is not confirmed.

Area	Inspection Point	Result	Evidence / WO
Safety	Acceptable weather; PTW/LOTO/PPE; safe opening; MSD and pack plug in accordance with OEM instructions.		
Container	No damage, corrosion, deformation, combustible materials, moisture or foreign objects.		
Foundation / Doors	Fixings free of corrosion, lock operational, seals intact and doors closing correctly.		
Airflow	Intakes, outlets and ventilation paths clear.		
Cables	No damage, correct routing, sealed entries, no looseness or short-circuit risk.		
Connections	Torque to OEM values; terminal insulation, screens, busbars, SPDs and fuses in correct condition.		
Switchgear / Relays	Switchgear operation, settings, interlocks and protection test.		
Thermography	Connections, switchgear, PCS, busbars and anomalies documented.		
Earthing	Connections and bonding correct; annual measurement $\leq 4 \Omega$.		
Battery	Visual inspection of modules, cell V/T, balancing, BMS communications and SOH.		
Thermal Systems	HVAC/liquid cooling, fans, filters, noise, sensors and performance.		
Fire Safety	Suppression ready/pressure OK, detectors, E-stop,		

	interlocks, ventilation and signage.		
Data	BMS/run/parameters/logs saved; firmware, update, communications and monitoring verified.		
C5 / Coastal Environment	Coatings, salt, grilles, seals, drains, surfaces, hinges and fasteners; photographs.		
Access / Gates	Roads, parking, 4 m/6 m gates and access for EAC/emergency services clear; no obstructions or damage.		
Fencing / Fauna	2.10 m fencing complete; fauna passages clear, with no sharp edges or signs of trapped animals.		
Drainage / Stream	Drains and channels clear; no erosion or ponding; at G1 no interference with or contamination of stream No. 303.		
Security	CCTV, laser barriers, lighting, locks and lightning protection operational; test and evidence.		
Vegetation / Waste	Dry biomass removed; no uncontrolled waste; transfer documents for a licensed recipient.		
EOA / as-built	No new structures or location changes outside the approved plan; every difference entered in the Permit Register.		
After Work	MSDs connected, tools removed, system operational and doors/seals/locks checked.		
Documentation	Log, photographs, measurements, parts,		

	recommendations, punch list and report complete.		
--	--	--	--

Appendix C. APPENDIX C - ALARM AND ESCALATION MATRIX

Event	Class	Initial Action / Escalation	Client
Fire / Gas / Thermal Event	Critical	Isolation, evacuation, 112, Client, HSE, OEM	Immediately
Cell voltage $\leq 2,5$ V	Critical	Protection/isolation, Client, OEM, warranty incident	Immediately
Cell voltage $< 2,9$ V / low SOC	Critical if warranty-threatening	Recharge plan, Client, OEM if the condition worsens	≤ 30 min
Full Park Outage	Critical	Diagnosis, dispatch, plan ≤ 4 h, update every ≤ 2 h	≤ 30 min
PCS trip / $> 10\%$ unavailable capacity	Major / Major Incident	Client, Electrical Lead, OEM; report ≤ 24 h if $> 10\%$	≤ 2 h
HVAC/liquid cooling fault	Major or Critical depending on temperature	Operating limitation, HVAC dispatch, thermal monitoring	≤ 2 h / ≤ 30 min
Monitoring platform failure	Major; Critical if safety-related	Backup channel, SCADA/IT dispatch, Client	≤ 2 h / ≤ 30 min
Communication / DSO Telemetry Loss	Major	Gateway/EMS/SCADA, DSO if required, availability coding	≤ 2 h
Cyber Incident	Critical / Major Incident	Logical isolation, Client, evidence preservation, recovery	Immediately
Minor Sensor / Cosmetic Defect	Minor	WO; next visit or ≤ 30 days	Next Report

Appendix D. APPENDIX D - MINIMUM FIELDS FOR REGISTERS AND REPORTS

Register	Minimum Fields
Work Order	ID, Park/tag, alarm, class, timestamp, owner, scope, LOTO/PTW, parts, times, results, test, downtime coding and closure.
Incident Log	Timeline, severity, notifications, safety state, unavailable capacity, evidence, RCA/CAPA, warranty/DSO/insurance impact.
Downtime Log	Start/stop, Park, affected MW/MWh, included/excluded,

	causal evidence, stop-clock, reviewer and Client challenge.
Spares Ledger	Part number, compatibility, serial/lot, min/max, stock, location, storage, shelf life, issue/return, reorder deadline.
Configuration Register	System/tag, setting/version before/after, approver, backup, test, rollback, DSO/OEM reference.
Warranty Register	OEM, scope, start/end, extension, claim, evidence, status, deadlines, reserve/support confirmation.
Training Matrix	Person, role, qualification, OEM/HSE/SCADA/cyber training, validity and refresher due date.
Contact Matrix	Role, person, telephone/e-mail, deputy, coverage, escalation level, language and contact test.
Permit & Lease Register	Park, document, number, authority/party, scope, issue/expiry, conditions, alert, owner, status and evidence.
Environmental & Waste Register	Event/waste, code and quantity, location, recipient/licence, transfer record, spill, actions and photographs.

EOA DOCUMENTS AND LAND-RIGHTS REGISTER

The following section supplements Appendix D and describes the source package provided on 07.08.2026. The Greek-language originals remain the governing documents; the summaries in this Plan are intended for operational control of obligations.

ID	Asset	Document	Key Data	O&M Status
G1-01	5.0 MWp / 71 and 73	Designer declaration for the BESS/data-centre procedure - Special Exemption Order 2026	Andreas Papaioacovou Architects L.L.C.; policy dated 28.04.2026	Open - confirm validity and EOA acceptance
G1-02	5.0 MWp / 71 and 73	BESS Site-Layout and Foundation Plans	April 2026; scale 1:2000; C35/B420C	To be replaced with stamped/as-built drawings after approval
G1-03	5.0 MWp / 71 and 73	EOA Certificate of Approval with Notes	P1 139876 dated 25.02.2026	Note: container on plot 73
G1-04	5.0 MWp / 71 and 73	Long-Term Lease Agreement	02.11.2018; initial term to 2039; 2 × 5-year renewals	Active - monitor deadlines
G1-05	5.0 MWp / 71 and 73	Building Permit and Environmental Conditions	Permit 052161; environmental documentation and	Conditions included in checklists

			EOA conditions	
G1-06	5.0 MWp / 71 and 73	CERA/RAEK operating exemption	E2674/2020; 14.04.2020- 13.04.2050	Active - 5.0 MWp PV
G1-07	5.0 MWp / 71 and 73	Property Titles	0/3190 and 0/3189; Foinitzi, Avgorou	Source of plot data
G1-08	5.0 MWp / 71 and 73	Cadastral Plan	Plans 2-278-381 and 2-278-382; section 12	Source of boundaries and stream data
G1-09	5.0 MWp / 71 and 73	Power of Attorney	02.11.2018; N.S.P.S. Plantations Limited	Historical document for the PV procedure
G2-01	2.5 MWp / 471 and 520	Designer declaration for the BESS/data- centre procedure - Special Exemption Order 2026	Andreas Papaiaconou Architects L.L.C.; policy dated 28.04.2026	Open - confirm validity and EOA acceptance
G2-02	2.5 MWp / 471 and 520	BESS Site-Layout and Foundation Plans	April 2026; scale 1:1000; C35/B420C	To be replaced with stamped/as-built drawings after approval
G2-03	2.5 MWp / 471 and 520	EOA Certificate of Approval	P1 139841 dated 25.02.2026	PV completed in accordance with the permits
G2-04	2.5 MWp / 471 and 520	Long-Term Leases	Agreements/registers from 01.11.2018 to 2039	Active - monitor deadlines
G2-05	2.5 MWp / 471 and 520	Building Permit and Conditions	Permit 052065; file B80/2015	Road, drainage, fencing and EAC conditions
G2-06	2.5 MWp / 471 and 520	CERA/RAEK operating exemption	E2673/2020; 14.04.2020- 13.04.2050	Active - 2.5 MWp PV
G2-07	2.5 MWp / 471 and 520	Property/Lease Titles	0/7249 and 0/7864; Kerimis, Avgorou	Source of plot data
G2-08	2.5 MWp / 471 and 520	Cadastral Plans	Plan 2-278-381; section 03	Source of boundaries and access data
G2-09	2.5 MWp / 471	Power of Attorney	02.11.2018; Dinos Konstantinou	Historical document for the PV procedure

END OF DOCUMENT