

Cyber Range Lab 1 - Network Check & Verification

Objective:

Verify students understand the baseline connectivity and read the dashboard

Required Equipment:

Router Pi, DMZ Pi, Server Pi, Client Pi, Dashboard accessible at http://10.0.0.30/dashboard_index.html, and Terminal access

Steps:

1. Ping Each Node

Run from the Client Pi (or from each Pi individually):

```
ping -c 1 10.0.0.1      # Router
ping -c 1 10.0.0.20     # DMZ
ping -c 1 10.0.0.30     # Server
ping -c 1 10.0.0.40     # Client
```

2. Test DNS Resolution

```
ping -c 1 fakebank.local
ping -c 1 dashboard.local
```

Confirm that DNS returns the correct IPs.

3. Open the Dashboard

Visit:

http://10.0.0.30/dashboard_index.html

Check that all nodes display "Shielded / Up."

Record whether replies succeed.

4. Award Points Manually

Use:

```
curl -X POST http://10.0.0.30:8080/score/team1/10
```

Check Your Work:

Successful ping output, dashboard with all nodes "Up," example of the curl command.

Reflection Question:

What can you tell from the dashboard's health indicators when one Pi is unplugged?