

10.1 chizma. Pyezonurlatgichni Arduinoga ulanish sxemasi.

10 jadval.

1 oktava	Belgilanishi	Chastota, Gs	2 oktava	Belgilanishi	Chastota, Gs
do	S	261	do	S	523
do-diyez	C#(R)	277	do-diyez	s#(g)	554
re	D	293	re	d	587
re-diyez	D#(S)	311	re-diyez	d#(s)	622
mi	YE	329	mi	ye	659
fa	F	349	fa	f	698
fa-diyez	F#(T)	370	fa-diyez	f#(t)	740
sol	G	392	sol	g	784
sol-diyez	G#(U)	415	sol-diyez	g#(u)	830
lya	A	440	lya	a	880
si-bimol	V	466	si-bimol	ь	932
si	Н	494	si	h	988

Notalar boʻyicha musiqani tuzamiz, melody[] massivga kiritiladi, notalar davrining roʻyxatini duration [] massivga kiritiladi. Notalarni belgilangan axborot notes [] massivga kiritiladi, kerakli notalarga tegishli chastotalar haqidagi axborot frequency[] massiviga kiritiladi.10.1 listingda sketch keltirilgan.



Ris. 10.2 chizma. Imperiya marshining bir qismi.