

16

Meeting Room, Display and Audio-Visual Equipment

Room displays, conferencing systems, projectors, microphones and wireless sharing

Default priority: P3 Medium
(P2 if an executive or client meeting is within the hour)

Target response / resolution: Respond in 10 min / on-site within 30 min for urgent

Handled by: Tier 1, then deskside / AV team

Scope

Use this instruction for faults with meeting room equipment: displays, projectors, conferencing systems, microphones, speakers, cameras, touch panels, and wireless presentation.

Related instructions: WI-12 Video Conferencing, WI-15 Telephony, WI-06 Network

Common symptoms

- Room display shows no signal
- Conferencing system will not start a meeting
- No sound, echo, or feedback in the room
- Laptop will not connect to the screen
- Touch panel is frozen or shows an error

Information to collect

- Room name and building, and the meeting start time
- Equipment affected and any messages on the screen
- Whether the problem is with a laptop connection or the room system
- Who is hosting, and whether the meeting has external guests

Resolution steps

- 1 Prioritize by meeting time.** If a meeting is imminent, get a quick workaround ready first: join from a laptop and use the room display or a phone dial-in.
- 2 Check power and cables.** Confirm the display, codec, and speakers are on and the right input is selected. Reseat HDMI, USB, and network cables.
- 3 Check the room system.** Look at the touch panel and the room system status in the management portal. Restart the room system if it is offline.
- 4 Check the laptop connection.** Try another cable or adapter, set display mode to extend or duplicate, and check the resolution. Try a second laptop to separate laptop and room faults.
- 5 Check audio.** Check that microphones are not muted and that the right speaker and microphone are chosen. Reduce echo by lowering the volume or muting unused devices.
- 6 Check network and sign-in.** Confirm the room account is signed in and that the system has a network connection. Check the calendar link if meetings do not appear.
- 7 Test and record.** Run a short test call with the user. Record the fault and the fix on the room's equipment record.

Escalate when

- Room system is offline and cannot be restored remotely
- Hardware fault (display, camera, microphone, panel) that needs a vendor or AV engineer
- Repeated faults in the same room, which may indicate a design or network issue

Resolution and closure

- Update the room equipment log with the fault and the fix
- Report recurring faults for a problem record
- Close after the user confirms the room works for their meeting

Quick troubleshooting reference

Symptom	Likely cause	What to do
Display shows 'No signal'	Wrong input selected, or cable fault	Select the right input, reseal the cable, and try another adapter.
Room system will not join a meeting	Not signed in, or network or calendar link fault	Check sign-in and network, then restart the system.
Echo or feedback	Open microphones, high speaker volume	Mute unused microphones, lower the volume, and check the room settings.
Camera not showing	Camera input or USB fault	Check the camera is selected, reseal the USB, and restart the system.
Touch panel frozen	Software hang	Power cycle the panel and the codec, then check firmware status.

Suggested wording for the user

Open	<i>"When does your meeting start? I will get you a working setup first and then look at the cause."</i>
During	<i>"Please try joining from your laptop and share to the room display while I check the room system remotely."</i>
Close	<i>"The room system is working again. I have noted the problem on the room record so we can watch it."</i>

Good practice

Do

- Keep a quick-start guide in every room
- Prepare a laptop-based workaround
- Label cables and adapters
- Check rooms before key meetings

Do not

- Do not leave users without a backup option
- Do not change room firmware just before a meeting
- Do not remove cables or adapters from rooms
- Do not forget to check the calendar link

Worked example

A sales director cannot present to a client because the display shows no signal 15 minutes before a meeting.

Ticket note field	Entry
Issue reported	Meeting Room 4 display shows 'No signal', client arrives in 15 minutes.
Checks performed	Display input set to HDMI 2, cable plugged into HDMI 1.
Cause	Input changed by the previous user.
Action taken	Selected HDMI 1 remotely and confirmed the laptop display.
Result	Presentation ready in 5 minutes. Added an input lock to the room's settings.

Analyst checklist

- | | |
|--|--|
| ☐ Prioritize by meeting time | ☐ Check network and sign-in |
| ☐ Check power and cables | ☐ Test and record |
| ☐ Check the room system | ☐ Ticket note completed using the standard template |
| ☐ Check the laptop connection | ☐ User confirmed the issue is resolved |
| ☐ Check audio | |

Preventing repeat tickets

- Standardize equipment across rooms
- Monitor room systems and alert on offline status
- Post short instructions in each room
- Schedule regular room checks and firmware updates