

1、Install the required libraries

```
import serial
import serial.tools.list_ports
import struct
```

2、Modify the baud rate matched to the current device

```
74         try:
75             selection = int(input("Please enter the code in front of the port number according to the prompt above:"))
76             if 1 <= selection <= len(com_list):
77                 return com_list[selection - 1]
78             else:
79                 print("The entered code is invalid, please re-enter.")
80                 return self.select_com_port()
81         except ValueError:
82             print("The entered is not a valid number, please re-enter.")
83             return self.select_com_port()
84
85     def open_data(self, select_com):
86         if not self.ser.is_open:
87             com = select_com
88             btr = 921600
89             try:
90                 # self.ser = serial.Serial(com, btr, parity=serial.PARITY_NONE, stopbits=1, bytesize=8, timeout=0.3)
91                 self.ser = serial.Serial(com, btr, parity=serial.PARITY_NONE, stopbits=serial.STOPBITS_ONE,
92                                         timeout=0.08)
93                 self.ser.reset_output_buffer()
94
```

3、run the program(after connecting the device).

4、Enter the number for your device

```
114         m = k * 10
115         v = (struct.unpack('h', datain[m:m + 2])[0]) / (2 ** q)
116         peakValue = (struct.unpack('h', datain[m + 2:m + 4])[0])
117         x = (struct.unpack('h', datain[m + 4:m + 6])[0]) / (2 ** q)
118         y = (struct.unpack('h', datain[m + 6:m + 8])[0]) / (2 ** q)
119
120     SerialPortDataManager > open_data() > if not self.ser.is_open > if self.ser.is_open > while True
121
122 mrr_points_4DSNR_SDK
123
124 D:\pure_py_env\Scripts\python.exe D:\2944_points_track\mrr_points_4DSNR_SDK.py
125
126 The available COM ports are:
127 1. COM17
128 2. COM5
129 Please enter the code in front of the port number according to the prompt above: 2
130 Current frame: 6248
131
132 points index:1
133 x:-0.015625 m
134 y:1.8846875 m
135 z:0.0 m
136 v:0.0 m/s
137 PeakValue:5790
138
139 points index:2
140 x:0.421875 m
141 y:2.3846875 m
142 z:0.0 m
143 v:0.0 m/s
144 PeakValue:5495
145
146 points index:3
147 x:-1.6796875 m
148 y:5.8390625 m
149 z:0.0 m
```