

pggo

KIDS SMART GPS WATCHES

Kids GPS Smart Watch

(Water resistant IP67)

User Manual

Model:LT53

1. Get a Nano SIM card

1) Prepare for a Nano SIM card firstly and the phone card package should include internet flux and voice call. You can buy it from local telecom operators. Please inquiry presale customer service if you have any questions.

2) The SIM card must support 4G network with data streaming and airtime.

Normal SIM Card

Micro SIM Card

NORMAL SIM Card after cutting

NANO Card

NO

YES

2. How to install SIM card ?

1) Draw out SIM card tray , then chipset side face up and put into the tray.

2) Power on or reboot the watch till signal coming (can not recognize SIM card if don't operate)

5. Buttons illustration

Button 1:
SOS: Press for 5-6s
Wake-up screen: Short press
Return to upper menu: Short press

Button 2:
Power on: Press for 5-6s
Power off: Press for 5-6s after remove SIM card out
Lock screen: Instant press
Wake-up screen: Instant press

Button 1

Button 2

Return button

4. Download the APP

1) Scan the QR code below, download and install it.

2) Or searching APP name: JuniCare from Apple store or Google Play to down load and install it.

*Compatible with IOS11 and Android 4.4 or above.

5. Login and Registration

You need to create account or log in with Apple ID or Google account when use it firstly.

Create account

Or log in with Apple ID or Google account

6. Bind watch

1) After successful login, please go to Add Watch interface and click start binding.

2) Long press the watch power button to turn on your watch.

Start binding

3) After turning on the watch, will display the APP download code and Reg Code. Scan Reg code (in watch second page or stick on watch backside) to add your watch.

Step 1: Click here

Reg Code

Step 2: Use APP scan the Reg Code

版本	变更描述	日期
A0	第一次发布	2026/09/29

4) After binding successfully, there will be a indication of bind succeeded, then you can enter the app to explore more functions.

7. Verify successful bundling with watch

Pls go to Find Watch to verify watch bundling well, it means watch and APP connection successfully.

Look for the watch

8. Setting

Log in and find the setting, click the phone book or contacts and save the numbers you need. The same goes for the other functions.

Watch:XX

15800000000000000000

Set a SOS number(Mum/ Dad / Brother?)

Only those numbers saved in phone book or contacts have the privilege to call the watch, suggest adding baby's friends too.

You should save the numbers in App, the watch can call out these numbers.

Remember to click the save button.

9. Power off device

Kindly press button 2 to Setting menu, and press Power Off .

10. Location

1): Turn on the map and make sure that it got signal.

2): Open the map on APP, click the location then it will shows your device real-time position.

Notes: If the watch is indoors, it usually locates yourself via LBS or WIFI, and the deviation is inevitable, which depends on the distance between the watch and Base Station and the environment as well. If you're in outside, it switch to GPS automatically (in optional function), the range of deviation will also narrowed, but will still become unstable while the watch moved, which is normal, you can't regard it as quality issues, won't be listed in After-sale service.

Troubleshooting

1: Has GPRS Network

2: Has 4G data streaming

3: Can dial out

FAQ:

1. Even if you inserted the SIM card, it still got no signal

1): Check the card's type and size to see if it's right, also check if the card has 4G network.

2): Check the card to see if it's inserted properly. First shut down the watch, second, insert the card, then reboot.

2. When you save the numbers it indicates that the device can not connect the network.

1): Is there any signal after inserting the card, please check, and can the watch rings when receiving a phone call.

2): Check whether the watch is on or not.(before using the APP, the watch must be on)

3): Make sure that the SIM card has the data package and make sure you have paid the phone charge and the SIM card is available to call.

4): Check whether the watch ID match the ID on the tags or not.

5): If still not working, please send ts# to the phone number that inserted SIM in watch then your phone will receive a message from your watch, please send the message and IMEI number on the backside of watch to service center, they will solve this problem as soon as possible.

3. When you call the watch, it reminds you the number you have dialed is busy, please try again later.

1): Is there any signal after inserting the card, please check.

2): Please check you have saved phone numbers on your APP.

3): Check If you have turn on the DO NOT DISTURB in App and set a time, if yes, please switch to OFF.

4. The time can not update automatically.

When you manage inserting the card(must have data), the watch will update the time automatically, which might take few minuets.

5. The positioning function is not working.

1): Go outside and try again.

2): Once the watch goes to SLEEP MODE, it will switch to SAVE POWER MODE, which means the function of uploading data is OFF, at this time, you can refresh the positioning and shake the watch to wake it up.

6. Neither charge nor boot

The battery enter into a self-protection mode, do as the following step by step:

1): Try another USB Cable to see if the original one was damaged.

2): Press the POWER key for 50 seconds, then recharge, it will indicate recharging on the watch after 1 minutes, at this time you can reboot.

3): If still not working, the watch has a recovery time, after two days, it has no power and then recharge it ,it should be work.

7. No voice on watch or phone.

Check the volume + - while calling. If the watch switch to max. still no voice, the speaker must damaged, it need be repaired.

8. The watch can receive any call.

Apply to your local operator for a function of showing callers ID.

9. When use the watch to call, it indicates that can not connect

Check the GSM signal, it shows on the screen. If not, maybe your SIM card has loosened, try to reload again.

10. How to remove PIN lock screen after install SIM card.

Please set smartphone to remove, Setting→Security&Privacy→Set SIM lock, then turn off "Lock SIM card" as per below picture.

Security & privacy

Screen lock & passwords

Student mode

TrustSpace

Find my phone

App lock

File safe

Location services

Set SIM 1/SIM 2 lock

Show passwords

Device administrators

Set SIM 1/SIM 2 lock

Lock SIM card

Require PIN to use phone

Change SIM PIN

Device is equipped with a microphone for recording and making video calls on the watch, a camera for taking photos and making video calls on the watch, and a gravity sensor for counting steps on the watch.

Watch roaming calculation is enabled by default in factory state.

Simplified EU DoC

Hereby, Shenzhen Motto Electronics Co., Ltd. declares that the radio equipment type Children's phone watchis in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address: <https://trust.motto4u.com/about>

*The vulnerability submission policy, product support period, and compliance statement can be found in the following link.
<https://trust.motto4u.com>

CE

ROHS

MADE IN CHINA

技术要求
材质:XXX
尺寸:XXX
公差:XXX
备注:XXXXXX

尺寸：70*70mm 折页印刷

备注:

- 1、标有“*”号尺寸为重点尺寸，QC需要重点检查，未标注尺寸按2D图纸检查，未标注公差按右图公差表执行；
- 2、不能有变形、毛刺、划伤等外观不良；
- 3、可靠性测试按客户要求执行，没要求部分按我司内部标准执行；
- 4、环保按照IDO标准执行。

深圳市阿科奇电子科技有限公司						
项目名称:	LT53	物料编码:		制作者:	徐秋霞	
订单编号:	O260928007	尺寸范围:	公差范围:	单位: mm	制作日期:	2026/09/29
零件名称:	说明书	0~10	+/-0.05	角度公差:	审查: 董艳	日期: 2026/09/29
材 质:		10~50	+/-0.10	+/-0.25	批准: 谢君涛	日期: 2026/09/29
页次: 1/1	比例: 1:1	50~:	+/-0.15	用量: 1		