

BP-Synth

MIDI Control Changes List

CC#	Name	Description (If needed)
1	ModWheel	The large wheel next to the PitchWheel. Default is Vibrato.
2-4	Not Used	(further on, if a CC# is not listed, it is Not Used).
5	Portamento	Turns on Portamento and adjusts. time.
6	OSC Select	Selects the "Voice" or timbre (sometimes multi Osc'd).
7	Volume	Adjust Main Output Volume.
8	Legato Switch	Turn Legato On/Off.
11	Osc1CourseFreq	Oscillator 1 Coarse Frequency Set.
12	Osc2CourseFreq	Oscillator 2 Coarse Frequency Set (only used with HardSync).
13	DelayFX Switch	Switch Delay On/Off.
14	Delay Time	Length of Delay loop.
15	Delay Feedback	Strength of Repeats/Echo.
16	Delay Wet Mix	Delay Mix Control.
26	Phaser Switch	Switch Phaser On/Off.
27	Phaser Rate	Adjust Speed of phasing.
27	Phaser Feedback	Increase Feedback/Resonance.
27	Phaser Wet Mix	Phaser Mix Control.
30	Auto Pitch Depth	Depth of Influence to Pitch.
31	Auto Pitch Attack	Attack Rate
32	Auto Pitch Decay	Decay Rate
33	Auto Pitch Sustain	Final Pitch.
34	Arpeggiator Switch	Turns ARP On/Off.
35	ARP Tempo	Adjust ARP Tempo.
36	ARP Ext. Sync	Turn External Sync On/Off.
37	ARP Note Length	Adjust Note Length.
38	ARP Mode	0=Up, 1=Down, 3=Bounce.
39	ARP Hold	Turn ARP Hold On/Off.
40	ARP Octave Plus	Play extra Octave On/Off.
41	Amp Attack	
42	Amp Decay	
43	Amp Sustain	
44	Amp Release	

CC#	Name	Description (If needed)
45	Filter Attack	Filter EG settings also used for PWM and Hard Sync Pitch EG.
46	Filter Decay	
47	Filter Sustain	
48	Filter Release	
49	Filter EG Depth	Filter Envelope Generator Influence
50	Amp Velocity Depth	Key Velocity Influence to Volume
51	Filter Velocity Depth	Key Velocity Influence to Filter
52	LFO Velocity Depth	Key Velocity Influence to Filter LFO Speed
57	Amp LFO Depth	LFO's Influence to Volume
58	Amp LFO Rate	Speed of Amp LFO
60	Vibrato Rate	Speed of LFO to Pitch
61	KeyTrack Switch	Turn KeyTrack On/Off
62	KeyTrack Depth	Adjust KeyTrack Influence
63	KeyTrack Exponent	Influence Balance/Ratio (Low Keys:High keys)
66	Filter LFO Rate	Speed of LFO to Filter
67	Vibr/Amp LFO Wave	Waveshape Select for Vibrato/Amp LFO
68	Filter LFO Wave	Waveshape Select for Filter LFO
69	PWM Depth	LFO Influence to PWM Duty Cycle
70	PWM Rate	Speed of PWM's LFO
71	Filter Resonance	
72	Filter LFO Depth	LFO influence to Filter
73	Filter Type	Select Lo or Hi Pass Filter Type
74	Filter Cutoff Freq.	
77	Wheel Mod 1	Select a feature for Modwheel to influence: 0=Nil, 1=Vibr, 2=Trem, 3=FilterCO, 4=FltrLFOdepth, 5= FltrLFOrate, 6= VibrRate, 7=TremRate, 8=PWMdepth, 9= PWMrate, 10=PhaserRate, 11= Osc1Freq, 12= Osc2Freq
78	Wheel Mod 2	Select a feature for Modwheel to influence. (see above list)
79	Wheel Mod 3	Select a feature for Modwheel to influence. (see above list)
85	Delay Expander	Stereo Expand Echoes. (Subtle Stereo on up to a Ping Pong Delay)
94	Detune	Detune 3 Saw and 2 Saw voices.
99	Duty Cycle	Waveshape control. (Most Square or Waveshaper voices.)