

450G /interface vlan

```
add interface=ether1 name=eth1-vlan500 vlan-id=500
add interface=ether1 name=eth1-vlan501 vlan-id=501
add interface=ether1 name=eth1-vlan521 vlan-id=521
add interface=ether1 name=eth1-vlan522 vlan-id=522
```

```
add interface=ether5 name=eth5-vlan500 vlan-id=500
add interface=ether5 name=eth5-vlan501 vlan-id=501
```

450G Bridges

```
bridge-vlan500 (members eth1-vlan500 & eth4 & eth5-vlan500)
bridge-vlan501 (members eth1-vlan501 & eth5-vlan501)
bridge-vlan521 (members eth2 & eth1 & eth1-vlan521)
bridge-vlan522 (members eth1-vlan522 & eth3)
```

Need UNTAGGED INTERNET on both SMC & Switch so ansible doesn't get broken during initial deployment so create a bridge with just Eth1 & Eth2 Bridge_521 but eth0 has no VLAN associated but call 521 for consistency

VLAN 500 has secondary IP 192.168.5.100 for backwards compatibility with Dallas Delta UI

Need 192.168.100.2 on SMC VLAN 521 which can then be passed over the bridge to Ether2 for access to nbn modem during Installer Mode

RP3 IP Interface Configuration

```
WLAN0: Bridged in VLAN500
vlan500@eth0: 10.255.0.1/24
               192.168.5.100/24
vlan501@eth0: 10.0.0.1/23
vlan521@eth0: 192.168.100.50/24
vlan522@eth0: DHCP
eth0: DHCP
```

```
# Management IPTables Rules
-A FORWARD -i vlan500 -j ACCEPT
```

```
#### VLAN500 => Managment ####
```

```
subnet 10.255.0.0 netmask 255.255.255.0 {
    authoritative;
    option domain-name-servers 116.250.255.18 , 116.250.255.19;
    option routers 10.255.0.1;
    range 10.255.0.100 10.255.0.110;
}
```

```
#### VLAN501 => Public ####
```

```
subnet 10.0.0.0 netmask 255.255.254.0 {
    authoritative;
    option domain-name-servers 116.250.255.18 , 116.250.255.19;
    option routers 10.0.0.1;
    range 10.0.0.10 10.0.1.254;
}
```

WLAN0 Configuration

```
SSID: A8_Management
PSK: [SomethingNew]
```



RP3

Trunk 500,501,522
Trunk 521 to access NTD
Untagged eth0-ETH2

VLAN 500
IP: 10.255.0.5/24
DG: 10.255.0.1

Mikrotik 450GX4

ETH1

ETH2

ETH3

ETH4

ETH5

Untagged ETH2-eth0

Access 521 for NTD

Access 522

Access 500

PoE
Trunk 500,501



Metal Wifi AP

Ethernet:
VLAN 500
IP: 10.255.0.20/24
DG: 10.255.0.1

Wifi:
VLAN 501
Bridge



Satellite Modem
Not VLAN Aware

Uni-D1

Uni-D1

Uni-D2

No VLAN
IP: 192.168.5.253 /24
DG: 192.168.5.100



Dallas Delta ATA UI



Thuraya Sat Phone

Thuraya Backup is hard coded into UI Circuitry BIA Module to switch to Thuraya when UI does not have SIP Registration (1)

- 1 – Not registered with SIP server
- 2 – Registered with SIP server, handset on hook
- 3 – Registered with SIP server, call in progress