* Values:
  * 0 if asynchronous mode is not supported
  * 1 if asynchronous mode is supported by Initiator
  * NOTE: Synchronous mode is always implicitly supported.

Range Control (`RC`)

The Range Control (`RC`) field specifies parameters related to offset and length of the transfer:

* whether the transfer has a definite length (`DEFLEN`);
* whether an offset is present (`STARTOFS`);
* the width of the length and offset fields (`WIDERANGE`).

Table 112. SendInit/ReceiveInit Range Control (`RC`) field structure

bit 7	6	5	4	3	2	1	0
RFU			WIDERANGE	RFU		STARTOFS	DEFLEN

The fields for `RC` are:

SendInit/ReceiveInit `RC[DEFLEN]`: definite length present

* Width: 1 bit
  * Values:
    * 0 if no length is present (indefinite length)
    * 1 if a definite length is present (see Section 11.22.5.1.5, “Length (`DEFLEN`)”)

SendInit/ReceiveInit `RC[STARTOFS]`: start offset present

* Width: 1 bit
  * Values:
    * 0 if a start offset is not present
    * 1 if a start offset is present

SendInit/ReceiveInit `RC[WIDERANGE]`: wide (64-bit) range enable for values

* Width: 1 bit
  * Values:
    * 0 to indicate that offset (`STARTFOFS`) and length (`DEFLEN`) are 4 octets (32-bit) little-endian unsigned quantities.
    * 1 to indicate that offset (`STARTFOFS`) and length (`DEFLEN`) are 8 octets (64-bit) little-endian unsigned quantities.