ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	**MeasuredValue**	uint16	0, MinMeasuredValue to MaxMeasuredValue	P X		R V	M
0x0001	**MinMeasuredValue**	uint16	1 to 65533	X		R V	M
0x0002	**MaxMeasuredValue**	uint16	min (MinMeasuredValue + 1)	X		R V	M
0x0003	**Tolerance**	uint16	max 2048			R V	O
0x0004	**LightSensorType**	LightSensorTypeEnum	all	X	null	R V	O

2.2.5.1. MeasuredValue Attribute

This attribute SHALL indicate the illuminance in Lux (symbol lx) as follows:

- MeasuredValue = 10,000 x $\log_{10}$(illuminance) + 1,

where 1 lx <= illuminance <= 3.576 Mlx, corresponding to a MeasuredValue in the range 1 to 0xFFFE.

The MeasuredValue attribute can take the following values:

- 0 indicates a value of illuminance that is too low to be measured,
- MinMeasuredValue <= MeasuredValue <= MaxMeasuredValue under normal circumstances,
- null indicates that the illuminance measurement is invalid.

The MeasuredValue attribute is updated continuously as new measurements are made.

2.2.5.2. MinMeasuredValue Attribute

This attribute SHALL indicate the minimum value of MeasuredValue that can be measured. A value of null indicates that this attribute is not defined. See Measured Value for more details.

2.2.5.3. MaxMeasuredValue Attribute

This attribute SHALL indicate the maximum value of MeasuredValue that can be measured. A value of null indicates that this attribute is not defined. See Measured Value for more details.

2.2.5.4. Tolerance Attribute

See Measured Value.

