

Note 2: Any undefined values are reserved for future use.

Note 3: A Commissionee can indicate multiple methods of being put into Commissioning Mode by setting multiple bits in the bitmap at the same time. However, only one such method can be specified which has a mandatory dependency on the PI key (PI Dependency=**M**) at a time.

For example:

- A **PH** value of 33 (bits 0 and 5 are set) indicates that the user can cause the Commissionee to enter Commissioning Mode by either power cycling it or by following special instructions provided in the Device Manual.
- A **PH** value of 9 (bits 0 and 3 are set) indicates that the user can cause the Commissionee to enter Commissioning Mode by either power cycling it or going to the settings menu and following instructions there.
- A **PH** value of 1 (bit 0 is set) indicates that the user can cause the Commissionee to enter Commissioning Mode only by power cycling it.
- A **PH** value of 16 (bit 4 is set) indicates that the user can cause the Commissionee to enter Commissioning Mode following a custom procedure described by the value of the PI key.
- A **PH** value of 256 (bits 8 is set) indicates that the user can cause the Commissionee to enter Commissioning Mode by pressing the reset button for a duration of time in seconds specified via by the value of the PI key.

When the **PH** key is provided, at least one bit in the above bitmap SHALL be set. That is, a **PH** value of 0 is undefined and illegal.

When the **PH** key is provided, the Commissioner SHOULD take its value into account when providing guidance to the user regarding steps required to put the Commissionee into Commissioning Mode.

4.3.1.12. TXT key for pairing instructions (**PI**)

The optional key **PI** MAY give the *pairing instruction*.

If present, the value SHALL be encoded as a valid UTF-8 string with a maximum length of 128 bytes.

The meaning of this key is dependent upon the **PH** key value, see [Table 5, “Pairing and Reset Hint Values”](#).

For example, given **PH=256**, bit 8 is set which indicates "Press Reset Button for N seconds". Therefore, a value of **PI=10** would indicate that N is 10 in that context.

When bit 4 of the value expressed by the **PH** key is set, indicating presence of a custom string, the Commissionee SHALL be responsible for localization (translation to user's preferred language) as required using the Device's currently configured locale. The Custom Instruction option is NOT recommended for use by a Commissionee that does not have knowledge of the user's language preference.

It is RECOMMENDED to keep the length of PI field small and adhere to the guidance given in section 6.2 of [\[RFC 6763\]](#).