

```

responderSessionId    [3] : UNSIGNED INTEGER [ range 16-bits ],
pbkdf_parameters      [4] : Crypto_PBKDFParameterSet,
responderSessionParams [5, optional] : session-parameter-struct
}

```

On receipt of **PBKDFParamRequest**, the responder SHALL:

1. Verify **passcodeID** is set to 0. If verification fails, the responder SHALL send a **status report: StatusReport(GeneralCode: FAILURE, ProtocolId: SECURE_CHANNEL, ProtocolCode: INVALID_PARAMETER)** and perform no further processing.
2. **Generate a random number** **ResponderRandom** = **Crypto_DRBG(len = 32 * 8)**.
3. Generate a **session identifier** (**ResponderSessionId**) for subsequent identification of this session. The **ResponderSessionId** field SHALL NOT overlap with any other existing PASE or CASE **session identifier** in use by the responder. See **Section 4.13.2.4, “Choosing Secure Unicast Session Identifiers”** for more details. The responder SHALL set the **Local Session Identifier** in the **Session Context** to the value **ResponderSessionId**.
4. Set the **Peer Session Identifier** in the **Session Context** to the value **PBKDFParamRequest.initiatorSessionId**.
5. Construct the appropriate **Crypto_PBKDFParameterSet** (**PBKDFParameters**). If **PBKDFParamRequest.hasPBKDFParameters** is **True** the responder SHALL NOT include the PBKDF parameters (i.e. salt and iteration count) in the **Crypto_PBKDFParameterSet**. If **Msg1.hasPBKDFParameters** is **False** the responder SHALL include the PBKDF parameters (i.e. salt and iteration count) in the **Crypto_PBKDFParameterSet**.
6. Send a message with the appropriate **Protocol Id** and **Protocol Opcode** from **Table 18, “Secure Channel Protocol Opcodes”** whose payload is the TLV-encoded **pbkdfparamresp-struct** **PBKDFParamResponse** with an anonymous tag for the outermost struct.

```

PBKDFParamResponse =
{
    initiatorRandom (1) = PBKDFParamRequest.initiatorRandom,
    responderRandom (2) = ResponderRandom,
    responderSessionId (3) = ResponderSessionId,
    pbkdf_parameters (4) = PBKDFParameters
}

```

Pake1

```

pake-1-struct => STRUCTURE [ tag-order ]
{
    pA [1] : OCTET STRING [ length CRYPTO_PUBLIC_KEY_SIZE_BYTES ],
}

```

On receipt of **PBKDFParamResponse**, the initiator SHALL: