

PASE or CASE [session identifier](#) in use by the initiator. See [Section 4.13.2.4, “Choosing Secure Unicast Session Identifiers”](#) for more details.

3. The initiator SHALL generate a destination identifier ([DestinationId](#)) according to [Destination Identifier](#) to enable the responder to properly select a mutual Fabric and trusted root for the secure session.
4. The initiator SHALL [generate an ephemeral key pair](#) `InitiatorEphKeyPair = Crypto_GenerateKeyPair()`.
5. The initiator MAY encode any relevant [MRP parameters](#).
6. Any context-specific tags not listed in the above TLV schemas SHALL be reserved for future use, and SHALL be silently ignored if seen by a responder which cannot understand them.
7. If the initiator is resuming a session from a previous execution of the CASE with the same peer, the initiator SHALL:
 - a. Note the [ResumptionID](#) of the previous session.
 - b. Generate the [S1RK key](#).
 - c. Generate the [initiatorResumeMIC](#) using the [SharedSecret](#) from the previous session:

```
byte Resume1MIC_P[] = {}
byte Resume1MIC_A[] = {}
byte Resume1MIC_Nonce[13] = /* "NCASE_SigmaS1" */
    {0x4e, 0x43, 0x41, 0x53, 0x45, 0x5f, 0x53, 0x69,
     0x67, 0x6d, 0x61, 0x53, 0x31}

InitiatorResume1MIC = Crypto_AEAD_GenerateEncrypt(
    K = S1RK,
    P = Resume1MIC_P,
    A = Resume1MIC_A,
    N = Resume1MIC_Nonce
)
```

8. The initiator SHALL send a message with [Secure Channel Protocol ID](#) and [Sigma1 Protocol Opcode](#) from [Table 18, “Secure Channel Protocol Opcodes”](#) whose payload is the TLV-encoded [Sigma1 Msg1](#) with an anonymous tag for the outermost struct.

```
Msg1 =
{
    initiatorRandom      (1) = InitiatorRandom,
    initiatorSessionId   (2) = InitiatorSessionId,
    destinationId        (3) = DestinationId,
    initiatorEphPubKey    (4) = InitiatorEphKeyPair.publicKey
    initiatorSessionParams (5) = session-parameter-struct (optional),
    resumptionID          (6) = ResumptionID (optional, only present if performing
```