

uses little endian encoding for any header fields larger than one byte in length.

Table 37, “PAFTP Packet PDU format” defines the PAFTP Packet PDU format.

Unused fields SHALL be set to '0'.

Table 37. PAFTP Packet PDU format

bit 0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Control Flags								[Management Opcode]							
[Ack Number]								[Sequence Number]							
[Message Length]															
[Segment Payload]...															
...															

4.20.2.1. Control Flags

Table 38. PAFTP Control Flags

bit 7	6	5	4	3	2	1	0
-	H	M	-	A	E	C	B

H (Handshake) bit

Set to '0' for normal PAFTP packets. When set, this bit indicates a PAFTP handshake packet for session establishment and has a different packet format described below.

M (Management Message) bit

Indicates the presence ('1') or absence ('0') of the Management Opcode field. All segments of a message SHALL set this bit to the same value.

A (Acknowledgement) bit

Indicates the presence of the Ack Number field.

E (Ending Segment) bit

Set to '1' on the last segment of a PAFTP SDU and set to '0' for all other segments of the same PAFTP SDU. A segment MAY have both the Beginning and Ending bits set indicating that a full PAFTP SDU is included in the message. When set, the segment payload length is equal to the total remaining unreceived message data. When not set, the segment payload length is equal to the maximum allowable PAFTP session packet size minus header overhead.

C (Continuing Segment) bit

Set to '0' on the first segment of a PAFTP SDU and set to '1' for all remaining segments of the same PAFTP SDU.