

In case the chained message exceeds the maximum supported message size, an error response conforming to [Table 50](#) SHALL be issued, indicating 'Not enough memory space'.

Table 50. TRANSPORT error Response APDU - Not enough memory space

SW1	SW2
0x6A	0x84

4.21.4.3. GET RESPONSE command

This command SHALL be issued following the reception of an incomplete successful R-APDU, in compliance with [ISO/IEC 7816-4](#).

Table 51. GET RESPONSE command APDU

CLA	INS	P1	P2	Le
0x00	0xC0	0x00	0x00	...

- The **Le** single-octet field SHALL encode the maximum length in octets that the reader/writer can receive in the response APDU in compliance with [ISO/IEC 7816-4](#). To optimize underlying ISO-DEP chaining, **Le** SHOULD encode the value equal to $\min(256, \text{FSD}-6)$.

Successful response APDU is in following tables:

Table 52. GET RESPONSE successful Response APDU - Complete message

Data	SW1	SW2
Message or last fragment of message to transmit	0x90	0x00

Table 53. GET RESPONSE successful Response APDU - Incomplete message

Data	SW1	SW2
Fragment of message to transmit	0x61	...

In case GET RESPONSE is received, but not following a [TRANSPORT successful Response APDU - Incomplete message](#), the commissionee SHALL answer with an error indicating the condition of use is not satisfied, as shown in [Table 54](#)

Table 54. GET RESPONSE error Response APDU - Condition of use not satisfied

SW1	SW2
0x69	0x85

4.21.4.4. APDU sequence diagram

A sequence diagram showing the APDU chaining feature is shown in [NTL APDU sequence diagram](#).