

Table 57. Packed Binary Data Structure for Onboarding Payload

Onboarding Payload Element	Size (bits)	Required	Notes
Version	3	Yes	3-bit value specifying the QR code payload version. SHALL be 000.
Vendor ID	16	Yes	
Product ID	16	Yes	
Custom Flow	2	Yes	Device Commissioning Flow 0: Standard commissioning flow: such a device, when uncommissioned, always enters commissioning mode upon power-up, subject to the rules in Section 5.4.2.2, “Announcement Commencement”. 1: User-intent commissioning flow: user action required to enter commissioning mode. 2: Custom commissioning flow: interaction with a vendor-specified means is needed before commissioning. 3: Reserved
Discovery Capabilities Bitmask	8	Yes	Defined in table below.
Discriminator	12	Yes	12-bit as defined in Discriminator
Passcode	27	Yes	See Section 5.1.7, “Generation of the Passcode”
Padding	4	Yes	Bit-padding of '0's to expand to the nearest byte boundary, thus byte-aligning any TLV Data that follows.
TLV Data	Variable	No	Variable length TLV data. Zero length if TLV is not included. This data is byte-aligned. See Section 5.1.3.1.4, “TLV Data” for detail.

Table 58. Discovery Capabilities Bitmask

Bit	Size (bits)	Description
0 (lsb)	1	Reserved (SHALL be 0)
1	1	BLE: 0: Device does not support BLE for discovery or is currently commissioned into one or more fabrics. 1: Device supports BLE for discovery when not commissioned.
2	1	On IP network: 1: Device is already on the IP network