

Byte	Value	Description
2	0x05	Bit 0 (LE Limited Discoverable Mode) SHOULD be set to 1 Bit 1 (LE General Discoverable Mode) SHOULD be set to 0 Bit 2 (BR/EDR Not Supported) set to 1
3	0x0E	AD[1] Length == 14 bytes
4	0x16	AD[1] Type == 0x16 (Service Data - 16-bit UUID)
5-6	0xF6, 0xFF	16-bit Matter UUID assigned by Bluetooth SIG
7	0x01	Matter BLE OpCode == 0x01 (Network Recovery mode)
8	0x00	Bits[7:4] == 0x0 (Advertisement version) Bits[3:0] == 0x0 (reserved for future use)
9-16	0x11, 0x22, 0x33, 0x44 0x55, 0x66, 0x77, 0x88	64-bit Recovery ID 11 22 33 44 55 66 77 88
17	0x00	Bit[0] == 0 (GATT-based Additional Data Flag not present) Bits[7:1] clear (reserved for future use)

5.4.2.5.7. GATT-based Additional Data

When the Additional Data Flag is set in the Matter Service Data in the BLE Advertisement, the commissioner MAY access additional commissioning-related data via an unencrypted read-only GATT characteristic C3 (see [Table 34, “BTP GATT service”](#)).

The value of the C3 characteristic SHALL be set to the Extended Data payload of the Discovery Information (see [Section 5.4.2.4.4, “Extended Data”](#)).

5.4.2.6. Using Wi-Fi Public Action Frame

This section provides details of how a device announces its commissionable status using Wi-Fi Public Action Frame. As required in [Section 5.4.2.2, “Announcement Commencement”](#), Nodes currently commissioned into one or more fabrics or already connected to an IP-bearing network SHALL NOT employ this method.

5.4.2.6.1. Device Role

Commissionable devices SHALL implement the role of a publisher in Wi-Fi Alliance Unsynchronized Service Discovery ([WFA-USD](#)).

5.4.2.6.2. Channels

The Commissionable device advertises itself on channel 6 in the 2.4 GHz frequency band, which is the Default Publish Channel in [WFA-USD](#). Additionally, the Commissionable device also advertises