

choose either channel 44 or channel 149 in the 5 GHz band for the subscribe instance, whichever is permitted with a higher transmission power based on the regulatory domain. Access Points as Commissioners can choose to create subscribe instance on any operating channel, including Dynamic Frequency Selection channels.

When the Commissioner discovers the `_matterc._udp` service name published by a Commissionable device, and the Commissioner uniquely identifies the Commissionable device through [12-bit discriminator](#) or [Extended Data](#), then the Commissioner MAY proceed with the commissioning flow (see [Section 5.5, “Commissioning Flows”](#)). When commissioning over Wi-Fi Public Action Frame, the Commissioner SHALL use concurrent connection commissioning flow. Any Commissionable device supporting Wi-Fi Public Action Frame commissioning SHALL support concurrent connection commissioning flow, indicating this capability in the [SupportsConcurrentConnection](#) attribute of the [General Commissioning Cluster](#).

During commissioning flow, the Commissioner and the Commissionable device SHALL use [WFA-USD](#) Service Discovery Frame (SDF) Follow-up messages to transport Matter messages until the Commissionable device joins the operational network. When a [WFA-USD](#) SDF Follow-up message is used to transport a Matter message, the Service Info field of the Service Descriptor Extension Attribute included in the Wi-Fi USD Follow-up message SHALL be used to encapsulate the Matter message. The value of its Service Protocol Type field SHALL be set to '3' to indicate [Matter](#), and its Service Specific Info field SHALL carry the Matter message sent by the Commissionable device or the Commissioner.

5.4.3.3. Using Existing IP-bearing Network

To discover a commissionable device over an existing IP-bearing network connection, the Commissioner SHALL perform service discovery using DNS-SD as detailed in [Section 4.3, “Discovery”](#), and more specifically in [Section 4.3.1, “Commissionable Node Discovery”](#).

5.4.3.4. Using NFC Transport Layer

To discover a commissionable device over NFC interface, the user needs to bring the Commissioner in close proximity to the Commissionee, and the Commissioner SHALL follow the activities defined for POLL Mode in [NFC Forum Activity](#).

5.5. Commissioning Flows

There are two commissioning flows depending upon the networking capability of the Commissioner and Commissionee, namely concurrent connection commissioning flow and non-concurrent connection commissioning flow.

For additional security requirements related to commissioning flows, refer to [Section 13.6, “Security Best Practices”](#).

A Commissioner and Commissionee with concurrent connection have the ability to maintain two network connections simultaneously. One connection is between the Commissioner (or Commissionee) and the operational network (e.g., home Wi-Fi network or Thread network) that the Commissionee is being programmed to join. The second connection is between the Commissioner and Commissionee for commissioning as is referred to as commissioning channel. A Commissioner and