

```

id-sha256 OBJECT IDENTIFIER ::= {
    joint-iso-itu-t(2) country(16) us(840) organization(1) gov(101)
    csor(3) nistAlgorithms(4) hashalgs(2) 1
}

-- Below is an example value for the above exemplary FirmwareInformation

firmwareInformation FirmwareInformation ::= {
    -- The firmwareDigests contain two values, for two separate components.
    firmwareDigests {
        {
            digestAlgorithm {
                id id-sha256
            },
            digestHash '00112233445566778899AABBCCDDEEFF00112233445566778899AABBCCDDEEFF'H
        },
        {
            digestAlgorithm {
                id id-sha256
            },
            digestHash '101112131415161718191A1B1C1D1E1F101112131415161718191A1B1C1D1E1F'H
        }
    }
}

```

The above example would yield the following DER-encoded octet string:

```

30663031 300d0609 60864801 65030402 01050004 20001122 33445566 778899AA
BBCCDDEE FF001122 33445566 778899AA BBCCDDEE FF303130 0D060960 86480165
03040201 05000420 10111213 14151617 18191A1B 1C1D1E1F 10111213 14151617
18191A1B 1C1D1E1F

```

6.4. Node Operational Credentials Specification

6.4.1. Introduction

The Node Operational credentials are a collection of credentials to enable a Node to identify itself within a Fabric. The Node Operational credentials are distinct from the Device Attestation credentials. The Node Operational credentials are installed during [Commissioning](#).

The Node Operational credentials include the following items:

- [Node Operational Key Pair](#)