

```

    0: {
      Type: AttributeAccessForbidden, // access limitation for attribute
      Id: 0x0000                      // attribute 0x0000
    },
    1: {
      Type: CommandForbidden, // command limitation
      Id: NULL                // all commands
    },
    2: {
      Type: EventForbidden, // event limitation
      Id: NULL              // all events
    }
  ]
}
]
ARL: [
  0: {
    FabricIndex: 1,
    Endpoint: 1,      // application endpoint 1
    Cluster: 0x0453,   // application cluster 0x0453
    Restrictions: [
      0: {
        Type: AttributeAccessForbidden, // access limitation for attribute
        Id: 0x0000                      // attribute 0x0000
      },
      1: {
        Type: CommandForbidden, // command limitation
        Id: NULL                // all commands
      },
      2: {
        Type: EventForbidden, // event limitation
        Id: NULL              // all events
      }
    ]
  }
]
}

```

In this example, the restrictions during commissioning, expressed by the CommissioningARL attribute, include 3 limitations on Cluster 0x0453 of Endpoint 1: access to attribute 0x0000, all commands, all events. The restrictions for the fabric at FabricIndex 1, expressed by the ARL attribute, include the same 3 limitations on Cluster 0x0453 of Endpoint 1.