

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ActionID	uint16	all			M
1	InvokeID	uint32	all			O

This command enables a certain action or automation. Afterwards, the action's state SHALL be Active.

Example: enable a motion sensor to control the lights in an area.

9.14.6.10. EnableActionWithDuration Command

This command is used to enable an action with a duration.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ActionID	uint16	all			M
1	InvokeID	uint32	all			O
2	Duration	uint32	all		MS	M

This command enables a certain action or automation, and SHALL change the action's state to be Active. After the specified Duration, the action or automation will stop, and the action's state SHALL change to Disabled.

Example: enable a "presence mimicking" behavior for the lights in your home during a vacation; the Duration field is used to indicated the length of your absence from home. After that period, the presence mimicking behavior will no longer control these lights.

Duration Field

This field SHALL indicate the requested duration in seconds.

9.14.6.11. DisableAction Command

This command is used to disable an action.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ActionID	uint16	all			M
1	InvokeID	uint32	all			O

This command disables a certain action or automation, and SHALL change the action's state to Inactive.

Example: disable a motion sensor to no longer control the lights in an area.