

Bit index	Name	Requirement	UserActiveModeTriggerInstruction Dependency
11	ResetButtonTimes	The Device will enter Active Mode when reset button is pressed N times with maximum 1 second between each press. The exact value of N SHALL be made available via UserActiveModeTriggerInstruction attribute.	True
12	SetupButton	The Device will enter Active Mode when setup button is pressed.	False
13	SetupButtonSeconds	The Device will enter Active Mode when setup button is pressed for N seconds. The exact value of N SHALL be made available via the UserActiveModeTriggerInstruction attribute.	True
14	SetupButtonLightsBlink	The Device will enter Active Mode when setup button is pressed until associated light blinks. Information on color of light MAY be made available via the UserActiveModeTriggerInstruction attribute.	True
15	SetupButtonTimes	The Device will enter Active Mode when setup button is pressed N times with maximum 1 second between each press. The exact value of N SHALL be made available via the UserActiveModeTriggerInstruction attribute.	True