

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x000A	ActiveWiredFaults	list[Wired-Fault-Enum]	max 8			R V	[WIRED]
0x000B	BatVoltage	uint32	all	C X		R V	[BAT]
0x000C	BatPercentRemaining	uint8	max 200	Q X		R V	[BAT]
0x000D	Bat-TimeRemaining	uint32	all	Q X		R V	[BAT]
0x000E	BatCharge Level	BatChargeLevelEnum	desc			R V	BAT
0x000F	BatReplacement-Needed	bool	all			R V	BAT
0x0010	BatReplaceability	BatReplaceabilityEnum	all	F		R V	BAT
0x0011	BatPresent	bool	all			R V	[BAT]
0x0012	ActiveBat-Faults	list[Bat-Fault-Enum]	max 8			R V	[BAT]
0x0013	BatReplacementDescription	string	max 60	F		R V	REPLC
0x0014	BatCommonDesignation	BatCommonDesignationEnum	desc	F		R V	[REPLC]
0x0015	BatANSIDesignation	string	max 20	F		R V	[REPLC]
0x0016	BatIECDesignation	string	max 20	F		R V	[REPLC]
0x0017	BatApproved-Chemistry	BatApproved-ChemistryEnum	desc	F		R V	[REPLC]