

ThreadScanResults Field

If NetworkingStatus was Success, this field SHALL contain the Thread network scan results. The list MAY be empty if none were found in range on the bands supported by the interface.

The maximum number of results present in the result list supported MAY depend on memory and MAY contain a subset of possibilities, to avoid memory exhaustion on the cluster server and avoid crossing the maximum command response size supported (see [Section 4.4.4, “Message Size Requirements”](#)).

The order in which results are reported is implementation-specific. Results SHOULD be reported in decreasing LQI order, to maximize the likelihood that most likely to be reachable elements are included within the size limits of the response.

11.9.7.3. AddOrUpdateWiFiNetwork Command

This command is used to add or update a Wi-Fi network configuration.

This command SHALL be used to add or modify Wi-Fi network configurations.

If this command is received without an armed fail-safe context (see [Section 11.10.7.2, “ArmFail-Safe”](#)), then this command SHALL fail with a FAILSAFE_REQUIRED status code sent back to the initiator.

The Credentials associated with the network are not readable after execution of this command, as they do not appear in the [Section 11.9.6.2, “Networks”](#) attribute, for security reasons.

If this command contains a ClientIdentifier, and the [Section 11.9.6.2, “Networks”](#) list does not contain an entry with a matching ClientIdentifier, then this command SHALL fail with a status of NOT_FOUND.

See [Section 11.9.7.5, “Common processing of AddOrUpdateWiFiNetwork and AddOrUpdateThreadNetwork”](#) for behavior of addition/update.

ID	Name	Type	Constraint	Fallback	Conformance
0	SSID	octstr	max 32		M
1	Credentials	octstr	max 64		M
2	Breadcrumb	uint64	all		O

SSID Field

This field SHALL contain the SSID to which to attempt connection. Specific BSSID selection is not supported by this cluster.

Credentials Field

Credentials is the passphrase or PSK for the network (if any is needed).

Security type, cipher and credential format (passphrase or PSK) SHALL be contextually auto-selected during execution of the [ConnectNetwork](#) command and during subsequent operational