

requests. The attribute SHALL only be incremented by 1 for each broadcast MAC transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.26. TxAckRequestedCount Attribute

This attribute SHALL indicate the total number of unique MAC frame transmission requests with requested acknowledgment. The attribute SHALL only be incremented by 1 for each MAC transmission request with requested acknowledgment regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.27. TxAckedCount Attribute

This attribute SHALL indicate the total number of unique MAC frame transmission requests that were acked. The attribute SHALL only be incremented by 1 for each MAC transmission request that is acked regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.28. TxNoAckRequestedCount Attribute

This attribute SHALL indicate the total number of unique MAC frame transmission requests without requested acknowledgment. The attribute SHALL only be incremented by 1 for each MAC transmission request that is does not request acknowledgement regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions.

11.14.6.29. TxDataCount Attribute

This attribute SHALL indicate the total number of unique MAC Data frame transmission requests. The attribute SHALL only be incremented by 1 for each MAC Data frame transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.30. TxDataPollCount Attribute

This attribute SHALL indicate the total number of unique MAC Data Poll frame transmission requests. The attribute SHALL only be incremented by 1 for each MAC Data Poll frame transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.31. TxBeaconCount Attribute

This attribute SHALL indicate the total number of unique MAC Beacon frame transmission requests. The attribute SHALL only be incremented by 1 for each MAC Beacon frame transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions.

11.14.6.32. TxBeaconRequestCount Attribute

This attribute SHALL indicate the total number of unique MAC Beacon Request frame transmission requests. The attribute SHALL only be incremented by 1 for each MAC Beacon Request frame transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions.