

This value SHALL only be reset upon a Node reboot.

11.14.6.33. TxOtherCount Attribute

This attribute SHALL indicate the total number of unique MAC frame transmission requests that are not counted by any other attribute. The attribute SHALL only be incremented by 1 for each MAC frame transmission request regardless of the amount of CCA failures, CSMA-CA attempts, or retransmissions. This value SHALL only be reset upon a Node reboot.

11.14.6.34. TxRetryCount Attribute

This attribute SHALL indicate the total number of MAC retransmission attempts. The attribute SHALL only be incremented by 1 for each retransmission attempt that may be triggered by lack of acknowledgement, CSMA/CA failure, or other type of transmission error. This value SHALL only be reset upon a Node reboot.

11.14.6.35. TxDirectMaxRetryExpiryCount Attribute

This attribute SHALL indicate the total number of unique MAC transmission packets that meet maximal retry limit for direct packets. The attribute SHALL only be incremented by 1 for each unique MAC transmission packets that meets the maximal retry limit for direct packets. This value SHALL only be reset upon a Node reboot.

11.14.6.36. TxIndirectMaxRetryExpiryCount Attribute

This attribute SHALL indicate the total number of unique MAC transmission packets that meet maximal retry limit for indirect packets. The attribute SHALL only be incremented by 1 for each unique MAC transmission packets that meets the maximal retry limit for indirect packets. This value SHALL only be reset upon a Node reboot.

11.14.6.37. TxErrCcaCount Attribute

This attribute SHALL indicate the total number of CCA failures. The TxErrCcaCount attribute SHALL only be incremented by 1 for each instance of a CCA failure. This value SHALL only be reset upon a Node reboot.

11.14.6.38. TxErrAbortCount Attribute

This attribute SHALL indicate the total number of unique MAC transmission request failures caused by an abort error. The attribute SHALL only be incremented by 1 for each unique MAC transmission request failure caused by an abort error.

11.14.6.39. TxErrBusyChannelCount Attribute

This attribute SHALL indicate the total number of unique MAC transmission request failures caused by an error as the result of a busy channel (a CSMA/CA fail). The attribute SHALL only be incremented by 1 for each unique MAC transmission request failure caused by a busy channel such as a CSMA/CA failure.