

The format of the new Access Control Entry, created from this, SHALL be:

```
{
  FabricIndex: **FabricIndex derived from current or new Fabric**,
  Privilege: Administer,
  AuthMode: CASE,
  Subjects: [**CaseAdminSubject provided in the AddNOC command**],
  Targets: [],      // entire node
  Extension: []     // empty
}
```

**NOTE**

Unless such an Access Control Entry is added atomically as described here, there would be no way for the caller on its given Fabric to eventually add another [Access Control Entry](#) for CASE authentication mode, to enable the new Administrator to administer the device, since the [Fabric Scoping](#) of the Access Control List prevents the current Node from being able to write new entries scoped to that Fabric, if the session is established from [CASE](#). While a session established from [PASE](#) does gain Fabric Scope of a newly-joined Fabric, this argument is made mandatory to provide symmetry between both types of session establishment, both of which need to eventually add an "Administer Node over CASE" Access Control Entry to finalize new Fabric configuration and subsequently be able to call the [CommissioningComplete](#) command.

**AdminVendorID Field**

This field SHALL be set to the [Vendor ID](#) of the entity issuing the AddNOC command. This value SHALL NOT be one of the reserved Vendor ID values defined in [Table 1, "Vendor ID Allocations"](#).

**Effect on Receipt**

If this command is received without an armed fail-safe context (see [Section 11.10.7.2, "ArmFail-Safe"](#)), then this command SHALL fail with a FAILSAFE\_REQUIRED status code sent back to the initiator.

If a prior UpdateNOC or AddNOC command was successfully executed within the fail-safe timer period, then this command SHALL fail with a CONSTRAINT\_ERROR status code sent back to the initiator.

If the prior [CSRRequest](#) state that preceded AddNOC had the IsForUpdateNOC field indicated as true, then this command SHALL fail with a CONSTRAINT\_ERROR status code sent back to the initiator.

If no prior [AddTrustedRootCertificate](#) command was successfully executed within the fail-safe timer period, then this command SHALL process an error by responding with a [NOCResponse](#) with a StatusCode of [InvalidNOC](#) as described in [Section 11.18.6.7.2, "Handling Errors"](#). In other words, AddNOC always requires that the client provides the root of trust certificate within the same Fail-Safe context as the rest of the new fabric's operational credentials, even if some other fabric