

period, then this command SHALL fail with a `CONSTRAINT_ERROR` status code sent back to the initiator, since the only valid following logical operation is invoking the [AddNOC](#) command.

If the prior [CSRRequest](#) state that preceded UpdateNOC had the `IsForUpdateNOC` field indicated as false, then this command SHALL fail with a `CONSTRAINT_ERROR` status code sent back to the initiator.

If any of the following conditions arise, the Node SHALL process an error by responding with an [NOCResponse](#) with a `StatusCode` of [InvalidNOC](#) as described in [Section 11.18.6.7.2, “Handling Errors”](#):

- The NOC provided in the `NOCValue` does not refer in its subject to the [FabricID](#) associated with the [accessing fabric](#).
- The ICAC provided in the `ICACValue` (if present) has a `FabricID` in its subject that does not match the [FabricID](#) associated with the [accessing fabric](#).

Otherwise, the command is considered an update of existing credentials for a given Fabric, and the following SHALL apply:

1. The Operational Certificate under the [accessing fabric index](#) in the [NOCs](#) list SHALL be updated to match the incoming `NOCValue` and `ICACValue` (if present), such that the Node's Operational Identifier within the Fabric immediately changes.
 - a. The operational key pair associated with the incoming NOC from the `NOCValue`, and generated by the prior [CSRRequest](#) command, SHALL be committed to permanent storage, for subsequent use during [CASE](#).
 - b. The [operational discovery](#) service record SHALL immediately reflect the new Operational Identifier.
 - c. All internal data reflecting the prior operational identifier of the Node within the Fabric SHALL be revoked and removed, to an outcome equivalent to the disappearance of the prior Node, except for the ongoing [CASE](#) session context, which SHALL temporarily remain valid until the [NOCResponse](#) has been successfully delivered or until the next transport-layer error, so that the response can be received by the Administrator invoking the command.

Thereafter, the Node SHALL respond with an [NOCResponse](#) with a `StatusCode` of OK and a `FabricIndex` field matching the `FabricIndex` under which the updated [NOC](#) is scoped.

11.18.6.10. NOCResponse Command

This command is used to report the results of the [AddNOC](#), [UpdateNOC](#), [UpdateFabricLabel](#) and [RemoveFabric](#) commands.

This command SHALL be generated in response to the following commands:

- [AddNOC](#)
- [UpdateNOC](#)
- [UpdateFabricLabel](#)
- [RemoveFabric](#)