

Label Field

This field SHALL contain the label to set for the fabric associated with the current secure session.

Effect on Receipt

If the Label field is identical to a Label already in use by a Fabric within the [Fabrics](#) list that is not the [accessing fabric](#), then an NOCResponse with a StatusCode of [LabelConflict](#) SHALL be returned for the command and there SHALL NOT be any permanent changes to any Fabric data.

Otherwise, the Label field for the accessing fabric SHALL immediately be updated to reflect the Label argument provided. Following the update, an NOCResponse with a StatusCode of OK SHALL be returned.

If the command was invoked within a fail-safe context after a successful [UpdateNOC](#) command, then the label update SHALL apply to the pending update state that will be reverted if fail-safe expires prior to a [CommissioningComplete](#) command. In other words, label updates apply to the state of the [Fabrics Attribute](#) as currently visible, even for an existing fabric currently in process of being updated.

11.18.6.12. RemoveFabric Command

This command is used to remove a Fabric from the device.

This command is used by Administrators to remove a given Fabric and **delete all associated fabric-scoped data**.

If the given Fabric being removed is the last one to reference a given [Trusted Root CA Certificate](#) stored in the [Trusted Root Certificates](#) list, then that Trusted Root Certificate SHALL be removed.

WARNING

This command, if referring to an already existing Fabric not under the control of the invoking Administrator, SHALL ONLY be invoked after obtaining some form of explicit user consent through some method executed by the Administrator or Commissioner. This method of obtaining consent SHOULD employ as much data as possible about the existing Fabric associations within the [Fabrics](#) list, so that likelihood is as small as possible of a user removing a Fabric unwittingly. If a method exists for an Administrator or Commissioner to convey Fabric Removal to an entity related to that Fabric, whether in-band or out-of-band, then this method SHOULD be used to notify the other Administrative Domain's party of the removal. Otherwise, users may only observe the removal of a Fabric association as persistently failing attempts to reach a Node operationally.

NOTE

If the Administrator intends to remove a fabric over a [CASE](#) session, the RevokeCommissioning command of the [AdministratorCommissioning Cluster](#) SHOULD be invoked before removal of the fabric and, if the removal is successful, also after the removal of the fabric. This serves as a security measure to prevent a malicious fabric administrator from re-adding themselves through an open commissioning window after being removed.