

sages.

Transfer control (TC)

The Transfer Control (TC) field specifies, as subfields, the transfer mode and protocol version.

For the transfer mode (TC[SENDER_DRIVE], TC[RECEIVER_DRIVE]), exactly one mode SHALL be chosen for this transfer, which SHALL be one of the original proposed transfer methods sent by the Initiator.

The version SHALL be the newest version that is supported by the Responder and is not newer than the proposed version sent by the Initiator. If the Responder cannot support a version equal or older to the [proposed version](#), the Responder SHALL send a `StatusReport(GeneralCode: FAILURE, ProtocolId: BDX_, ProtocolCode: VERSION_NOT_SUPPORTED)` to end the transfer.

The Responder MAY reject a proposed asynchronous transfer (PTC[ASYNC] = 1) by sending a `StatusReport(GeneralCode: FAILURE, ProtocolId: BDX, ProtocolCode: TRANSFER_METHOD_NOT_SUPPORTED)` to end the transfer. If the Initiator proposed both the PTC[RECEIVER_DRIVE] and PTC[SENDER_DRIVE], the Responder SHALL select exactly one of those options. In that case, to retain the request/response semantics, the Responder SHALL default to TC[SENDER_DRIVE].

Table 115. SendAccept/ReceiveAccept Transfer Control (TC) field structure

bit 7	6	5	4	3	2	1	0
RFU	ASYNC	RECEIVER_DRIVE	SENDER_DRIVE	VERSION			

The fields for TC are:

SendAccept/ReceiveAccept TC[VERSION]: protocol version

- Width: 4 bits
- Values: 0x00-0x0F accepted protocol version

SendAccept/SendAccept TC[SENDER_DRIVE]: sender drive enabled

- Width: 1 bit
- Values:
 - 0 if Sender drive was not chosen
 - 1 if Sender drive was chosen (if this is set, TC[RECEIVER_DRIVE] SHALL be 0)

SendAccept/ReceiveAccept TC[RECEIVER_DRIVE]: receiver drive enabled

- Width: 1 bit
- Values:
 - 0 if Receiver drive was not chosen
 - 1 if Receiver drive was chosen (if this is set, TC[SENDER_DRIVE] SHALL be 0)