

11.23.6.25. EnhancedSetupFlowTCFileSize

This field (when provided) SHALL indicate the total size of the Enhanced Setup Flow Terms and Conditions file in bytes, and SHALL be used to ensure the downloaded file size is within the bounds of EnhancedSetupFlowTCFileSize. This field SHALL be provided if and only if the EnhancedSetupFlowTCUrl field is present.

11.23.6.26. EnhancedSetupFlowMaintenanceUrl

This field (when provided) SHALL identify a link to a vendor-specific URL which SHALL provide a manufacturer specific means to resolve any functionality limitations indicated by the TERMS_AND_CONDITIONS_CHANGED status code. This field SHALL be present if the EnhancedSetupFlowOptions field has bit 0 set. During the lifetime of the product, the specified URL SHOULD resolve to a maintained web page. The syntax of this field SHALL follow the syntax as specified in [RFC 1738](#). The maximum length of this field is 256 ASCII characters. All URLs SHALL use the [https](#) scheme.

11.23.6.27. IcdUserActiveModeTriggerHint

This field (when provided) is applicable to an [ICD](#) that supports the [UserActiveModeTrigger](#) feature. This field SHALL indicate which user action(s) will trigger the ICD to switch to Active mode. This field SHALL follow the requirements specified in [UserActiveModeTriggerHint](#).

11.23.6.28. IcdUserActiveModeTriggerInstruction

This field (when provided) is applicable to an [ICD](#) that supports the [UserActiveModeTrigger](#) feature. The meaning of this field is dependent upon the [UserActiveModeTriggerHint](#) field value, and the conformance is indicated in the "dependency" column in [UserActiveModeTriggerHint table](#). This field SHALL follow the requirements specified in [UserActiveModeTriggerInstruction](#).

11.23.6.29. FactoryResetStepsHint

This field (when provided) SHALL identify a hint for the steps that MAY be used to factory reset a device. This field is a bitmap with values defined in the [Pairing/Reset Hint Table](#). For example, a value of 64 (bit 6 is set) indicates that a device will be factory reset when the Reset Button is pressed.

11.23.6.30. FactoryResetStepsInstruction

This field SHALL be populated with the appropriate factory reset instruction for those values of FactoryResetStepsHint, for which the [Pairing/Reset Hint Table](#) indicates a dependency in the Instruction Dependency column.

11.23.7. DeviceSoftwareVersionModel Schema

A unique combination of the VendorID, ProductID and SoftwareVersion is used to identify a DeviceSoftwareVersionModel. The record schema available to vendors to provide information specific to a particular software version for a given product is presented below.