

been executed using NFC-based commissioning, SHALL actively inform a user about devices not appearing on the operational network in the second phase, allowing a user to detect potential re-commissioning over NFC by unauthorized users. [CM276 for T255]

- g. After initial Commissioning of a Device, subsequent Commissioning SHALL only be triggered by an Administrator or an equivalent entity where the user gives administrative consent. [CM2 for T1]

13.4. Factory Reset

- a. Devices and Nodes SHALL have a factory reset capability. [CM15 for T16, T17, T79, T82]
- b. Factory reset SHALL remove from the Node all security- and privacy-related data and key material created during or after commissioning except data explicitly required to persist across resets. [CM35 for T16, T17, T79, T82]

See the following sections for detailed factory reset requirements.

- [Section 6.4.3, “Node Operational Identifier Composition”](#)
- [Section 6.4.11, “Security Considerations”](#)
- [Section 6.6.3, “Access Control List Examples”](#)
- [Section 7.12.1, “Persistence”](#)
- [Section 7.14, “Event”](#)
- [Section 11.12, “General Diagnostics Cluster”](#)
- [Section 11.20.4.2, “Image Verification”](#)
- [NOCs](#)
- [Fabrics](#)
- [CommissionedFabrics](#)
- [TrustedRootCertificates](#)

13.5. Firmware

- a. Nodes SHALL support OTA firmware updates, either using Matter-provided means (see [Section 11.20, “Over-the-Air \(OTA\) Software Update”](#)) or proprietary means. [CM58 for T59, T226]
- b. Nodes SHALL validate the authenticity and integrity of the firmware prior to installation, such as through cryptographic means (see [Section 11.20.4.2, “Image Verification”](#)). [CM58 for T59, T226]
- c. Nodes SHOULD validate configuration and input for length, and acceptable values and ranges before applying them. This validation is dependent on the configuration or input being applied (see [Section 9.10, “Access Control Cluster”](#)). Configuration and input validation is explicitly defined in relevant sections of the specification. [CM46 for T55]