

D.3.1. General status codes (**GeneralCode**)

General status codes conveyed in the **GeneralCode** field are uniform codes that convey both success and failures.

The following general status codes are defined:

Code	Numeric Value	Description
SUCCESS	0	Operation completed successfully.
FAILURE	1	Generic failure, additional details may be included in the <i>protocol specific status</i> .
BAD_PRECONDITION	2	Operation was rejected by the system because the system is in an invalid state.
OUT_OF_RANGE	3	A value was out of a required range
BAD_REQUEST	4	A request was unrecognized or malformed
UNSUPPORTED	5	An unrecognized or unsupported request was received
UNEXPECTED	6	A request was not expected at this time
RESOURCE_EXHAUSTED	7	Insufficient resources to process the given request
BUSY	8	Device is busy and cannot handle this request at this time
TIMEOUT	9	A timeout occurred
CONTINUE	10	Context-specific signal to proceed
ABORTED	11	Failure, may be due to a concurrency error.
INVALID_ARGUMENT	12	An invalid/unsupported argument was provided
NOT_FOUND	13	Some requested entity was not found
ALREADY_EXISTS	14	The sender attempted to create something that already exists
PERMISSION_DENIED	15	The sender does not have sufficient permissions to execute the requested operations.
DATA_LOSS	16	Unrecoverable data loss or corruption has occurred.
MESSAGE_TOO_LARGE	17	Message size is larger than the recipient can handle.

If none of the specific codes above fits for application usage, a protocol SHALL use *FAILURE* and provide more information encoded in the **ProtocolId** and **ProtocolCode** subfields.

D.3.2. Protocol-specific codes (**ProtocolId** and **ProtocolCode**)

The protocol-specific portion of StatusReport messages is composed of a fully-qualified **ProtocolId** which qualifies the subsequent **ProtocolCode** space.

The **ProtocolId** is encoded as a 32 bit value of **Protocol Vendor ID** (upper 16 bits) and **Protocol ID**