

Cur- rentLevel	EiO	OnOff	Physical Device	Com- mand Before After	Cur- rentLevel	OnOff	Physical Device	Device Output Result
<i>any</i>	1	FALSE	Off	Move- With- OnOff(up, rate=64/s)	<i>MAX</i>	TRUE	On	Turn on and out- put level adjusts to or stays at full
<i>any</i>	1	FALSE	Off	Move- With- OnOff(do wn, rate=64/s)	<i>MIN</i>	FALSE	Off	Stays off
<i>any</i>	<i>any</i>	TRUE	On (any bright- ness)	Move- ToLevel- With- OnOff(l= <i>MID</i> , t=2 sec)	<i>MID</i>	TRUE	On (mid- point bright- ness)	Output level adjusts to or stays at half
<i>any</i>	<i>any</i>	TRUE	On (any bright- ness)	Move- With- OnOff(up, rate=64/s)	<i>MAX</i>	TRUE	On (full bright- ness)	Output level adjusts to or stays at full
<i>any</i>	<i>any</i>	TRUE	On (any bright- ness)	Move(do wn, rate=64/s)	<i>MIN</i>	TRUE	On (at minimum bright- ness)	Output level adjusts to minimum
<i>any</i>	<i>any</i>	TRUE	On (any bright- ness)	Move- With- OnOff(do wn, rate=64/s)	<i>MIN</i>	FALSE	Off	Output level adjusts to off

1.7. Boolean State Cluster

This cluster provides an interface to a boolean state.

1.7.1. Revision History

The global ClusterRevision attribute value SHALL be the highest revision number in the table below.