

user has become aware that the sensor is triggered, but it is no longer desired to have the alarm modes active on the device, e.g.:

- The triggering cause have been resolved by the user, but the sensor has not yet stopped detecting the triggering cause.
- The user is not able to address the triggering cause, but is aware of the alarm and suppress/acknowledge it be addressed at a later point.

Acknowledge of alarms will for the remainder of this cluster be referred to as suppress.

A suppressed alarm is still considered active and will remain so unless it is actively disabled or the triggering condition is not longer present. The action of suppressing an alarm mode is only applicable to and is intended to stop the physical alarming, e.g. emitting a sound or blinking a light; it does not impact alarm reporting in AlarmsActive.

1.8.5. Data Types

1.8.5.1. AlarmModeBitmap Type

This data type is derived from map8.

Bit	Name	Summary	Conformance
0	Visual	Visual alarming	VIS
1	Audible	Audible alarming	AUD

1.8.5.2. SensorFaultBitmap Type

This data type is derived from map16.

Bit	Name	Summary	Conformance
0	GeneralFault	Unspecified fault detected	M

1.8.6. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	CurrentSensitivityLevel	uint8	max (SupportedSensitivityLevels - 1)	N		RW VO	SENSLVL
0x0001	SupportedSensitivityLevels	uint8	2 to 10	F		R V	SENSLVL