

semantic tag defined by the manufacturer. Each manufacturer code supports a single namespace of values. The same manufacturer code and semantic tag value in separate cluster instances are part of the same namespace and have the same meaning. For example: a manufacturer tag meaning "pinch", has the same meaning in a cluster whose purpose is to choose the amount of sugar, or amount of salt.

1.9.5.2. ModeOptionStruct Type

This is a struct representing a possible mode of the server.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	Label	string	max 64	F	MS		M
1	Mode	uint8		F	MS		M
2	Semantic-Tags	list[SemanticTagStruct]	max 64	F	MS		M

1.9.5.2.1. Label Field

This field is readable text that describes the mode option that can be used by a client to indicate to the user what this option means. This field is meant to be readable and understandable by the user.

1.9.5.2.2. Mode Field

The Mode field is used to identify the mode option. The value SHALL be unique for every item in the SupportedModes attribute.

1.9.5.2.3. SemanticTags Field

This field is a list of semantic tags that map to the mode option. This MAY be used by clients to determine the meaning of the mode option as defined in a standard or manufacturer specific namespace. Semantic tags can help clients look for options that meet certain criteria. A semantic tag SHALL be either a standard tag or manufacturer specific tag as defined in each [SemanticTagStruct](#) list entry.

A mode option MAY have more than one semantic tag. A mode option MAY be mapped to a mixture of standard and manufacturer specific semantic tags.

All standard semantic tags are from a single namespace indicated by the StandardNamespace attribute.

For example: A mode labeled "100%" can have both the **HIGH** (MS) and **MAX** (standard) semantic tag. Clients seeking the option for either **HIGH** or **MAX** will find the same option in this case.

1.9.6. Attributes