

mode tag. Clients seeking the mode for either High or Max will find the same mode in this case.

- A mode that includes a LowEnergy tag can be displayed by the client using a widget icon that shows a green leaf.
- A mode that includes a LowNoise tag may be used by the client when the user wishes for a lower level of audible sound, less likely to disturb the household's activities.
- A mode that includes a LowEnergy tag (standard, defined in this cluster specification) and also a Delicate tag (standard, defined in the namespace of a Laundry Mode derived cluster).
- A mode that includes both a generic Quick tag (defined here), and Vacuum and Mop tags, (defined in the RVC Clean cluster that is a derivation of this cluster).

1.10.6. Attributes

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x0000	SupportedModes	list[ModeOptionStruct]	2 to 255	F		R V	M
0x0001	CurrentMode	uint8	desc	N		R V	M
0x0002	StartupMode	uint8	desc	N X	MS	RW VO	O
0x0003	OnMode	uint8	desc	N X		RW VO	DEP ON OFF

1.10.6.1. SupportedModes Attribute

This attribute SHALL contain the list of supported modes that may be selected for the CurrentMode attribute. Each item in this list represents a unique mode as indicated by the Mode field of the [ModeOptionStruct](#).

Each entry in this list SHALL have a unique value for the Mode field.

Each entry in this list SHALL have a unique value for the Label field.

The set of ModeTags listed in each entry in this list SHALL be distinct from the sets of ModeTags listed in the other entries. This comparison SHALL NOT depend on the order of the ModeTags in the lists. Two sets SHALL be considered distinct if one of them contains an element that the other one does not. Note that the two sets could have a non-empty intersection, or one could be a subset of the other, and still be distinct.

Simplified examples of allowed ModeTags lists:

SupportedModes Index	Simplified mode tag list	Reason
0	Cool	Subset is ok