

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	NewPosition	uint8	0 to (NumberOfPositions - 1)			M

1.13.6.2.1. NewPosition Field

This field SHALL indicate the new value of the CurrentPosition attribute, i.e. while pressed.

1.13.6.3. LongPress Event

This event SHALL be generated when the momentary switch has been pressed for a "long" time. The time interval constituting a "long" time is manufacturer-determined, since it depends on the switch physics.

- When the AS feature flag is set, this event:
 - SHALL NOT be generated during a multi-press sequence (since a long press is a separate cycle from any multi-press cycles);
 - SHALL only be generated after the first InitialPress following a MultiPressComplete when a long press is detected after the idle time.
- Else, when the MSM feature flag is set, this event:
 - SHALL NOT be generated during a multi-press sequence (since a long press is a separate cycle from any multi-press cycles);
 - SHALL only be generated after the first InitialPress following a MultiPressComplete when a long press is detected after the idle time;
 - SHALL NOT be generated after a MultiPressOngoing event without an intervening MultiPressComplete event.

The above constraints imply that for a given activity detection cycle of a switch having MSM and/or MSL feature flags set, the entire activity is either a single long press detection cycle of (InitialPress, LongPress, LongRelease), or a single multi-press detection cycle (ending in MultiPressComplete), where presses that would otherwise be reported as long presses are instead reported as a counted press in the MultiPressComplete event, and as InitialPress/ShortRelease pairs otherwise (where applicable).

The rationale for this constraint is the ambiguity of interpretation of events when mixing long presses and multi-press events.

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	NewPosition	uint8	0 to (NumberOfPositions - 1)			M