

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PreviousPosition	uint8	0 to (NumberOfPositions - 1)			M
1	TotalNumberOfPressesCounted	uint8	max MultiPressMax			M

The PreviousPosition field SHALL indicate the previous value of the CurrentPosition attribute, i.e. just prior to release.

The TotalNumberOfPressesCounted field SHALL contain:

- a value of 0 when there was an aborted multi-press sequence, where the number of presses goes beyond MultiPressMax presses,
- a value of 1 when there was exactly one press in a multi-press sequence (and the sequence has ended), i.e. there was no double press (or more),
- a value of 2 when there were exactly two presses in a multi-press sequence (and the sequence has ended),
- a value of 3 when there were exactly three presses in a multi-press sequence (and the sequence has ended),
- a value of N when there were exactly N presses in a multi-press sequence (and the sequence has ended).

NOTE

The introduction of TotalNumberOfPressesCounted supporting the value 0 MAY impact clients of switches using cluster revision 1 since such servers would not use this value of TotalNumberOfPressesCounted to indicate an aborted sequence. Clients SHOULD always act using the TotalNumberOfPressesCounted field taken into account since for values from 1 to MultiPressMax, the user action that led to the event was different depending on the count.

1.13.7. Sequence of generated events

This section describes the sequence of events that will be generated by three types of momentary switches (distinguished by their feature flags). For each switch type, we will define the sequence of generated events for these three interactions:

1. Sequence for a switch which is pressed briefly.
2. Sequence for a switch pressed for a long time.
3. Sequence for a switch pressed for a very long time.

In the three interactions described in the subsections below, if the NumberOfPositions attribute is equal to 2, the InitialPress and LongPress events have the NewPosition field set to 1 and the ShortRelease and LongRelease events have the PreviousPosition field set to 1. For larger values of the