

On a SUCCESS case, the server SHALL also change the value of the Mask attribute to the value of the Mask field from this command. After that the server SHALL also update the value of its State attribute to reflect the status of the new alarm set as indicated by the new value of the Mask attribute.

1.15.8. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	Notify	INFO		V	M

1.15.8.1. Notify Event

This event SHALL be generated when one or more alarms change state.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Active	Alarm-Bitmap	all			M
1	Inactive	Alarm-Bitmap	all			M
2	State	Alarm-Bitmap	all			M
3	Mask	Alarm-Bitmap	all			M

1.15.8.1.1. Active Field

This field SHALL indicate those alarms that have become active.

1.15.8.1.2. Inactive Field

This field SHALL indicate those alarms that have become inactive.

1.15.8.1.3. Mask Field

This field SHALL be a copy of the Mask attribute when this event was generated.

1.15.8.1.4. State Field

This field SHALL be a copy of the new State attribute value that resulted in the event being generated. That is, this field SHALL have all the bits in Active set and SHALL NOT have any of the bits in Inactive set.

1.16. Messages Cluster

This cluster provides an interface for passing messages to be presented by a device.