

1.16.5.5.3. MessageControl Field

This field SHALL indicate control information related to the message.

1.16.5.5.4. StartTime Field

This field SHALL indicate the time in UTC at which the message becomes available to be presented. A null value SHALL indicate "now."

1.16.5.5.5. Duration Field

This field SHALL indicate the amount of time, in milliseconds, after the [StartTime](#) during which the message is available to be presented. A null value SHALL indicate "until changed".

1.16.5.5.6. MessageText Field

This field SHALL indicate a string containing the message to be presented.

1.16.5.5.7. Responses Field

This field SHALL indicate a list of potential responses to the message. The entries in this list SHALL have unique values of MessageResponseID.

If the [ResponseRequired](#) bit is set on the message but this list is empty, the device SHALL provide a generic acknowledgement button, e.g. "OK".

If the [ResponseRequired](#) bit is not set on the message, this list SHALL be ignored.

1.16.5.6. MessageResponseOptionStruct Type

This represents a possible response to a message.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	MessageResponseID	uint32	min 1				M
1	Label	string	max 32				M

1.16.5.6.1. MessageResponseID Field

This field SHALL indicate a unique unsigned 32-bit number identifier for this message response option.

1.16.5.6.2. Label Field

This field SHALL indicate the text for this option; e.g. "Yes", "No", etc.

1.16.6. Attributes