

2.7.6.10. UltrasonicUnoccupiedToOccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the Ultrasonic sensor changes to its occupied state after the first detection of occupancy in the sensed area.

2.7.6.11. UltrasonicUnoccupiedToOccupiedThreshold Attribute

This attribute SHALL specify the number of occupancy detection events that must occur in the period UltrasonicUnoccupiedToOccupiedDelay, before the Ultrasonic sensor changes to its occupied state.

2.7.6.12. PhysicalContactOccupiedToUnoccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the physical contact occupancy sensor changes to its unoccupied state after detecting the unoccupied event.

2.7.6.13. PhysicalContactUnoccupiedToOccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the physical contact sensor changes to its occupied state after the first detection of the occupied event.

2.7.6.14. PhysicalContactUnoccupiedToOccupiedThreshold Attribute

This attribute SHALL specify the number of occupancy detection events that must occur in the period PhysicalContactUnoccupiedToOccupiedDelay, before the PhysicalContact sensor changes to its occupied state.

2.7.7. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	Occupancy-Changed	INFO		V	O

2.7.7.1. OccupancyChanged Event

If this event is supported, it SHALL be generated when the Occupancy attribute changes.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Occupancy	Occupancy-Bitmap				M

2.7.7.1.1. Occupancy Field

This field SHALL indicate the new value of the Occupancy attribute.

2.8. Resource Monitoring Clusters

This generic cluster provides an interface to the current condition of a resource. A resource is a