

2.11.8.5. EndOfService Event

This event SHALL be generated when the EndOfServiceAlert is set to Expired.

2.11.8.6. SelfTestComplete Event

This event SHALL be generated when the SelfTest completes, and the attribute TestInProgress changes to False.

2.11.8.7. AlarmMuted Event

This event SHALL be generated when the DeviceMuted attribute changes to Muted.

2.11.8.8. MuteEnded Event

This event SHALL be generated when DeviceMuted attribute changes to NotMuted.

2.11.8.9. InterconnectSmokeAlarm Event

This event SHALL be generated when the device hosting the server receives a smoke alarm from an interconnected sensor.

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Alarm-SeverityLevel	AlarmStateEnum	all			M

2.11.8.9.1. AlarmSeverityLevel Field

This field SHALL indicate the current value of the InterconnectSmokeAlarm attribute.

2.11.8.10. InterconnectCOAlarm Event

This event SHALL be generated when the device hosting the server receives a CO alarm from an interconnected sensor.

The data of this event SHALL contain the following information:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Alarm-SeverityLevel	AlarmStateEnum	all			M

2.11.8.10.1. AlarmSeverityLevel Field

This field SHALL indicate the current value of the InterconnectCOAlarm attribute.