

time indicated in [EndTimestamp](#).

2.12.5.2.6. ApparentEnergy Field

This field SHALL indicate the reported apparent energy.

If the [EnergyMeasurementStruct](#) represents cumulative energy, then this SHALL represent the cumulative apparent energy recorded at either the value of the [EndTimestamp](#) field or the value of the [EndSystime](#) field, or both.

If the [EnergyMeasurementStruct](#) represents periodic energy, then this SHALL represent the apparent energy recorded during the period specified by either the [StartTimestamp](#) and [EndTimestamp](#) fields, the period specified by the [StartSystime](#) and [EndSystime](#) fields, or both.

2.12.5.2.7. ReactiveEnergy Field

This field SHALL be the reported reactive energy.

If the [EnergyMeasurementStruct](#) represents cumulative energy, then this SHALL represent the cumulative reactive energy recorded at either the value of the [EndTimestamp](#) field or the value of the [EndSystime](#) field, or both.

If the [EnergyMeasurementStruct](#) represents periodic energy, then this SHALL represent the reactive energy recorded during the period specified by either the [StartTimestamp](#) and [EndTimestamp](#) fields, the period specified by the [StartSystime](#) and [EndSystime](#) fields, or both.

2.12.5.3. CumulativeEnergyResetStruct Type

This struct SHALL represent the times at which cumulative measurements were last zero, either due to initialization of the device, or an internal reset of the cumulative value.

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0	ImportedResetTimestamp	epoch-s		X	null		[IMPE]
1	ExportedResetTimestamp	epoch-s		X	null		[EXPE]
2	ImportedResetSystime	systime-ms		X	null		[IMPE]
3	ExportedResetSystime	systime-ms		X	null		[EXPE]