

## 2.13.2. Classification

| Hierarchy | Role        | Scope    | PICS Code |
|-----------|-------------|----------|-----------|
| Base      | Application | Endpoint | EPM       |

## 2.13.3. Cluster ID

| ID     | Name                         |
|--------|------------------------------|
| 0x0090 | Electrical Power Measurement |

## 2.13.4. Features

This cluster SHALL support the FeatureMap bitmap attribute as defined below.

| Bit | Code        | Feature            | Conformance | Summary                                     |
|-----|-------------|--------------------|-------------|---------------------------------------------|
| 0   | <b>DIRC</b> | DirectCurrent      | O.a+        | Supports measurement of direct current      |
| 1   | <b>ALTC</b> | AlternatingCurrent | O.a+        | Supports measurement of alternating current |
| 2   | <b>POLY</b> | PolyphasePower     | [ALTC]      | Supports polyphase measurements             |
| 3   | <b>HARM</b> | Harmonics          | [ALTC]      | Supports measurement of AC harmonics        |
| 4   | <b>PWRQ</b> | PowerQuality       | [ALTC]      | Supports measurement of AC harmonic phases  |

### 2.13.4.1. DirectCurrent Feature

This feature indicates the cluster can measure a direct current.

### 2.13.4.2. AlternatingCurrent Feature

This feature indicates the cluster can measure an alternating current.

### 2.13.4.3. PolyphasePower Feature

This feature indicates the cluster represents the collective measurements for a Polyphase power supply.