

2.13.4.4. Harmonics Feature

This feature indicates the cluster can measure the harmonics of an alternating current.

2.13.4.5. PowerQuality Feature

This feature indicates the cluster can measure the harmonic phases of an alternating current.

2.13.5. Data Types

2.13.5.1. PowerModeEnum Type

This data type is derived from enum8.

Value	Name	Summary	Conformance
0	Unknown		M
1	DC	Direct current	M
2	AC	Alternating current, either single-phase or polyphase	M

2.13.5.2. MeasurementTypeEnum Type

This data type is derived from enum16.

Value	Name	Summary	Conformance
0	Unspecified		M
1	Voltage	Voltage in millivolts (mV)	M
2	ActiveCurrent	Active current in milliamps (mA)	M
3	ReactiveCurrent	Reactive current in milliamps (mA)	M
4	ApparentCurrent	Apparent current in milliamps (mA)	M
5	ActivePower	Active power in milliwatts (mW)	M
6	ReactivePower	Reactive power in millivolt-amps reactive (mVAR)	M
7	ApparentPower	Apparent power in millivolt-amps (mVA)	M